arXiv:0809.2368v1 [math-ph] 13 Sep 2008

Zernike Basis to Cartesian Transformations

Richard J. Mathar*
Leiden Observatory, P.O. Box 9513, 2300 RA Leiden, The Netherlands
(Dated: September 16, 2008)

The radial polynomials of the 2D (circular) and 3D (spherical) Zernike functions are tabulated as powers of the radial distance. The reciprocal tabulation of powers of the radial distance in series of radial polynomials is also given, based on projections that take advantage of the orthogonality of the polynomials over the unit interval. They may play a role in the expansion of products of the polynomials into sums, which is demonstrated by some examples.

Multiplication of the polynomials by the angular bases (azimuth, polar angle) defines the Zernike functions, for which we derive and tabulate transformations to and from the Cartesian coordinate system centered at the middle of the circle or sphere.

PACS numbers: 42.15.Fr, 95.75.Pq
Keywords: Zernike Polynomial, Cartesian Transformation, Spherical Basis

I. SCOPE

The incentive of the following exercises in standard analysis is to model paths of optical rays through a turbulent atmosphere based on Snell's law, if the dielectric function is created on a computer with modes founded on a Zernike basis inside a sphere [14]. Since calculation of gradients is more tedious in curvilinear local spherical coordinates than in Cartesian coordinates, a transformation of the basis is useful.

There is sufficient similarity between the 3D and 2D Zernike functions to present both cases conjointly. The more familiar 2D Zernike functions in Noll's nomenclature are covered in Section II—although no new aspects beyond earlier work emerge [4]—and similar methodology is independently applied to the 3D case in Section III.

II. ZERNIKE CIRCLE FUNCTIONS

A. Zernike Radial Polynomials

1. Definition

We define Zernike radial polynomials in Noll's nomenclature [2, 10, 13, 16, 18, 22, 23] for $0 \le m \le n$, even $n-m$ as

$$R_n^m(r) = \sum_{s=0}^{(n-m)/2} (-1)^s \binom{n-s}{s} \binom{n-2s}{(n-m)/2-s} r^{n-2s} \tag{1}$$

$$= (-1)^{(n-m)/2} \sum_{s=0}^{(n-m)/2} (-1)^s \binom{(n+m)/2+s}{(n-m)/2-s} \binom{m+2s}{s} r^{m+2s} \tag{2}$$

$$= (-1)^a \binom{-b}{-a} r^m \, {}_2F_1\left(a, 1-b; 1+m; r^2\right) = \binom{n}{-a} r^n \, {}_2F_1\left(a, b; -n; \frac{1}{r^2}\right), \tag{3}$$

where an equivalent set of two negative parameters

$$a \equiv -(n-m)/2; \quad b \equiv -(n+m)/2 \tag{4}$$

abbreviates the notation in the context of hypergeometric series. The formulas show that each expansion coefficient can be quickly generated by multiplying two binomial integers. Following the original notation, we will not put the upper index m in R_n^m—which is not a power—into parentheses.

*URL: http://www.strw.leidenuniv.nl/~mathar; Electronic address: mathar@strw.leidenuniv.nl

```
R_0^0(r) = 1.
R_1^1(r) = r.
R_2^0(r) = -1 +2*r^2.
R_2^2(r) = r^2.
R_3^1(r) = -2*r +3*r^3.
R_3^3(r) = r^3.
R_4^0(r) = 1 -6*r^2 +6*r^4.
R_4^2(r) = -3*r^2 +4*r^4.
R_4^4(r) = r^4.
R_5^1(r) = 3*r -12*r^3 +10*r^5.
R_5^3(r) = -4*r^3 +5*r^5.
R_5^5(r) = r^5.
R_6^0(r) = -1 +12*r^2 -30*r^4 +20*r^6.
R_6^2(r) = 6*r^2 -20*r^4 +15*r^6.
R_6^4(r) = -5*r^4 +6*r^6.
R_6^6(r) = r^6.
R_7^1(r) = -4*r +30*r^3 -60*r^5 +35*r^7.
R_7^3(r) = 10*r^3 -30*r^5 +21*r^7.
R_7^5(r) = -6*r^5 +7*r^7.
R_7^7(r) = r^7.
R_8^0(r) = 1 -20*r^2 +90*r^4 -140*r^6 +70*r^8.
R_8^2(r) = -10*r^2 +60*r^4 -105*r^6 +56*r^8.
R_8^4(r) = 15*r^4 -42*r^6 +28*r^8.
R_8^6(r) = -7*r^6 +8*r^8.
R_8^8(r) = r^8.
R_9^1(r) = 5*r -60*r^3 +210*r^5 -280*r^7 +126*r^9.
R_9^3(r) = -20*r^3 +105*r^5 -168*r^7 +84*r^9.
R_9^5(r) = 21*r^5 -56*r^7 +36*r^9.
R_9^7(r) = -8*r^7 +9*r^9.
R_9^9(r) = r^9.
R_10^0(r) = -1 +30*r^2 -210*r^4 +560*r^6 -630*r^8 +252*r^10.
R_10^2(r) = 15*r^2 -140*r^4 +420*r^6 -504*r^8 +210*r^10.
R_10^4(r) = -35*r^4 +168*r^6 -252*r^8 +120*r^10.
R_10^6(r) = 28*r^6 -72*r^8 +45*r^10.
R_10^8(r) = -9*r^8 +10*r^10.
R_10^10(r) = r^10.
R_11^1(r) = -6*r +105*r^3 -560*r^5 +1260*r^7 -1260*r^9 +462*r^11.
R_11^3(r) = 35*r^3 -280*r^5 +756*r^7 -840*r^9 +330*r^11.
R_11^5(r) = -56*r^5 +252*r^7 -360*r^9 +165*r^11.
R_11^7(r) = 36*r^7 -90*r^9 +55*r^11.
R_11^9(r) = -10*r^9 +11*r^11.
R_11^11(r) = r^11.
R_12^0(r) = 1 -42*r^2 +420*r^4 -1680*r^6 +3150*r^8 -2772*r^10 +924*r^12.
R_12^2(r) = -21*r^2 +280*r^4 -1260*r^6 +2520*r^8 -2310*r^10 +792*r^12.
R_12^4(r) = 70*r^4 -504*r^6 +1260*r^8 -1320*r^10 +495*r^12.
R_12^6(r) = -84*r^6 +360*r^8 -495*r^10 +220*r^12.
R_12^8(r) = 45*r^8 -110*r^10 +66*r^12.
R_12^10(r) = -11*r^10 +12*r^12.
R_12^12(r) = r^12.
R_13^1(r) = 7*r -168*r^3 +1260*r^5 -4200*r^7 +6930*r^9 -5544*r^11 +1716*r^13.
R_13^3(r) = -56*r^3 +630*r^5 -2520*r^7 +4620*r^9 -3960*r^11 +1287*r^13.
R_13^5(r) = 126*r^5 -840*r^7 +1980*r^9 -1980*r^11 +715*r^13.
R_13^7(r) = -120*r^7 +495*r^9 -660*r^11 +286*r^13.
R_13^9(r) = 55*r^9 -132*r^11 +78*r^13.
R_13^11(r) = -12*r^11 +13*r^13.
R_13^13(r) = r^13.
```

2. Inverse Representation

The inversion of the representations (2) decomposes powers r^j into sums of $R_n^m(r)$,

$$r^j \equiv \sum_{n=m \mod 2}^{j} h_{j,n,m} R_n^m(r); \quad j-m = 0,2,4,6,\ldots \tag{5}$$

Multiplying this equation by $R_{n'}^m(r)$, contraction on the right hand side with the normalization integral

$$\int_0^1 r\, R_n^m(r) R_{n'}^m(r) dr = \frac{1}{2(n+1)} \delta_{n,n'} \tag{6}$$

to isolate one h-coefficient, and using the explicit polynomial expression (2) on the left hand side yields [13, 19]:

$$h_{j,n,m} = 2(n+1) \int_0^1 r^{j+1} (-1)^a \binom{-b}{-a} r^m \, {}_2F_1(a, 1-b; 1+m; r^2) dr = (n+1)(-1)^a \frac{\left(\frac{m-j}{2}\right)_{-a}}{\left(1+\frac{m+j}{2}\right)_{1-a}}. \tag{7}$$

(See App. A for notational standards like Pochhammer's symbol.) From

$$R_n^m(1) = 1, \tag{8}$$

and (5) at $r = 1$ we obtain the sum rule

$$\sum_{n=m \mod 2}^{j} h_{j,n,m} = 1. \tag{9}$$

Recurrences follow from basic properties of the Gamma Functions implicitly contained in (7):

$$h_{j+2,n,m} = \frac{(j+2+m)(j+2-m)}{(j+2-n)(j+4+n)} h_{j,n,m}; \tag{10}$$

$$h_{j,n+2,m} = \frac{(n+3)(j-n)}{(j+4+n)(n+1)} h_{j,n,m}; \tag{11}$$

$$h_{j,n,m+2} = \frac{j+2+m}{j-m} h_{j,n,m}. \tag{12}$$

If we write `r^j` for r^j and `R_n^m` for R_n^m, expansions of (5) are

```
r^0 = R_0^0(r).
r^1 = R_1^1(r).
r^2 = 1/2*R_0^0(r) +1/2*R_2^0(r)
   = R_2^2(r).
r^3 = 2/3*R_1^1(r) +1/3*R_3^1(r)
   = R_3^3(r).
r^4 = 1/3*R_0^0(r) +1/2*R_2^0(r) +1/6*R_4^0(r)
   = 3/4*R_2^2(r) +1/4*R_4^2(r)
   = R_4^4(r).
r^5 = 1/2*R_1^1(r) +2/5*R_3^1(r) +1/10*R_5^1(r)
   = 4/5*R_3^3(r) +1/5*R_5^3(r)
   = R_5^5(r).
r^6 = 1/4*R_0^0(r) +9/20*R_2^0(r) +1/4*R_4^0(r) +1/20*R_6^0(r)
   = 3/5*R_2^2(r) +1/3*R_4^2(r) +1/15*R_6^2(r)
   = 5/6*R_4^4(r) +1/6*R_6^4(r)
   = R_6^6(r).
r^7 = 2/5*R_1^1(r) +2/5*R_3^1(r) +6/35*R_5^1(r) +1/35*R_7^1(r)
   = 2/3*R_3^3(r) +2/7*R_5^3(r) +1/21*R_7^3(r)
   = 6/7*R_5^5(r) +1/7*R_7^5(r)
   = R_7^7(r).
r^8 = 1/5*R_0^0(r) +2/5*R_2^0(r) +2/7*R_4^0(r) +1/10*R_6^0(r) +1/70*R_8^0(r)
   = 1/2*R_2^2(r) +5/14*R_4^2(r) +1/8*R_6^2(r) +1/56*R_8^2(r)
```

```
   = 5/7*R_4^4(r) +1/4*R_6^4(r) +1/28*R_8^4(r)
   = 7/8*R_6^6(r) +1/8*R_8^6(r)
   = R_8^8(r).
r^9 = 1/3*R_1^1(r) +8/21*R_3^1(r) +3/14*R_5^1(r) +4/63*R_7^1(r) +1/126*R_9^1(r)
   = 4/7*R_3^3(r) +9/28*R_5^3(r) +2/21*R_7^3(r) +1/84*R_9^3(r)
   = 3/4*R_5^5(r) +2/9*R_7^5(r) +1/36*R_9^5(r)
   = 8/9*R_7^7(r) +1/9*R_9^7(r)
   = R_9^9(r).
r^10 = 1/6*R_0^0(r) +5/14*R_2^0(r) +25/84*R_4^0(r) +5/36*R_6^0(r) +1/28*R_8^0(r) +1/252*R_10^0(r)
   = 3/7*R_2^2(r) +5/14*R_4^2(r) +1/6*R_6^2(r) +3/70*R_8^2(r) +1/210*R_10^2(r)
   = 5/8*R_4^4(r) +7/24*R_6^4(r) +3/40*R_8^4(r) +1/120*R_10^4(r)
   = 7/9*R_6^6(r) +1/5*R_8^6(r) +1/45*R_10^6(r)
   = 9/10*R_8^8(r) +1/10*R_10^8(r)
   = R_10^10(r).
r^11 = 2/7*R_1^1(r) +5/14*R_3^1(r) +5/21*R_5^1(r) +2/21*R_7^1(r) +5/231*R_9^1(r) +1/462*R_11^1(r)
   = 1/2*R_3^3(r) +1/3*R_5^3(r) +2/15*R_7^3(r) +1/33*R_9^3(r) +1/330*R_11^3(r)
   = 2/3*R_5^5(r) +4/15*R_7^5(r) +2/33*R_9^5(r) +1/165*R_11^5(r)
   = 4/5*R_7^7(r) +2/11*R_9^7(r) +1/55*R_11^7(r)
   = 10/11*R_9^9(r) +1/11*R_11^9(r)
   = R_11^11(r).
r^12 = 1/7*R_0^0(r) +9/28*R_2^0(r) +25/84*R_4^0(r) +1/6*R_6^0(r) +9/154*R_8^0(r) +1/84*R_10^0(r)
   +1/924*R_12^0(r)
   = 3/8*R_2^2(r) +25/72*R_4^2(r) +7/36*R_6^2(r) +3/44*R_8^2(r) +1/72*R_10^2(r) +1/792*R_12^2(r)
   = 5/9*R_4^4(r) +14/45*R_6^4(r) +6/55*R_8^4(r) +1/45*R_10^4(r) +1/495*R_12^4(r)
   = 7/10*R_6^6(r) +27/110*R_8^6(r) +1/20*R_10^6(r) +1/220*R_12^6(r)
   = 9/11*R_8^8(r) +1/6*R_10^8(r) +1/66*R_12^8(r)
   = 11/12*R_10^10(r) +1/12*R_12^10(r)
   = R_12^12(r).
r^13 = 1/4*R_1^1(r) +1/3*R_3^1(r) +1/4*R_5^1(r) +4/33*R_7^1(r) +5/132*R_9^1(r) +1/143*R_11^1(r)
   +1/1716*R_13^1(r)
   = 4/9*R_3^3(r) +1/3*R_5^3(r) +16/99*R_7^3(r) +5/99*R_9^3(r) +4/429*R_11^3(r) +1/1287*R_13^3(r)
   = 3/5*R_5^5(r) +16/55*R_7^5(r) +1/11*R_9^5(r) +12/715*R_11^5(r) +1/715*R_13^5(r)
   = 8/11*R_7^7(r) +5/22*R_9^7(r) +6/143*R_11^7(r) +1/286*R_13^7(r)
   = 5/6*R_9^9(r) +2/13*R_11^9(r) +1/78*R_13^9(r)
   = 12/13*R_11^11(r) +1/13*R_13^11(r)
   = R_13^13(r).
r^14 = 1/8*R_0^0(r) +7/24*R_2^0(r) +7/24*R_4^0(r) +49/264*R_6^0(r) +7/88*R_8^0(r) +7/312*R_10^0(r)
   +1/264*R_12^0(r) +1/3432*R_14^0(r)
   = 1/3*R_2^2(r) +1/3*R_4^2(r) +7/33*R_6^2(r) +1/11*R_8^2(r) +1/39*R_10^2(r) +1/231*R_12^2(r)
   +1/3003*R_14^2(r)
   = 1/2*R_4^4(r) +7/22*R_6^4(r) +3/22*R_8^4(r) +1/26*R_10^4(r) +1/154*R_12^4(r) +1/2002*R_14^4(r)
   = 7/11*R_6^6(r) +3/11*R_8^6(r) +1/13*R_10^6(r) +1/77*R_12^6(r) +1/1001*R_14^6(r)
   = 3/4*R_8^8(r) +11/52*R_10^8(r) +1/28*R_12^8(r) +1/364*R_14^8(r)
   = 11/13*R_10^10(r) +1/7*R_12^10(r) +1/91*R_14^10(r)
   = 13/14*R_12^12(r) +1/14*R_14^12(r)
   = R_14^14(r).
```

B. Zernike Functions

The Zernike functions Z_j are products of the radial polynomials by azimuth functions, $\cos(m\varphi)$ or $\sin(m\varphi)$, related to Cartesian coordinates

$$x = r\cos\varphi; \quad y = r\sin\varphi. \tag{13}$$

Starting at $Z_1 = 1$, the index j is increased by increasing m, increasing n, if this is exhausted as $n = m$ has been reached, and keeping j even for functions $\propto \cos(m\varphi)$, $m > 0$ and keeping j odd for functions $\propto \sin(m\varphi)$ [16],

$$Z_j = \begin{cases} \sqrt{2n+2}R_n^m(r)\cos(m\varphi), & m > 0, j \text{ even}; \\ \sqrt{2n+2}R_n^m(r)\sin(m\varphi), & m > 0, j \text{ odd}; \\ \sqrt{n+1}R_n^m(r), & m = 0. \end{cases} \tag{14}$$

$$\int_{r<1} Z_j(r,\varphi)Z_k(r,\varphi)d^2r = \pi\delta_{j,k}; \quad d^2r = r\,dr d\varphi. \tag{15}$$

```
Z_1 = 1*R_0^0(r).
Z_2 = 2*R_1^1(r)*cos(phi).    Z_3 = 2*R_1^1(r)*sin(phi).
Z_4 = 3^(1/2)*R_2^0(r).
Z_5 = 6^(1/2)*R_2^2(r)*sin(2*phi).    Z_6 = 6^(1/2)*R_2^2(r)*cos(2*phi).
Z_7 = 2*2^(1/2)*R_3^1(r)*sin(phi).    Z_8 = 2*2^(1/2)*R_3^1(r)*cos(phi).
Z_9 = 2*2^(1/2)*R_3^3(r)*sin(3*phi).    Z_10 = 2*2^(1/2)*R_3^3(r)*cos(3*phi).
Z_11 = 5^(1/2)*R_4^0(r).
Z_12 = 10^(1/2)*R_4^2(r)*cos(2*phi).    Z_13 = 10^(1/2)*R_4^2(r)*sin(2*phi).
Z_14 = 10^(1/2)*R_4^4(r)*cos(4*phi).    Z_15 = 10^(1/2)*R_4^4(r)*sin(4*phi).
Z_16 = 2*3^(1/2)*R_5^1(r)*cos(phi).    Z_17 = 2*3^(1/2)*R_5^1(r)*sin(phi).
Z_18 = 2*3^(1/2)*R_5^3(r)*cos(3*phi).    Z_19 = 2*3^(1/2)*R_5^3(r)*sin(3*phi).
Z_20 = 2*3^(1/2)*R_5^5(r)*cos(5*phi).    Z_21 = 2*3^(1/2)*R_5^5(r)*sin(5*phi).
Z_22 = 7^(1/2)*R_6^0(r).
Z_23 = 14^(1/2)*R_6^2(r)*sin(2*phi).    Z_24 = 14^(1/2)*R_6^2(r)*cos(2*phi).
Z_25 = 14^(1/2)*R_6^4(r)*sin(4*phi).    Z_26 = 14^(1/2)*R_6^4(r)*cos(4*phi).
Z_27 = 14^(1/2)*R_6^6(r)*sin(6*phi).    Z_28 = 14^(1/2)*R_6^6(r)*cos(6*phi).
Z_29 = 4*R_7^1(r)*sin(phi).    Z_30 = 4*R_7^1(r)*cos(phi).
Z_31 = 4*R_7^3(r)*sin(3*phi).    Z_32 = 4*R_7^3(r)*cos(3*phi).
Z_33 = 4*R_7^5(r)*sin(5*phi).    Z_34 = 4*R_7^5(r)*cos(5*phi).
Z_35 = 4*R_7^7(r)*sin(7*phi).    Z_36 = 4*R_7^7(r)*cos(7*phi).
Z_37 = 3*R_8^0(r).
Z_38 = 3*2^(1/2)*R_8^2(r)*cos(2*phi).    Z_39 = 3*2^(1/2)*R_8^2(r)*sin(2*phi).
Z_40 = 3*2^(1/2)*R_8^4(r)*cos(4*phi).    Z_41 = 3*2^(1/2)*R_8^4(r)*sin(4*phi).
Z_42 = 3*2^(1/2)*R_8^6(r)*cos(6*phi).    Z_43 = 3*2^(1/2)*R_8^6(r)*sin(6*phi).
Z_44 = 3*2^(1/2)*R_8^8(r)*cos(8*phi).    Z_45 = 3*2^(1/2)*R_8^8(r)*sin(8*phi).
Z_46 = 2*5^(1/2)*R_9^1(r)*cos(phi).    Z_47 = 2*5^(1/2)*R_9^1(r)*sin(phi).
Z_48 = 2*5^(1/2)*R_9^3(r)*cos(3*phi).    Z_49 = 2*5^(1/2)*R_9^3(r)*sin(3*phi).
Z_50 = 2*5^(1/2)*R_9^5(r)*cos(5*phi).    Z_51 = 2*5^(1/2)*R_9^5(r)*sin(5*phi).
Z_52 = 2*5^(1/2)*R_9^7(r)*cos(7*phi).    Z_53 = 2*5^(1/2)*R_9^7(r)*sin(7*phi).
Z_54 = 2*5^(1/2)*R_9^9(r)*cos(9*phi).    Z_55 = 2*5^(1/2)*R_9^9(r)*sin(9*phi).
Z_56 = 11^(1/2)*R_10^0(r).
Z_57 = 22^(1/2)*R_10^2(r)*sin(2*phi).    Z_58 = 22^(1/2)*R_10^2(r)*cos(2*phi).
Z_59 = 22^(1/2)*R_10^4(r)*sin(4*phi).    Z_60 = 22^(1/2)*R_10^4(r)*cos(4*phi).
Z_61 = 22^(1/2)*R_10^6(r)*sin(6*phi).    Z_62 = 22^(1/2)*R_10^6(r)*cos(6*phi).
Z_63 = 22^(1/2)*R_10^8(r)*sin(8*phi).    Z_64 = 22^(1/2)*R_10^8(r)*cos(8*phi).
Z_65 = 22^(1/2)*R_10^10(r)*sin(10*phi).    Z_66 = 22^(1/2)*R_10^10(r)*cos(10*phi).
```

Square roots $\sqrt{k}$ are written in the style `k^(1/2)`.

C. Cartesian to Zernike

With (13), each multinomial $x^p y^q$ can be decomposed into terms proportional to $R_n^m(r)\cos(m\varphi)$ if q is even, or proportional to $R_n^m(r)\sin(m\varphi)$ if q is odd,

$$x^p y^q = r^j \cos^p\varphi \sin^q\varphi, \quad j \equiv p+q. \tag{16}$$

$$\cos^p\varphi\sin^q\varphi = \frac{(e^{i\varphi}+e^{-i\varphi})^p}{2^p}\frac{(e^{i\varphi}-e^{-i\varphi})^q}{(2i)^q} \tag{17}$$

$$= \frac{(-1)^{\lfloor q/2\rfloor}}{2^{p+q}}\sum_{s=0}^{p}\sum_{l=0}^{q}\binom{p}{s}\binom{q}{l}(-1)^{q-l}\times\begin{cases}\cos[(2s-p+2l-q)\varphi], & q\,\text{even};\\ \sin[(2s-p+2l-q)\varphi], & q\,\text{odd};\end{cases} \tag{18}$$

$$= \frac{(-1)^{\lfloor q/2\rfloor}}{2^j}\times\begin{cases}\left[2\sum_{m=0}^{\lfloor (j-1)/2\rfloor}\sum_{l=\max(0,m-p)}^{\min(q,m)}\binom{p}{m-l}\binom{q}{l}(-1)^l\cos[(j-2m)\varphi]+C(p,q)\right], & q\,\text{even};\\ 2\sum_{m=0}^{\lfloor (j-1)/2\rfloor}\sum_{l=\max(0,m-p)}^{\min(q,m)}\binom{p}{m-l}\binom{q}{l}(-1)^l\sin[(j-2m)\varphi], & q\,\text{odd};\end{cases} \tag{19}$$

where $j \equiv p+q$, and where

$$C(p,q) \equiv \begin{cases}\sum_{l=0}^{q}\binom{p}{j/2-l}\binom{q}{l}(-1)^l = 2^j\frac{\Gamma((p+1)/2)}{\Gamma(j/2+1)\Gamma((1-q)/2)} = (-1)^{q/2}2^{j/2}\frac{(q-1)!!(p-1)!!}{(j/2)!}, & j\,\text{even};\\ 0, & j\,\text{odd}\end{cases} \tag{20}$$

is a "dangling" component representing the contribution at $j = 2m$ if q and j are both even [3, (B2b)].

This extends Section 1.32 of the Gradstein-Ryshik tables [9] and distributes $\cos^p\varphi \sin^q\varphi$ into sums over $\cos(m\varphi)$ or $\sin(m\varphi)$:

```
cos^2 phi = [ 1 +cos(2*phi) ]/2.
cos phi sin phi = [ sin(2*phi) ]/2.
sin^2 phi = [ 1 -cos(2*phi) ]/2.
cos^3 phi = [ 3*cos(phi) +cos(3*phi) ]/4.
cos^2 phi sin phi = [ sin(phi) +sin(3*phi) ]/4.
cos phi sin^2 phi = [ cos(phi) -cos(3*phi) ]/4.
sin^3 phi = [ 3*sin(phi) -sin(3*phi) ]/4.
cos^4 phi = [ 3 +4*cos(2*phi) +cos(4*phi) ]/8.
cos^3 phi sin phi = [ 2*sin(2*phi) +sin(4*phi) ]/8.
cos^2 phi sin^2 phi = [ 1 -cos(4*phi) ]/8.
cos phi sin^3 phi = [ 2*sin(2*phi) -sin(4*phi) ]/8.
sin^4 phi = [ 3 -4*cos(2*phi) +cos(4*phi) ]/8.
```

Back to (16), these are multiplied by $r^j = r^{p+q}$ for an intermediate table of Cartesian to spherical transformations:

```
x = r*cos(phi).
y = r*sin(phi).
x^2 = 1/2*r^2*cos(2*phi) +1/2*r^2.
x y = 1/2*r^2*sin(2*phi).
y^2 =  -1/2*r^2*cos(2*phi) +1/2*r^2.
x^3 = 1/4*r^3*cos(3*phi) +3/4*r^3*cos(phi).
x^2 y = 1/4*r^3*sin(3*phi) +1/4*r^3*sin(phi).
x y^2 =  -1/4*r^3*cos(3*phi) +1/4*r^3*cos(phi).
y^3 =  -1/4*r^3*sin(3*phi) +3/4*r^3*sin(phi).
x^4 = 1/8*r^4*cos(4*phi) +1/2*r^4*cos(2*phi) +3/8*r^4.
x^3 y = 1/8*r^4*sin(4*phi) +1/4*r^4*sin(2*phi).
x^2 y^2 =  -1/8*r^4*cos(4*phi) +1/8*r^4.
x y^3 =  -1/8*r^4*sin(4*phi) +1/4*r^4*sin(2*phi).
y^4 = 1/8*r^4*cos(4*phi) -1/2*r^4*cos(2*phi) +3/8*r^4.
x^5 = 1/16*r^5*cos(5*phi) +5/16*r^5*cos(3*phi) +5/8*r^5*cos(phi).
x^4 y = 1/16*r^5*sin(5*phi) +3/16*r^5*sin(3*phi) +1/8*r^5*sin(phi).
x^3 y^2 =  -1/16*r^5*cos(5*phi) -1/16*r^5*cos(3*phi) +1/8*r^5*cos(phi).
x^2 y^3 =  -1/16*r^5*sin(5*phi) +1/16*r^5*sin(3*phi) +1/8*r^5*sin(phi).
x y^4 = 1/16*r^5*cos(5*phi) -3/16*r^5*cos(3*phi) +1/8*r^5*cos(phi).
y^5 = 1/16*r^5*sin(5*phi) -5/16*r^5*sin(3*phi) +5/8*r^5*sin(phi).
```

Each factor r^j is expanded with (5) in a sum over R, selecting the line of the table of section II A associated with m:

```
x = R_1^1(r)*cos(phi).
y = R_1^1(r)*sin(phi).
x^2 = 1/2*R_2^2(r)*cos(2*phi) +1/4*R_0^0(r) +1/4*R_2^0(r).
x y = 1/2*R_2^2(r)*sin(2*phi).
y^2 = -1/2*R_2^2(r)*cos(2*phi) +1/4*R_0^0(r) +1/4*R_2^0(r).
x^3 = 1/4*R_3^3(r)*cos(3*phi) +1/2*cos(phi)*R_1^1(r) +1/4*cos(phi)*R_3^1(r).
x^2 y = 1/4*R_3^3(r)*sin(3*phi) +1/6*sin(phi)*R_1^1(r) +1/12*sin(phi)*R_3^1(r).
x y^2 = -1/4*R_3^3(r)*cos(3*phi) +1/6*cos(phi)*R_1^1(r) +1/12*cos(phi)*R_3^1(r).
y^3 = -1/4*R_3^3(r)*sin(3*phi) +1/2*sin(phi)*R_1^1(r) +1/4*sin(phi)*R_3^1(r).
x^4 = 1/8*R_4^4(r)*cos(4*phi) +3/8*cos(2*phi)*R_2^2(r) +1/8*cos(2*phi)*R_4^2(r) +1/8*R_0^0(r)
   +3/16*R_2^0(r) +1/16*R_4^0(r).
x^3 y = 1/8*R_4^4(r)*sin(4*phi) +3/16*sin(2*phi)*R_2^2(r) +1/16*sin(2*phi)*R_4^2(r).
x^2 y^2 = -1/8*R_4^4(r)*cos(4*phi) +1/24*R_0^0(r) +1/16*R_2^0(r) +1/48*R_4^0(r).
x y^3 = -1/8*R_4^4(r)*sin(4*phi) +3/16*sin(2*phi)*R_2^2(r) +1/16*sin(2*phi)*R_4^2(r).
y^4 = 1/8*R_4^4(r)*cos(4*phi) -3/8*cos(2*phi)*R_2^2(r) -1/8*cos(2*phi)*R_4^2(r) +1/8*R_0^0(r)
   +3/16*R_2^0(r) +1/16*R_4^0(r).
x^5 = 1/16*R_5^5(r)*cos(5*phi) +1/4*cos(3*phi)*R_3^3(r) +1/16*cos(3*phi)*R_5^3(r)
   +5/16*cos(phi)*R_1^1(r) +1/4*cos(phi)*R_3^1(r) +1/16*cos(phi)*R_5^1(r).
x^4 y = 1/16*R_5^5(r)*sin(5*phi) +3/20*sin(3*phi)*R_3^3(r) +3/80*sin(3*phi)*R_5^3(r)
   +1/16*sin(phi)*R_1^1(r) +1/20*sin(phi)*R_3^1(r) +1/80*sin(phi)*R_5^1(r).
x^3 y^2 = -1/16*R_5^5(r)*cos(5*phi) -1/20*cos(3*phi)*R_3^3(r) -1/80*cos(3*phi)*R_5^3(r)
   +1/16*cos(phi)*R_1^1(r) +1/20*cos(phi)*R_3^1(r) +1/80*cos(phi)*R_5^1(r).
x^2 y^3 = -1/16*R_5^5(r)*sin(5*phi) +1/20*sin(3*phi)*R_3^3(r) +1/80*sin(3*phi)*R_5^3(r)
```

```
   +1/16*sin(phi)*R_1^1(r) +1/20*sin(phi)*R_3^1(r) +1/80*sin(phi)*R_5^1(r).
x y^4 = 1/16*R_5^5(r)*cos(5*phi) -3/20*cos(3*phi)*R_3^3(r) -3/80*cos(3*phi)*R_5^3(r)
   +1/16*cos(phi)*R_1^1(r) +1/20*cos(phi)*R_3^1(r) +1/80*cos(phi)*R_5^1(r).
y^5 = 1/16*R_5^5(r)*sin(5*phi) -1/4*sin(3*phi)*R_3^3(r) -1/16*sin(3*phi)*R_5^3(r)
   +5/16*sin(phi)*R_1^1(r) +1/4*sin(phi)*R_3^1(r) +1/16*sin(phi)*R_5^1(r).
x^6 = 1/32*R_6^6(r)*cos(6*phi) +5/32*cos(4*phi)*R_4^4(r) +1/32*cos(4*phi)*R_6^4(r)
   +9/32*cos(2*phi)*R_2^2(r) +5/32*cos(2*phi)*R_4^2(r) +1/32*cos(2*phi)*R_6^2(r) +5/64*R_0^0(r)
   +9/64*R_2^0(r) +5/64*R_4^0(r) +1/64*R_6^0(r).
x^5 y = 1/32*R_6^6(r)*sin(6*phi) +5/48*sin(4*phi)*R_4^4(r) +1/48*sin(4*phi)*R_6^4(r)
   +3/32*sin(2*phi)*R_2^2(r) +5/96*sin(2*phi)*R_4^2(r) +1/96*sin(2*phi)*R_6^2(r).
x^4 y^2 = -1/32*R_6^6(r)*cos(6*phi) -5/96*cos(4*phi)*R_4^4(r) -1/96*cos(4*phi)*R_6^4(r)
   +3/160*cos(2*phi)*R_2^2(r) +1/96*cos(2*phi)*R_4^2(r) +1/480*cos(2*phi)*R_6^2(r) +1/64*R_0^0(r)
   +9/320*R_2^0(r) +1/64*R_4^0(r) +1/320*R_6^0(r).
x^3 y^3 = -1/32*R_6^6(r)*sin(6*phi) +9/160*sin(2*phi)*R_2^2(r) +1/32*sin(2*phi)*R_4^2(r)
   +1/160*sin(2*phi)*R_6^2(r).
x^2 y^4 = 1/32*R_6^6(r)*cos(6*phi) -5/96*cos(4*phi)*R_4^4(r) -1/96*cos(4*phi)*R_6^4(r)
   -3/160*cos(2*phi)*R_2^2(r) -1/96*cos(2*phi)*R_4^2(r) -1/480*cos(2*phi)*R_6^2(r) +1/64*R_0^0(r)
   +9/320*R_2^0(r) +1/64*R_4^0(r) +1/320*R_6^0(r).
x y^5 = 1/32*R_6^6(r)*sin(6*phi) -5/48*sin(4*phi)*R_4^4(r) -1/48*sin(4*phi)*R_6^4(r)
   +3/32*sin(2*phi)*R_2^2(r) +5/96*sin(2*phi)*R_4^2(r) +1/96*sin(2*phi)*R_6^2(r).
y^6 = -1/32*R_6^6(r)*cos(6*phi) +5/32*cos(4*phi)*R_4^4(r) +1/32*cos(4*phi)*R_6^4(r)
   -9/32*cos(2*phi)*R_2^2(r) -5/32*cos(2*phi)*R_4^2(r) -1/32*cos(2*phi)*R_6^2(r) +5/64*R_0^0(r)
   +9/64*R_2^0(r) +5/64*R_4^0(r) +1/64*R_6^0(r).
x^7 = 1/64*R_7^7(r)*cos(7*phi) +3/32*cos(5*phi)*R_5^5(r) +1/64*cos(5*phi)*R_7^5(r)
   +7/32*cos(3*phi)*R_3^3(r) +3/32*cos(3*phi)*R_5^3(r) +1/64*cos(3*phi)*R_7^3(r) +7/32*cos(phi)*R_1^1(r)
   +7/32*cos(phi)*R_3^1(r) +3/32*cos(phi)*R_5^1(r) +1/64*cos(phi)*R_7^1(r).
x^6 y = 1/64*R_7^7(r)*sin(7*phi) +15/224*sin(5*phi)*R_5^5(r) +5/448*sin(5*phi)*R_7^5(r)
   +3/32*sin(3*phi)*R_3^3(r) +9/224*sin(3*phi)*R_5^3(r) +3/448*sin(3*phi)*R_7^3(r)
   +1/32*sin(phi)*R_1^1(r) +1/32*sin(phi)*R_3^1(r) +3/224*sin(phi)*R_5^1(r) +1/448*sin(phi)*R_7^1(r).
x^5 y^2 = -1/64*R_7^7(r)*cos(7*phi) -9/224*cos(5*phi)*R_5^5(r) -3/448*cos(5*phi)*R_7^5(r)
   -1/96*cos(3*phi)*R_3^3(r) -1/224*cos(3*phi)*R_5^3(r) -1/1344*cos(3*phi)*R_7^3(r)
   +1/32*cos(phi)*R_1^1(r) +1/32*cos(phi)*R_3^1(r) +3/224*cos(phi)*R_5^1(r) +1/448*cos(phi)*R_7^1(r).
x^4 y^3 = -1/64*R_7^7(r)*sin(7*phi) -3/224*sin(5*phi)*R_5^5(r) -1/448*sin(5*phi)*R_7^5(r)
   +1/32*sin(3*phi)*R_3^3(r) +3/224*sin(3*phi)*R_5^3(r) +1/448*sin(3*phi)*R_7^3(r)
   +3/160*sin(phi)*R_1^1(r) +3/160*sin(phi)*R_3^1(r) +9/1120*sin(phi)*R_5^1(r) +3/2240*sin(phi)*R_7^1(r).
x^3 y^4 = 1/64*R_7^7(r)*cos(7*phi) -3/224*cos(5*phi)*R_5^5(r) -1/448*cos(5*phi)*R_7^5(r)
   -1/32*cos(3*phi)*R_3^3(r) -3/224*cos(3*phi)*R_5^3(r) -1/448*cos(3*phi)*R_7^3(r)
   +3/160*cos(phi)*R_1^1(r) +3/160*cos(phi)*R_3^1(r) +9/1120*cos(phi)*R_5^1(r) +3/2240*cos(phi)*R_7^1(r).
x^2 y^5 = 1/64*R_7^7(r)*sin(7*phi) -9/224*sin(5*phi)*R_5^5(r) -3/448*sin(5*phi)*R_7^5(r)
   +1/96*sin(3*phi)*R_3^3(r) +1/224*sin(3*phi)*R_5^3(r) +1/1344*sin(3*phi)*R_7^3(r)
   +1/32*sin(phi)*R_1^1(r) +1/32*sin(phi)*R_3^1(r) +3/224*sin(phi)*R_5^1(r) +1/448*sin(phi)*R_7^1(r).
x y^6 = -1/64*R_7^7(r)*cos(7*phi) +15/224*cos(5*phi)*R_5^5(r) +5/448*cos(5*phi)*R_7^5(r)
   -3/32*cos(3*phi)*R_3^3(r) -9/224*cos(3*phi)*R_5^3(r) -3/448*cos(3*phi)*R_7^3(r)
   +1/32*cos(phi)*R_1^1(r) +1/32*cos(phi)*R_3^1(r) +3/224*cos(phi)*R_5^1(r) +1/448*cos(phi)*R_7^1(r).
y^7 = -1/64*R_7^7(r)*sin(7*phi) +3/32*sin(5*phi)*R_5^5(r) +1/64*sin(5*phi)*R_7^5(r)
   -7/32*sin(3*phi)*R_3^3(r) -3/32*sin(3*phi)*R_5^3(r) -1/64*sin(3*phi)*R_7^3(r) +7/32*sin(phi)*R_1^1(r)
   +7/32*sin(phi)*R_3^1(r) +3/32*sin(phi)*R_5^1(r) +1/64*sin(phi)*R_7^1(r).
x^8 = 1/128*R_8^8(r)*cos(8*phi) +7/128*cos(6*phi)*R_6^6(r) +1/128*cos(6*phi)*R_8^6(r)
   +5/32*cos(4*phi)*R_4^4(r) +7/128*cos(4*phi)*R_6^4(r) +1/128*cos(4*phi)*R_8^4(r)
   +7/32*cos(2*phi)*R_2^2(r) +5/32*cos(2*phi)*R_4^2(r) +7/128*cos(2*phi)*R_6^2(r)
   +1/128*cos(2*phi)*R_8^2(r) +7/128*R_0^0(r) +7/64*R_2^0(r) +5/64*R_4^0(r) +7/256*R_6^0(r)
   +1/256*R_8^0(r).
x^7 y = 1/128*R_8^8(r)*sin(8*phi) +21/512*sin(6*phi)*R_6^6(r) +3/512*sin(6*phi)*R_8^6(r)
   +5/64*sin(4*phi)*R_4^4(r) +7/256*sin(4*phi)*R_6^4(r) +1/256*sin(4*phi)*R_8^4(r)
   +7/128*sin(2*phi)*R_2^2(r) +5/128*sin(2*phi)*R_4^2(r) +7/512*sin(2*phi)*R_6^2(r)
   +1/512*sin(2*phi)*R_8^2(r).
x^6 y^2 = -1/128*R_8^8(r)*cos(8*phi) -7/256*cos(6*phi)*R_6^6(r) -1/256*cos(6*phi)*R_8^6(r)
   -5/224*cos(4*phi)*R_4^4(r) -1/128*cos(4*phi)*R_6^4(r) -1/896*cos(4*phi)*R_8^4(r)
   +1/64*cos(2*phi)*R_2^2(r) +5/448*cos(2*phi)*R_4^2(r) +1/256*cos(2*phi)*R_6^2(r)
   +1/1792*cos(2*phi)*R_8^2(r) +1/128*R_0^0(r) +1/64*R_2^0(r) +5/448*R_4^0(r) +1/256*R_6^0(r)
   +1/1792*R_8^0(r).
x^5 y^3 = -1/128*R_8^8(r)*sin(8*phi) -7/512*sin(6*phi)*R_6^6(r) -1/512*sin(6*phi)*R_8^6(r)
   +5/448*sin(4*phi)*R_4^4(r) +1/256*sin(4*phi)*R_6^4(r) +1/1792*sin(4*phi)*R_8^4(r)
   +3/128*sin(2*phi)*R_2^2(r) +15/896*sin(2*phi)*R_4^2(r) +3/512*sin(2*phi)*R_6^2(r)
```

```
   +3/3584*sin(2*phi)*R_8^2(r).
x^4 y^4 = 1/128*R_8^8(r)*cos(8*phi) -5/224*cos(4*phi)*R_4^4(r) -1/128*cos(4*phi)*R_6^4(r)
   -1/896*cos(4*phi)*R_8^4(r) +3/640*R_0^0(r) +3/320*R_2^0(r) +3/448*R_4^0(r) +3/1280*R_6^0(r)
   +3/8960*R_8^0(r).
x^3 y^5 = 1/128*R_8^8(r)*sin(8*phi) -7/512*sin(6*phi)*R_6^6(r) -1/512*sin(6*phi)*R_8^6(r)
   -5/448*sin(4*phi)*R_4^4(r) -1/256*sin(4*phi)*R_6^4(r) -1/1792*sin(4*phi)*R_8^4(r)
   +3/128*sin(2*phi)*R_2^2(r) +15/896*sin(2*phi)*R_4^2(r) +3/512*sin(2*phi)*R_6^2(r)
   +3/3584*sin(2*phi)*R_8^2(r).
x^2 y^6 = -1/128*R_8^8(r)*cos(8*phi) +7/256*cos(6*phi)*R_6^6(r) +1/256*cos(6*phi)*R_8^6(r)
   -5/224*cos(4*phi)*R_4^4(r) -1/128*cos(4*phi)*R_6^4(r) -1/896*cos(4*phi)*R_8^4(r)
   -1/64*cos(2*phi)*R_2^2(r) -5/448*cos(2*phi)*R_4^2(r) -1/256*cos(2*phi)*R_6^2(r)
   -1/1792*cos(2*phi)*R_8^2(r) +1/128*R_0^0(r) +1/64*R_2^0(r) +5/448*R_4^0(r) +1/256*R_6^0(r)
   +1/1792*R_8^0(r).
x y^7 = -1/128*R_8^8(r)*sin(8*phi) +21/512*sin(6*phi)*R_6^6(r) +3/512*sin(6*phi)*R_8^6(r)
   -5/64*sin(4*phi)*R_4^4(r) -7/256*sin(4*phi)*R_6^4(r) -1/256*sin(4*phi)*R_8^4(r)
   +7/128*sin(2*phi)*R_2^2(r) +5/128*sin(2*phi)*R_4^2(r) +7/512*sin(2*phi)*R_6^2(r)
   +1/512*sin(2*phi)*R_8^2(r).
y^8 = 1/128*R_8^8(r)*cos(8*phi) -7/128*cos(6*phi)*R_6^6(r) -1/128*cos(6*phi)*R_8^6(r)
   +5/32*cos(4*phi)*R_4^4(r) +7/128*cos(4*phi)*R_6^4(r) +1/128*cos(4*phi)*R_8^4(r)
   -7/32*cos(2*phi)*R_2^2(r) -5/32*cos(2*phi)*R_4^2(r) -7/128*cos(2*phi)*R_6^2(r)
   -1/128*cos(2*phi)*R_8^2(r) +7/128*R_0^0(r) +7/64*R_2^0(r) +5/64*R_4^0(r) +7/256*R_6^0(r)
   +1/256*R_8^0(r).
```

If the factor y is absent, ie, for pure powers `x^p`, the coefficients could also be taken from the column headed with two `p` in Conforti's Table 1 [2].

D. Zernike to Cartesian

The reversal of the transformation of the previous section splits each $r^j\cos(m\varphi)$ or $r^j\sin(m\varphi)$ in the expansions of Section II A into

$$r^{j-m}r^m\cos(m\varphi) \;=\; (x^2+y^2)^{(j-m)/2}\sum_{k=0,2,4,\ldots}^{m}(-1)^{\lfloor k/2\rfloor}\binom{m}{k}x^{m-k}y^k, \tag{21}$$

$$r^{j-m}r^m\sin(m\varphi) \;=\; (x^2+y^2)^{(j-m)/2}\sum_{k=1,3,5,\ldots}^{m}(-1)^{\lfloor k/2\rfloor}\binom{m}{k}x^{m-k}y^k, \tag{22}$$

which yields a sum over the bivariate Cartesian products after binomial expansion of $(x^2+y^2)^{(j-m)/2}$. The two cases are

$$r^j\cos(m\varphi) \;=\; \sum_{t=0}^{(j-m)/2}\binom{(j-m)/2}{t}x^{2t}y^{j-m-2t}\sum_{k=0,2,4,\ldots}^{m}(-1)^{k/2}\binom{m}{k}x^{m-k}y^k \tag{23}$$

$$\;=\; \sum_{t=-\lfloor m/2\rfloor}^{(j-m)/2}\;\sum_{k=\max(0,-t)}^{\min((j-m)/2-t,\lfloor m/2\rfloor)}(-1)^k\binom{m}{2k}\binom{(j-m)/2}{t+k}x^{2t+m}y^{j-m-2t}, \tag{24}$$

and

$$r^j\sin(m\varphi) \;=\; \sum_{t=0}^{(j-m)/2}\binom{(j-m)/2}{t}x^{2t}y^{j-m-2t}\sum_{k=1,3,5,\ldots}^{m}(-1)^{(k-1)/2}\binom{m}{k}x^{m-k}y^k \tag{25}$$

$$\;=\; \sum_{t=-\lfloor (m-1)/2\rfloor}^{(j-m)/2}\;\sum_{k=\max(0,-t)}^{\min((j-m)/2-t,\lfloor (m-1)/2\rfloor)}(-1)^k\binom{m}{2k+1}\binom{(j-m)/2}{t+k}x^{2t+m-1}y^{j-m-2t+1}. \tag{26}$$

The explicit tabulation for small j and small m starts as follows:

```
r cos(phi) = x.
r sin(phi) = y.
```

```
r^2 = x^2 +y^2.
r^2 cos(2*phi) = x^2 -y^2.
r^2 sin(2*phi) = 2*x*y.
r^3 cos(phi) = x^3 +x*y^2.
r^3 sin(phi) = y*x^2 +y^3.
r^3 cos(3*phi) = x^3 -3*x*y^2.
r^3 sin(3*phi) = 3*y*x^2 -y^3.
r^4 = x^4 +2*x^2*y^2 +y^4.
r^4 cos(2*phi) = x^4 -y^4.
r^4 sin(2*phi) = 2*x^3*y +2*x*y^3.
r^4 cos(4*phi) = x^4 -6*x^2*y^2 +y^4.
r^4 sin(4*phi) = 4*x^3*y -4*x*y^3.
r^5 cos(phi) = x^5 +2*x^3*y^2 +x*y^4.
r^5 sin(phi) = y*x^4 +2*x^2*y^3 +y^5.
r^5 cos(3*phi) = x^5 -2*x^3*y^2 -3*x*y^4.
r^5 sin(3*phi) = 3*y*x^4 +2*x^2*y^3 -y^5.
r^5 cos(5*phi) = x^5 -10*x^3*y^2 +5*x*y^4.
r^5 sin(5*phi) = 5*y*x^4 -10*x^2*y^3 +y^5.
```

Linear superposition by inserting these into the right hand sides of (2) as tabulated in Section II A yields

```
R_0^0(r) = 1 Z_1 = 1.
R_1^1(r) cos(phi) = 1/2 Z_2 = x.
R_1^1(r) sin(phi) = 1/2 Z_3 = y.
R_2^0(r) = 1/3*3^(1/2) Z_4 = 2*x^2 +2*y^2 -1.
R_2^2(r) cos(2*phi) = 1/6*6^(1/2) Z_6 = x^2 -y^2.
R_2^2(r) sin(2*phi) = 1/6*6^(1/2) Z_5 = 2*x*y.
R_3^1(r) cos(phi) = 1/4*2^(1/2) Z_8 = 3*x^3 +3*x*y^2 -2*x.
R_3^1(r) sin(phi) = 1/4*2^(1/2) Z_7 = 3*x^2*y +3*y^3 -2*y.
R_3^3(r) cos(3*phi) = 1/4*2^(1/2) Z_10 = x^3 -3*x*y^2.
R_3^3(r) sin(3*phi) = 1/4*2^(1/2) Z_9 = 3*x^2*y -y^3.
R_4^0(r) = 1/5*5^(1/2) Z_11 = 6*x^4 +12*x^2*y^2 +6*y^4 -6*x^2 -6*y^2 +1.
R_4^2(r) cos(2*phi) = 1/10*10^(1/2) Z_12 = 4*x^4 -4*y^4 -3*x^2 +3*y^2.
R_4^2(r) sin(2*phi) = 1/10*10^(1/2) Z_13 = 8*x^3*y +8*x*y^3 -6*x*y.
R_4^4(r) cos(4*phi) = 1/10*10^(1/2) Z_14 = x^4 -6*x^2*y^2 +y^4.
R_4^4(r) sin(4*phi) = 1/10*10^(1/2) Z_15 = 4*x^3*y -4*x*y^3.
R_5^1(r) cos(phi) = 1/6*3^(1/2) Z_16 = 10*x^5 +20*x^3*y^2 +10*x*y^4 -12*x^3 -12*x*y^2 +3*x.
R_5^1(r) sin(phi) = 1/6*3^(1/2) Z_17 = 10*x^4*y +20*x^2*y^3 +10*y^5 -12*x^2*y -12*y^3 +3*y.
R_5^3(r) cos(3*phi) = 1/6*3^(1/2) Z_18 = 5*x^5 -10*x^3*y^2 -15*x*y^4 -4*x^3 +12*x*y^2.
R_5^3(r) sin(3*phi) = 1/6*3^(1/2) Z_19 = 15*x^4*y +10*x^2*y^3 -5*y^5 -12*x^2*y +4*y^3.
R_5^5(r) cos(5*phi) = 1/6*3^(1/2) Z_20 = x^5 -10*x^3*y^2 +5*x*y^4.
R_5^5(r) sin(5*phi) = 1/6*3^(1/2) Z_21 = 5*x^4*y -10*x^2*y^3 +y^5.
R_6^0(r) = 1/7*7^(1/2) Z_22 = 20*x^6 +60*x^4*y^2 +60*x^2*y^4 +20*y^6 -30*x^4 -60*x^2*y^2 -30*y^4
   +12*x^2 +12*y^2 -1.
R_6^2(r) cos(2*phi) = 1/14*14^(1/2) Z_24 = 15*x^6 +15*x^4*y^2 -15*x^2*y^4 -15*y^6 -20*x^4 +20*y^4
   +6*x^2 -6*y^2.
R_6^2(r) sin(2*phi) = 1/14*14^(1/2) Z_23 = 30*x^5*y +60*x^3*y^3 +30*x*y^5 -40*x^3*y -40*x*y^3 +12*x*y.
R_6^4(r) cos(4*phi) = 1/14*14^(1/2) Z_26 = 6*x^6 -30*x^4*y^2 -30*x^2*y^4 +6*y^6 -5*x^4 +30*x^2*y^2
   -5*y^4.
R_6^4(r) sin(4*phi) = 1/14*14^(1/2) Z_25 = 24*x^5*y -24*x*y^5 -20*x^3*y +20*x*y^3.
R_6^6(r) cos(6*phi) = 1/14*14^(1/2) Z_28 = x^6 -15*x^4*y^2 +15*x^2*y^4 -y^6.
R_6^6(r) sin(6*phi) = 1/14*14^(1/2) Z_27 = 6*x^5*y -20*x^3*y^3 +6*x*y^5.
R_7^1(r) cos(phi) = 1/4 Z_30 = 35*x^7 +105*x^5*y^2 +105*x^3*y^4 +35*x*y^6 -60*x^5 -120*x^3*y^2
   -60*x*y^4 +30*x^3 +30*x*y^2 -4*x.
R_7^1(r) sin(phi) = 1/4 Z_29 = 35*x^6*y +105*x^4*y^3 +105*x^2*y^5 +35*y^7 -60*x^4*y -120*x^2*y^3
   -60*y^5 +30*x^2*y +30*y^3 -4*y.
R_7^3(r) cos(3*phi) = 1/4 Z_32 = 21*x^7 -21*x^5*y^2 -105*x^3*y^4 -63*x*y^6 -30*x^5 +60*x^3*y^2
   +90*x*y^4 +10*x^3 -30*x*y^2.
R_7^3(r) sin(3*phi) = 1/4 Z_31 = 63*x^6*y +105*x^4*y^3 +21*x^2*y^5 -21*y^7 -90*x^4*y -60*x^2*y^3
   +30*y^5 +30*x^2*y -10*y^3.
R_7^5(r) cos(5*phi) = 1/4 Z_34 = 7*x^7 -63*x^5*y^2 -35*x^3*y^4 +35*x*y^6 -6*x^5 +60*x^3*y^2 -30*x*y^4.
R_7^5(r) sin(5*phi) = 1/4 Z_33 = 35*x^6*y -35*x^4*y^3 -63*x^2*y^5 +7*y^7 -30*x^4*y +60*x^2*y^3 -6*y^5.
R_7^7(r) cos(7*phi) = 1/4 Z_36 = x^7 -21*x^5*y^2 +35*x^3*y^4 -7*x*y^6.
R_7^7(r) sin(7*phi) = 1/4 Z_35 = 7*x^6*y -35*x^4*y^3 +21*x^2*y^5 -y^7.
R_8^0(r) = 1/3 Z_37 = 70*x^8 +280*x^6*y^2 +420*x^4*y^4 +280*x^2*y^6 +70*y^8 -140*x^6 -420*x^4*y^2
```

```
   -420*x^2*y^4 -140*y^6 +90*x^4 +180*x^2*y^2 +90*y^4 -20*x^2 -20*y^2 +1.
R_8^2(r) cos(2*phi) = 1/6*2^(1/2) Z_38 = 56*x^8 +112*x^6*y^2 -112*x^2*y^6 -56*y^8 -105*x^6
   -105*x^4*y^2 +105*x^2*y^4 +105*y^6 +60*x^4 -60*y^4 -10*x^2 +10*y^2.
R_8^2(r) sin(2*phi) = 1/6*2^(1/2) Z_39 = 112*x^7*y +336*x^5*y^3 +336*x^3*y^5 +112*x*y^7 -210*x^5*y
   -420*x^3*y^3 -210*x*y^5 +120*x^3*y +120*x*y^3 -20*x*y.
R_8^4(r) cos(4*phi) = 1/6*2^(1/2) Z_40 = 28*x^8 -112*x^6*y^2 -280*x^4*y^4 -112*x^2*y^6 +28*y^8 -42*x^6
   +210*x^4*y^2 +210*x^2*y^4 -42*y^6 +15*x^4 -90*x^2*y^2 +15*y^4.
R_8^4(r) sin(4*phi) = 1/6*2^(1/2) Z_41 = 112*x^7*y +112*x^5*y^3 -112*x^3*y^5 -112*x*y^7 -168*x^5*y
   +168*x*y^5 +60*x^3*y -60*x*y^3.
R_8^6(r) cos(6*phi) = 1/6*2^(1/2) Z_42 = 8*x^8 -112*x^6*y^2 +112*x^2*y^6 -8*y^8 -7*x^6 +105*x^4*y^2
   -105*x^2*y^4 +7*y^6.
R_8^6(r) sin(6*phi) = 1/6*2^(1/2) Z_43 = 48*x^7*y -112*x^5*y^3 -112*x^3*y^5 +48*x*y^7 -42*x^5*y
   +140*x^3*y^3 -42*x*y^5.
R_8^8(r) cos(8*phi) = 1/6*2^(1/2) Z_44 = x^8 -28*x^6*y^2 +70*x^4*y^4 -28*x^2*y^6 +y^8.
R_8^8(r) sin(8*phi) = 1/6*2^(1/2) Z_45 = 8*x^7*y -56*x^5*y^3 +56*x^3*y^5 -8*x*y^7.
R_9^1(r) cos(phi) = 1/10*5^(1/2) Z_46 = 126*x^9 +504*x^7*y^2 +756*x^5*y^4 +504*x^3*y^6 +126*x*y^8
   -280*x^7 -840*x^5*y^2 -840*x^3*y^4 -280*x*y^6 +210*x^5 +420*x^3*y^2 +210*x*y^4 -60*x^3 -60*x*y^2 +5*x.
R_9^1(r) sin(phi) = 1/10*5^(1/2) Z_47 = 126*x^8*y +504*x^6*y^3 +756*x^4*y^5 +504*x^2*y^7 +126*y^9
   -280*x^6*y -840*x^4*y^3 -840*x^2*y^5 -280*y^7 +210*x^4*y +420*x^2*y^3 +210*y^5 -60*x^2*y -60*y^3 +5*y.
R_9^3(r) cos(3*phi) = 1/10*5^(1/2) Z_48 = 84*x^9 -504*x^5*y^4 -672*x^3*y^6 -252*x*y^8 -168*x^7
   +168*x^5*y^2 +840*x^3*y^4 +504*x*y^6 +105*x^5 -210*x^3*y^2 -315*x*y^4 -20*x^3 +60*x*y^2.
R_9^3(r) sin(3*phi) = 1/10*5^(1/2) Z_49 = 252*x^8*y +672*x^6*y^3 +504*x^4*y^5 -84*y^9 -504*x^6*y
   -840*x^4*y^3 -168*x^2*y^5 +168*y^7 +315*x^4*y +210*x^2*y^3 -105*y^5 -60*x^2*y +20*y^3.
R_9^5(r) cos(5*phi) = 1/10*5^(1/2) Z_50 = 36*x^9 -288*x^7*y^2 -504*x^5*y^4 +180*x*y^8 -56*x^7
   +504*x^5*y^2 +280*x^3*y^4 -280*x*y^6 +21*x^5 -210*x^3*y^2 +105*x*y^4.
R_9^5(r) sin(5*phi) = 1/10*5^(1/2) Z_51 = 180*x^8*y -504*x^4*y^5 -288*x^2*y^7 +36*y^9 -280*x^6*y
   +280*x^4*y^3 +504*x^2*y^5 -56*y^7 +105*x^4*y -210*x^2*y^3 +21*y^5.
R_9^7(r) cos(7*phi) = 1/10*5^(1/2) Z_52 = 9*x^9 -180*x^7*y^2 +126*x^5*y^4 +252*x^3*y^6 -63*x*y^8
   -8*x^7 +168*x^5*y^2 -280*x^3*y^4 +56*x*y^6.
R_9^7(r) sin(7*phi) = 1/10*5^(1/2) Z_53 = 63*x^8*y -252*x^6*y^3 -126*x^4*y^5 +180*x^2*y^7 -9*y^9
   -56*x^6*y +280*x^4*y^3 -168*x^2*y^5 +8*y^7.
R_9^9(r) cos(9*phi) = 1/10*5^(1/2) Z_54 = x^9 -36*x^7*y^2 +126*x^5*y^4 -84*x^3*y^6 +9*x*y^8.
R_9^9(r) sin(9*phi) = 1/10*5^(1/2) Z_55 = 9*x^8*y -84*x^6*y^3 +126*x^4*y^5 -36*x^2*y^7 +y^9.
```

If m is odd, some of these lines are redundant; then the transformation from $\cos(m\varphi)$ to $\sin(m\varphi)$ and vice versa is a straight exchange of x and y plus a multiplication by $(-1)^{\lfloor m/2 \rfloor}$.

E. Product Expansion (Linearization Coefficients)

Products of Zernike functions are products $R_{n_1}^{m_1} R_{n_2}^{m_2}$ of the radial polynomials by products of azimuthal functions of essentially three different types [1, 4.3],

$$\cos(m_1\varphi)\cos(m_2\varphi) = \frac{1}{2}\cos[(m_1 - m_2)\varphi] + \frac{1}{2}\cos[(m_1 + m_2)\varphi]; \tag{27}$$

$$\sin(m_1\varphi)\cos(m_2\varphi) = \frac{1}{2}\sin[(m_1 - m_2)\varphi] + \frac{1}{2}\sin[(m_1 + m_2)\varphi]; \tag{28}$$

$$\sin(m_1\varphi)\sin(m_2\varphi) = \frac{1}{2}\cos[(m_1 - m_2)\varphi] - \frac{1}{2}\cos[(m_1 + m_2)\varphi]. \tag{29}$$

Since the azimuthal terms couple to $m_3 = m_1 \pm m_2$, most applications seek an expansion of the form

$$R_{n_1}^{m_1}(r) R_{n_2}^{m_2}(r) = \sum_{n_3=m_3}^{n_1+n_2} g_{n_1,m_1,n_2,m_2,n_3,m_3} R_{n_3}^{m_3}(r) \tag{30}$$

given any of these two cases of m_3. The sum is only over even values of $n_1 + n_2 - n_3$. Equations (8) and (30) establish the sum rule

$$\sum_{n_3=(n_1+n_2) \mod 2}^{n_1+n_2} g_{n_1,m_1,n_2,m_2,n_3,m_3} = 1 \tag{31}$$

for the linearization coefficients.

The orthogonality (6) rewrites (30) as

$$g_{n_1,m_1,n_2,m_2,n_3,m_3} = 2(n_3+1)\int_0^1 r R_{n_1}^{m_1}(r) R_{n_2}^{m_2}(r) R_{n_3}^{m_3}(r) dr. \tag{32}$$

Threefold use of (1) reduces the right hand side to a triple sum over elementary integrals over polynomials in r,

$$g_{n_1,m_1,n_2,m_2,n_3,m_3} = 2(n_3+1)\sum_{s_1=0}^{-a_1}\sum_{s_2=0}^{-a_2}\sum_{s_3=0}^{-a_3}\frac{1}{n_1+n_2+n_3+2(1-s_1-s_2-s_3)}\prod_{j=1}^{3}(-1)^{s_j}\binom{n_j-s_j}{s_j}\binom{n_j-2s_j}{-a_j-s_j}. \tag{33}$$

As an alternative, Bailey resummation [20] of the polynomial product on the left hand side of (30) with $\sigma = s_1+s_2$ and $1+m_j = 1-b_j+a_j$ for $j=1,2$ gives

$$\begin{aligned} R_{n_1}^{m_1} R_{n_2}^{m_2} &= (-1)^{a_1+a_2}\binom{-b_1}{-a_1}\binom{-b_2}{-a_2} r^{m_1+m_2}\sum_{s_1=0}^{-a_1}\sum_{s_2=0}^{-a_2}\frac{(a_1)_{s_1}(1-b_1)_{s_1}}{(1+a_1-b_1)_{s_1}s_1!}\frac{(a_2)_{s_2}(1-b_2)_{s_2}}{(1+a_2-b_2)_{s_2}s_2!}r^{2(s_1+s_2)} \qquad (34)\\ &= (-1)^{a_1+a_2}\binom{-b_1}{-a_1}\binom{-b_2}{-a_2} r^{m_1+m_2} \\ &\quad\times \sum_{\sigma=0}^{-a_1-a_2} r^{2\sigma}\frac{(a_2)_\sigma(1-b_2)_\sigma}{(1+a_2-b_2)_\sigma\sigma!}\,{}_4F_3(a_1,-\sigma,1-b_1,-a_2+b_2-\sigma;b_2-\sigma,1+a_1-b_1,1-a_2-\sigma;1). \qquad (35)\end{aligned}$$

(The terminating Hypergeometric Function ${}_4F_3$ at the right hand side is "well poised" and has various other representations [20, 24].) This points at two more ways besides (33) to compute the g:

1. Comparing coefficients of equal powers of r on both sides of (30), we obtain a linear system of equations. g with row index n_3 is the column vector of unknowns, the matrix has entries of the form

$$(-1)^{a_3}\binom{-b_3}{-a_3}\frac{(a_3)_{s_3}(1-b_3)_{s_3}}{(1+m_3)_{s_3}s_3!} \tag{36}$$

   with column index n_3 and row index s_3, and the constant vector is given by the coefficients of (35) with row index $s_3 = \sigma_3 + (m_1+m_2-m_3)/2$.

2. Substitution of the terms $r^{m_1+m_2+2\sigma}$ in (35) by (5) also converts the product to the format demanded by (30).

Omitting the trivial case of either n_1 or n_2 being zero, and showing only the cases $n_1 \le n_2$ (the others follow by swapping the two factors on the left hand sides) for $m_3 = m_1 \pm m_2$, examples of (30) are:

```
R_1^1(r)*R_1^1(r) = R_2^2(r)
   = 1/2*R_0^0(r) +1/2*R_2^0(r).
R_1^1(r)*R_2^0(r) = 1/3*R_1^1(r) +2/3*R_3^1(r).
R_1^1(r)*R_2^2(r) = R_3^3(r)
   = 2/3*R_1^1(r) +1/3*R_3^1(r).
R_1^1(r)*R_3^1(r) = 1/4*R_2^2(r) +3/4*R_4^2(r)
   = 1/2*R_2^0(r) +1/2*R_4^0(r).
R_1^1(r)*R_3^3(r) = R_4^4(r)
   = 3/4*R_2^2(r) +1/4*R_4^2(r).
R_2^0(r)*R_2^0(r) = 1/3*R_0^0(r) +2/3*R_4^0(r).
R_2^0(r)*R_2^2(r) = 1/2*R_2^2(r) +1/2*R_4^2(r).
R_2^2(r)*R_2^2(r) = R_4^4(r)
   = 1/3*R_0^0(r) +1/2*R_2^0(r) +1/6*R_4^0(r).
R_1^1(r)*R_4^0(r) = 2/5*R_3^1(r) +3/5*R_5^1(r).
R_1^1(r)*R_4^2(r) = 1/5*R_3^3(r) +4/5*R_5^3(r)
   = 3/5*R_3^1(r) +2/5*R_5^1(r).
R_1^1(r)*R_4^4(r) = R_5^5(r)
   = 4/5*R_3^3(r) +1/5*R_5^3(r).
R_2^0(r)*R_3^1(r) = 1/3*R_1^1(r) +1/15*R_3^1(r) +3/5*R_5^1(r).
R_2^0(r)*R_3^3(r) = 3/5*R_3^3(r) +2/5*R_5^3(r).
R_2^2(r)*R_3^1(r) = 2/5*R_3^3(r) +3/5*R_5^3(r)
   = 1/6*R_1^1(r) +8/15*R_3^1(r) +3/10*R_5^1(r).
```

```
R_2^2(r)*R_3^3(r) = R_5^5(r)
   = 1/2*R_1^1(r) +2/5*R_3^1(r) +1/10*R_5^1(r).
R_1^1(r)*R_5^1(r) = 1/3*R_4^2(r) +2/3*R_6^2(r)
   = 1/2*R_4^0(r) +1/2*R_6^0(r).
R_1^1(r)*R_5^3(r) = 1/6*R_4^4(r) +5/6*R_6^4(r)
   = 2/3*R_4^2(r) +1/3*R_6^2(r).
R_1^1(r)*R_5^5(r) = R_6^6(r)
   = 5/6*R_4^4(r) +1/6*R_6^4(r).
R_2^0(r)*R_4^0(r) = 2/5*R_2^0(r) +3/5*R_6^0(r).
R_2^0(r)*R_4^2(r) = 3/10*R_2^2(r) +1/6*R_4^2(r) +8/15*R_6^2(r).
R_2^0(r)*R_4^4(r) = 2/3*R_4^4(r) +1/3*R_6^4(r).
R_2^2(r)*R_4^0(r) = 1/10*R_2^2(r) +1/2*R_4^2(r) +2/5*R_6^2(r).
R_2^2(r)*R_4^2(r) = 1/3*R_4^4(r) +2/3*R_6^4(r)
   = 3/10*R_2^0(r) +1/2*R_4^0(r) +1/5*R_6^0(r).
R_2^2(r)*R_4^4(r) = R_6^6(r)
   = 3/5*R_2^2(r) +1/3*R_4^2(r) +1/15*R_6^2(r).
R_3^1(r)*R_3^1(r) = 2/5*R_2^2(r) +3/5*R_6^2(r)
   = 1/4*R_0^0(r) +1/20*R_2^0(r) +1/4*R_4^0(r) +9/20*R_6^0(r).
R_3^1(r)*R_3^3(r) = 1/2*R_4^4(r) +1/2*R_6^4(r)
   = 3/10*R_2^2(r) +1/2*R_4^2(r) +1/5*R_6^2(r).
R_3^3(r)*R_3^3(r) = R_6^6(r)
   = 1/4*R_0^0(r) +9/20*R_2^0(r) +1/4*R_4^0(r) +1/20*R_6^0(r).
R_1^1(r)*R_6^0(r) = 3/7*R_5^1(r) +4/7*R_7^1(r).
R_1^1(r)*R_6^2(r) = 2/7*R_5^3(r) +5/7*R_7^3(r)
   = 4/7*R_5^1(r) +3/7*R_7^1(r).
R_1^1(r)*R_6^4(r) = 1/7*R_5^5(r) +6/7*R_7^5(r)
   = 5/7*R_5^3(r) +2/7*R_7^3(r).
R_1^1(r)*R_6^6(r) = R_7^7(r)
   = 6/7*R_5^5(r) +1/7*R_7^5(r).
R_2^0(r)*R_5^1(r) = 2/5*R_3^1(r) +1/35*R_5^1(r) +4/7*R_7^1(r).
R_2^0(r)*R_5^3(r) = 4/15*R_3^3(r) +9/35*R_5^3(r) +10/21*R_7^3(r).
R_2^0(r)*R_5^5(r) = 5/7*R_5^5(r) +2/7*R_7^5(r).
R_2^2(r)*R_5^1(r) = 1/15*R_3^3(r) +16/35*R_5^3(r) +10/21*R_7^3(r)
   = 1/5*R_3^1(r) +18/35*R_5^1(r) +2/7*R_7^1(r).
R_2^2(r)*R_5^3(r) = 2/7*R_5^5(r) +5/7*R_7^5(r)
   = 2/5*R_3^1(r) +16/35*R_5^1(r) +1/7*R_7^1(r).
R_2^2(r)*R_5^5(r) = R_7^7(r)
   = 2/3*R_3^3(r) +2/7*R_5^3(r) +1/21*R_7^3(r).
R_3^1(r)*R_4^0(r) = 1/5*R_1^1(r) +1/5*R_3^1(r) +3/35*R_5^1(r) +18/35*R_7^1(r).
R_3^1(r)*R_4^2(r) = 2/5*R_3^3(r) +1/35*R_5^3(r) +4/7*R_7^3(r)
   = 3/10*R_1^1(r) +5/14*R_5^1(r) +12/35*R_7^1(r).
R_3^1(r)*R_4^4(r) = 4/7*R_5^5(r) +3/7*R_7^5(r)
   = 2/5*R_3^3(r) +16/35*R_5^3(r) +1/7*R_7^3(r).
R_3^3(r)*R_4^0(r) = 1/5*R_3^3(r) +18/35*R_5^3(r) +2/7*R_7^3(r).
R_3^3(r)*R_4^2(r) = 3/7*R_5^5(r) +4/7*R_7^5(r)
   = 1/10*R_1^1(r) +2/5*R_3^1(r) +27/70*R_5^1(r) +4/35*R_7^1(r).
R_3^3(r)*R_4^4(r) = R_7^7(r)
   = 2/5*R_1^1(r) +2/5*R_3^1(r) +6/35*R_5^1(r) +1/35*R_7^1(r).
R_1^1(r)*R_7^1(r) = 3/8*R_6^2(r) +5/8*R_8^2(r)
   = 1/2*R_6^0(r) +1/2*R_8^0(r).
R_1^1(r)*R_7^3(r) = 1/4*R_6^4(r) +3/4*R_8^4(r)
   = 5/8*R_6^2(r) +3/8*R_8^2(r).
R_1^1(r)*R_7^5(r) = 1/8*R_6^6(r) +7/8*R_8^6(r)
   = 3/4*R_6^4(r) +1/4*R_8^4(r).
R_1^1(r)*R_7^7(r) = R_8^8(r)
   = 7/8*R_6^6(r) +1/8*R_8^6(r).
R_2^0(r)*R_6^0(r) = 3/7*R_4^0(r) +4/7*R_8^0(r).
R_2^0(r)*R_6^2(r) = 8/21*R_4^2(r) +1/12*R_6^2(r) +15/28*R_8^2(r).
R_2^0(r)*R_6^4(r) = 5/21*R_4^4(r) +1/3*R_6^4(r) +3/7*R_8^4(r).
R_2^0(r)*R_6^6(r) = 3/4*R_6^6(r) +1/4*R_8^6(r).
R_2^2(r)*R_6^0(r) = 1/7*R_4^2(r) +1/2*R_6^2(r) +5/14*R_8^2(r).
R_2^2(r)*R_6^2(r) = 1/21*R_4^4(r) +5/12*R_6^4(r) +15/28*R_8^4(r)
   = 2/7*R_4^0(r) +1/2*R_6^0(r) +3/14*R_8^0(r).
R_2^2(r)*R_6^4(r) = 1/4*R_6^6(r) +3/4*R_8^6(r)
```

```
   = 10/21*R_4^2(r) +5/12*R_6^2(r) +3/28*R_8^2(r).
R_2^2(r)*R_6^6(r) = R_8^8(r)
   = 5/7*R_4^4(r) +1/4*R_6^4(r) +1/28*R_8^4(r).
R_3^1(r)*R_5^1(r) = 3/20*R_2^2(r) +25/84*R_4^2(r) +1/60*R_6^2(r) +15/28*R_8^2(r)
   = 3/10*R_2^0(r) +1/14*R_4^0(r) +1/5*R_6^0(r) +3/7*R_8^0(r).
R_3^1(r)*R_5^3(r) = 8/21*R_4^4(r) +1/12*R_6^4(r) +15/28*R_8^4(r)
   = 3/10*R_2^2(r) +1/42*R_4^2(r) +49/120*R_6^2(r) +15/56*R_8^2(r).
R_3^1(r)*R_5^5(r) = 5/8*R_6^6(r) +3/8*R_8^6(r)
   = 10/21*R_4^4(r) +5/12*R_6^4(r) +3/28*R_8^4(r).
R_3^3(r)*R_5^1(r) = 1/7*R_4^4(r) +1/2*R_6^4(r) +5/14*R_8^4(r)
   = 1/20*R_2^2(r) +9/28*R_4^2(r) +9/20*R_6^2(r) +5/28*R_8^2(r).
R_3^3(r)*R_5^3(r) = 3/8*R_6^6(r) +5/8*R_8^6(r)
   = 1/5*R_2^0(r) +3/7*R_4^0(r) +3/10*R_6^0(r) +1/14*R_8^0(r).
R_3^3(r)*R_5^5(r) = R_8^8(r)
   = 1/2*R_2^2(r) +5/14*R_4^2(r) +1/8*R_6^2(r) +1/56*R_8^2(r).
R_4^0(r)*R_4^0(r) = 1/5*R_0^0(r) +2/7*R_4^0(r) +18/35*R_8^0(r).
R_4^0(r)*R_4^2(r) = 3/10*R_2^2(r) +1/14*R_4^2(r) +1/5*R_6^2(r) +3/7*R_8^2(r).
R_4^0(r)*R_4^4(r) = 2/7*R_4^4(r) +1/2*R_6^4(r) +3/14*R_8^4(r).
R_4^2(r)*R_4^2(r) = 3/7*R_4^4(r) +4/7*R_8^4(r)
   = 1/5*R_0^0(r) +1/10*R_2^0(r) +1/14*R_4^0(r) +2/5*R_6^0(r) +8/35*R_8^0(r).
R_4^2(r)*R_4^4(r) = 1/2*R_6^6(r) +1/2*R_8^6(r)
   = 1/5*R_2^2(r) +3/7*R_4^2(r) +3/10*R_6^2(r) +1/14*R_8^2(r).
R_4^4(r)*R_4^4(r) = R_8^8(r)
   = 1/5*R_0^0(r) +2/5*R_2^0(r) +2/7*R_4^0(r) +1/10*R_6^0(r) +1/70*R_8^0(r).
```

Recursive application expands triple, quadruple etc. products of Zernike functions.

III. 3D ZERNIKE FUNCTIONS

A. Radial Polynomials

1. Definition

The radial polynomials of the 3D Zernike functions are [11, 14, 17]

$$R_n^{(l)}(r) = \frac{\sqrt{2n+3}}{2^{n-l}}\frac{(-1)^{(n-l)/2}}{\binom{n}{l}}\sum_{s=0}^{(n-l)/2}(-1)^s\binom{n}{(n-l)/2-s}\binom{l+s}{l}\binom{l+1+n+2s}{n-l}r^{l+2s} \tag{37}$$

$$= \frac{\sqrt{2n+3}}{2^{n-l}}\frac{1}{\binom{n}{l}}\sum_{s=0}^{(n-l)/2}(-1)^s\binom{n}{s}\binom{l+\frac{n-l}{2}-s}{l}\binom{2n+1-2s}{n-l}r^{n-2s}, \tag{38}$$

defined for $0 \le l \le n$, even $n-l$, and normalized by design as

$$\int_0^1 r^2 R_n^{(l)}(r)R_{n'}^{(l)}(r)dr = \delta_{n,n'}. \tag{39}$$

A noteworthy special value is

$$R_n^{(l)}(1) = \sqrt{2n+3}, \tag{40}$$

which is derived from representations as terminating Hypergeometric Functions or Jacobi Polynomials [14][8, (2.6)]

$$R_n^{(l)}(r) = \frac{\sqrt{2n+3}}{2^{n-l}}\frac{\binom{(l+n)/2}{l}\binom{1+2n}{n-l}}{\binom{n}{l}}r^n\,{}_2F_1\left(-\alpha,\alpha-n-\frac{1}{2};-n-\frac{1}{2};\frac{1}{r^2}\right) \tag{41}$$

$$= \sqrt{2n+3}\frac{(q)_\alpha}{\alpha!}(-1)^\alpha r^l\,{}_2F_1\left(-\alpha,q+\alpha;q;r^2\right) \tag{42}$$

$$= \sqrt{2n+3}r^l P_\alpha^{(0,q-1)}(2r^2-1); \quad \alpha \equiv (n-l)/2; \quad q \equiv l+3/2, \tag{43}$$

via equations (15.4.6) and (22.4.1) of [1]. To set them apart from the radial polynomials of Section II, the upper index is enclosed in parentheses. A stylistic difference to the 2D case is that Noll [16] maintained integer coefficients with the polynomials R_n^m by removing a factor $\sqrt{2n+2}$ from the R_n^m and a factor $\sqrt{\pi}$ from the azimuths, which resurface at places like (15) and (6). Examples of (38) for small n are:

```
R_0^(0)(r) = 3^(1/2).
R_1^(1)(r) = 5^(1/2)*r.
R_2^(0)(r) = 1/2*7^(1/2)*( -3 +5*r^2).
R_2^(2)(r) = 7^(1/2)*r^2.
R_3^(1)(r) = 3/2*r*( -5 +7*r^2).
R_3^(3)(r) = 3*r^3.
R_4^(0)(r) = 1/8*11^(1/2)*(15 -70*r^2 +63*r^4).
R_4^(2)(r) = 1/2*11^(1/2)*r^2*( -7 +9*r^2).
R_4^(4)(r) = 11^(1/2)*r^4.
R_5^(1)(r) = 1/8*13^(1/2)*r*(35 -126*r^2 +99*r^4).
R_5^(3)(r) = 1/2*13^(1/2)*r^3*( -9 +11*r^2).
R_5^(5)(r) = 13^(1/2)*r^5.
R_6^(0)(r) = 1/16*15^(1/2)*( -35 +315*r^2 -693*r^4 +429*r^6).
R_6^(2)(r) = 1/8*15^(1/2)*r^2*(63 -198*r^2 +143*r^4).
R_6^(4)(r) = 1/2*15^(1/2)*r^4*( -11 +13*r^2).
R_6^(6)(r) = 15^(1/2)*r^6.
R_7^(1)(r) = 1/16*17^(1/2)*r*( -105 +693*r^2 -1287*r^4 +715*r^6).
R_7^(3)(r) = 1/8*17^(1/2)*r^3*(99 -286*r^2 +195*r^4).
R_7^(5)(r) = 1/2*17^(1/2)*r^5*( -13 +15*r^2).
R_7^(7)(r) = 17^(1/2)*r^7.
R_8^(0)(r) = 1/128*19^(1/2)*(315 -4620*r^2 +18018*r^4 -25740*r^6 +12155*r^8).
R_8^(2)(r) = 1/16*19^(1/2)*r^2*( -231 +1287*r^2 -2145*r^4 +1105*r^6).
R_8^(4)(r) = 1/8*19^(1/2)*r^4*(143 -390*r^2 +255*r^4).
R_8^(6)(r) = 1/2*19^(1/2)*r^6*( -15 +17*r^2).
R_8^(8)(r) = 19^(1/2)*r^8.
R_9^(1)(r) = 1/128*21^(1/2)*r*(1155 -12012*r^2 +38610*r^4 -48620*r^6 +20995*r^8).
R_9^(3)(r) = 1/16*21^(1/2)*r^3*( -429 +2145*r^2 -3315*r^4 +1615*r^6).
R_9^(5)(r) = 1/8*21^(1/2)*r^5*(195 -510*r^2 +323*r^4).
R_9^(7)(r) = 1/2*21^(1/2)*r^7*( -17 +19*r^2).
R_9^(9)(r) = 21^(1/2)*r^9.
R_10^(0)(r) = 1/256*23^(1/2)*( -693 +15015*r^2 -90090*r^4 +218790*r^6 -230945*r^8 +88179*r^10).
R_10^(2)(r) = 1/128*23^(1/2)*r^2*(3003 -25740*r^2 +72930*r^4 -83980*r^6 +33915*r^8).
R_10^(4)(r) = 1/16*23^(1/2)*r^4*( -715 +3315*r^2 -4845*r^4 +2261*r^6).
R_10^(6)(r) = 1/8*23^(1/2)*r^6*(255 -646*r^2 +399*r^4).
R_10^(8)(r) = 1/2*23^(1/2)*r^8*( -19 +21*r^2).
R_10^(10)(r) = 23^(1/2)*r^10.
R_11^(1)(r) = 5/256*r*( -3003 +45045*r^2 -218790*r^4 +461890*r^6 -440895*r^8 +156009*r^10).
R_11^(3)(r) = 5/128*r^3*(6435 -48620*r^2 +125970*r^4 -135660*r^6 +52003*r^8).
R_11^(5)(r) = 5/16*r^5*( -1105 +4845*r^2 -6783*r^4 +3059*r^6).
R_11^(7)(r) = 5/8*r^7*(323 -798*r^2 +483*r^4).
R_11^(9)(r) = 5/2*r^9*( -21 +23*r^2).
R_11^(11)(r) = 5*r^11.
R_12^(0)(r) = 3/1024*3^(1/2)*(3003 -90090*r^2 +765765*r^4 -2771340*r^6 +4849845*r^8 -4056234*r^10
   +1300075*r^12).
R_12^(2)(r) = 3/256*3^(1/2)*r^2*( -9009 +109395*r^2 -461890*r^4 +881790*r^6 -780045*r^8 +260015*r^10).
R_12^(4)(r) = 3/128*3^(1/2)*r^4*(12155 -83980*r^2 +203490*r^4 -208012*r^6 +76475*r^8).
R_12^(6)(r) = 3/16*3^(1/2)*r^6*( -1615 +6783*r^2 -9177*r^4 +4025*r^6).
R_12^(8)(r) = 3/8*3^(1/2)*r^8*(399 -966*r^2 +575*r^4).
R_12^(10)(r) = 3/2*3^(1/2)*r^10*( -23 +25*r^2).
R_12^(12)(r) = 3*3^(1/2)*r^12.
R_13^(1)(r) = 1/1024*29^(1/2)*r*(15015 -306306*r^2 +2078505*r^4 -6466460*r^6 +10140585*r^8
   -7800450*r^10 +2340135*r^12).
R_13^(3)(r) = 1/256*29^(1/2)*r^3*( -21879 +230945*r^2 -881790*r^4 +1560090*r^6 -1300075*r^8
   +412965*r^10).
R_13^(5)(r) = 1/128*29^(1/2)*r^5*(20995 -135660*r^2 +312018*r^4 -305900*r^6 +108675*r^8).
R_13^(7)(r) = 1/16*29^(1/2)*r^7*( -2261 +9177*r^2 -12075*r^4 +5175*r^6).
R_13^(9)(r) = 1/8*29^(1/2)*r^9*(483 -1150*r^2 +675*r^4).
R_13^(11)(r) = 1/2*29^(1/2)*r^11*( -25 +27*r^2).
R_13^(13)(r) = 29^(1/2)*r^13.
```

2. Inverse Representation

Inversion of the representations (38) defines coefficients $f_{j,n,l}$,

$$r^j \equiv \sum_{n=l \mod 2}^{j} f_{j,n,l} R_n^{(l)}(r), \quad j-l \text{ even}. \tag{44}$$

The projection technique equivalent to the 2D case based on the orthogonality (39), (42) and [9, 7.512.2] yields

$$f_{j,n,l} = \int_0^1 r^{j+2} R_n^{(l)}(r) dr = \frac{\sqrt{2n+3}}{2^{n-l}} \frac{1}{\binom{n}{l}} \sum_{s=0}^{(n-l)/2} \frac{(-1)^s}{j+3+n-2s} \binom{n}{s} \binom{l+\frac{n-l}{2}-s}{l} \binom{2n+1-2s}{n-l} \tag{45}$$

$$= \sqrt{2n+3} \frac{1}{j+3+l} \frac{\left(\frac{j-n}{2}+1\right)_\alpha}{\left(\frac{j-l}{2}+q+1\right)_\alpha}. \tag{46}$$

Equation (44) evaluated at $r=1$ using (40) establishes the sum rule

$$\sum_{n=l \mod 2}^{j} \sqrt{2n+3} f_{j,n,l} = 1. \tag{47}$$

Recurrences derived from (46) are

$$f_{j+2,n,l} = \frac{(j+3+l)(j-l+2)}{(j-n+2)(j+n+5)} f_{j,n,l}; \tag{48}$$

$$f_{j,n+2,l} = \frac{j-n}{j+5+n} \sqrt{\frac{2n+7}{2n+3}} f_{j,n,l}; \tag{49}$$

$$f_{j,n,l+2} = \frac{j+3+l}{j-l} f_{j,n,l}. \tag{50}$$

Examples of (44) for small powers j are:

```
r^0 = 1/3*3^(1/2)*R_0^(0)(r).
r^1 = 1/5*5^(1/2)*R_1^(1)(r).
r^2 = 1/5*3^(1/2)*R_0^(0)(r) +2/35*7^(1/2)*R_2^(0)(r)
  = 1/7*7^(1/2)*R_2^(2)(r).
r^3 = 1/7*5^(1/2)*R_1^(1)(r) +2/21*R_3^(1)(r)
  = 1/3*R_3^(3)(r).
r^4 = 1/7*3^(1/2)*R_0^(0)(r) +4/63*7^(1/2)*R_2^(0)(r) +8/693*11^(1/2)*R_4^(0)(r)
  = 1/9*7^(1/2)*R_2^(2)(r) +2/99*11^(1/2)*R_4^(2)(r)
  = 1/11*11^(1/2)*R_4^(4)(r).
r^5 = 1/9*5^(1/2)*R_1^(1)(r) +4/33*R_3^(1)(r) +8/1287*13^(1/2)*R_5^(1)(r)
  = 3/11*R_3^(3)(r) +2/143*13^(1/2)*R_5^(3)(r)
  = 1/13*13^(1/2)*R_5^(5)(r).
r^6 = 1/9*3^(1/2)*R_0^(0)(r) +2/33*7^(1/2)*R_2^(0)(r) +8/429*11^(1/2)*R_4^(0)(r)
    +16/6435*15^(1/2)*R_6^(0)(r)
  = 1/11*7^(1/2)*R_2^(2)(r) +4/143*11^(1/2)*R_4^(2)(r) +8/2145*15^(1/2)*R_6^(2)(r)
  = 1/13*11^(1/2)*R_4^(4)(r) +2/195*15^(1/2)*R_6^(4)(r)
  = 1/15*15^(1/2)*R_6^(6)(r).
r^7 = 1/11*5^(1/2)*R_1^(1)(r) +18/143*R_3^(1)(r) +8/715*13^(1/2)*R_5^(1)(r)
    +16/12155*17^(1/2)*R_7^(1)(r)
  = 3/13*R_3^(3)(r) +4/195*13^(1/2)*R_5^(3)(r) +8/3315*17^(1/2)*R_7^(3)(r)
  = 1/15*13^(1/2)*R_5^(5)(r) +2/255*17^(1/2)*R_7^(5)(r)
  = 1/17*17^(1/2)*R_7^(7)(r).
r^8 = 1/11*3^(1/2)*R_0^(0)(r) +8/143*7^(1/2)*R_2^(0)(r) +16/715*11^(1/2)*R_4^(0)(r)
    +64/12155*15^(1/2)*R_6^(0)(r) +128/230945*19^(1/2)*R_8^(0)(r)
  = 1/13*7^(1/2)*R_2^(2)(r) +2/65*11^(1/2)*R_4^(2)(r) +8/1105*15^(1/2)*R_6^(2)(r)
    +16/20995*19^(1/2)*R_8^(2)(r)
  = 1/15*11^(1/2)*R_4^(4)(r) +4/255*15^(1/2)*R_6^(4)(r) +8/4845*19^(1/2)*R_8^(4)(r)
```

```
  = 1/17*15^(1/2)*R_6^(6)(r) +2/323*19^(1/2)*R_8^(6)(r)
  = 1/19*19^(1/2)*R_8^(8)(r).
r^9 = 1/13*5^(1/2)*R_1^(1)(r) +8/65*R_3^(1)(r) +16/1105*13^(1/2)*R_5^(1)(r)
    +64/20995*17^(1/2)*R_7^(1)(r) +128/440895*21^(1/2)*R_9^(1)(r)
  = 1/5*R_3^(3)(r) +2/85*13^(1/2)*R_5^(3)(r) +8/1615*17^(1/2)*R_7^(3)(r) +16/33915*21^(1/2)*R_9^(3)(r)
  = 1/17*13^(1/2)*R_5^(5)(r) +4/323*17^(1/2)*R_7^(5)(r) +8/6783*21^(1/2)*R_9^(5)(r)
  = 1/19*17^(1/2)*R_7^(7)(r) +2/399*21^(1/2)*R_9^(7)(r)
  = 1/21*21^(1/2)*R_9^(9)(r).
r^10 = 1/13*3^(1/2)*R_0^(0)(r) +2/39*7^(1/2)*R_2^(0)(r) +16/663*11^(1/2)*R_4^(0)(r)
    +32/4199*15^(1/2)*R_6^(0)(r) +128/88179*19^(1/2)*R_8^(0)(r) +256/2028117*23^(1/2)*R_10^(0)(r)
  = 1/15*7^(1/2)*R_2^(2)(r) +8/255*11^(1/2)*R_4^(2)(r) +16/1615*15^(1/2)*R_6^(2)(r)
    +64/33915*19^(1/2)*R_8^(2)(r) +128/780045*23^(1/2)*R_10^(2)(r)
  = 1/17*11^(1/2)*R_4^(4)(r) +6/323*15^(1/2)*R_6^(4)(r) +8/2261*19^(1/2)*R_8^(4)(r)
    +16/52003*23^(1/2)*R_10^(4)(r)
  = 1/19*15^(1/2)*R_6^(6)(r) +4/399*19^(1/2)*R_8^(6)(r) +8/9177*23^(1/2)*R_10^(6)(r)
  = 1/21*19^(1/2)*R_8^(8)(r) +2/483*23^(1/2)*R_10^(8)(r)
  = 1/23*23^(1/2)*R_10^(10)(r).
r^11 = 1/15*5^(1/2)*R_1^(1)(r) +2/17*R_3^(1)(r) +16/969*13^(1/2)*R_5^(1)(r)
    +32/6783*17^(1/2)*R_7^(1)(r) +128/156009*21^(1/2)*R_9^(1)(r) +256/780045*R_11^(1)(r)
  = 3/17*R_3^(3)(r) +8/323*13^(1/2)*R_5^(3)(r) +16/2261*17^(1/2)*R_7^(3)(r)
    +64/52003*21^(1/2)*R_9^(3)(r) +128/260015*R_11^(3)(r)
  = 1/19*13^(1/2)*R_5^(5)(r) +2/133*17^(1/2)*R_7^(5)(r) +8/3059*21^(1/2)*R_9^(5)(r)
    +16/15295*R_11^(5)(r)
  = 1/21*17^(1/2)*R_7^(7)(r) +4/483*21^(1/2)*R_9^(7)(r) +8/2415*R_11^(7)(r)
  = 1/23*21^(1/2)*R_9^(9)(r) +2/115*R_11^(9)(r)
  = 1/5*R_11^(11)(r).
r^12 = 1/15*3^(1/2)*R_0^(0)(r) +4/85*7^(1/2)*R_2^(0)(r) +8/323*11^(1/2)*R_4^(0)(r)
    +64/6783*15^(1/2)*R_6^(0)(r) +128/52003*19^(1/2)*R_8^(0)(r) +512/1300075*23^(1/2)*R_10^(0)(r)
    +1024/11700675*3^(1/2)*R_12^(0)(r)
  = 1/17*7^(1/2)*R_2^(2)(r) +10/323*11^(1/2)*R_4^(2)(r) +80/6783*15^(1/2)*R_6^(2)(r)
    +160/52003*19^(1/2)*R_8^(2)(r) +128/260015*23^(1/2)*R_10^(2)(r) +256/2340135*3^(1/2)*R_12^(2)(r)
  = 1/19*11^(1/2)*R_4^(4)(r) +8/399*15^(1/2)*R_6^(4)(r) +16/3059*19^(1/2)*R_8^(4)(r)
    +64/76475*23^(1/2)*R_10^(4)(r) +128/688275*3^(1/2)*R_12^(4)(r)
  = 1/21*15^(1/2)*R_6^(6)(r) +2/161*19^(1/2)*R_8^(6)(r) +8/4025*23^(1/2)*R_10^(6)(r)
    +16/36225*3^(1/2)*R_12^(6)(r)
  = 1/23*19^(1/2)*R_8^(8)(r) +4/575*23^(1/2)*R_10^(8)(r) +8/5175*3^(1/2)*R_12^(8)(r)
  = 1/25*23^(1/2)*R_10^(10)(r) +2/225*3^(1/2)*R_12^(10)(r)
  = 1/9*3^(1/2)*R_12^(12)(r).
r^13 = 1/17*5^(1/2)*R_1^(1)(r) +36/323*R_3^(1)(r) +40/2261*13^(1/2)*R_5^(1)(r)
    +320/52003*17^(1/2)*R_7^(1)(r) +384/260015*21^(1/2)*R_9^(1)(r) +512/468027*R_11^(1)(r)
    +1024/67863915*29^(1/2)*R_13^(1)(r)
  = 3/19*R_3^(3)(r) +10/399*13^(1/2)*R_5^(3)(r) +80/9177*17^(1/2)*R_7^(3)(r)
    +32/15295*21^(1/2)*R_9^(3)(r) +128/82593*R_11^(3)(r) +256/11975985*29^(1/2)*R_13^(3)(r)
  = 1/21*13^(1/2)*R_5^(5)(r) +8/483*17^(1/2)*R_7^(5)(r) +16/4025*21^(1/2)*R_9^(5)(r)
    +64/21735*R_11^(5)(r) +128/3151575*29^(1/2)*R_13^(5)(r)
  = 1/23*17^(1/2)*R_7^(7)(r) +6/575*21^(1/2)*R_9^(7)(r) +8/1035*R_11^(7)(r)
    +16/150075*29^(1/2)*R_13^(7)(r)
  = 1/25*21^(1/2)*R_9^(9)(r) +4/135*R_11^(9)(r) +8/19575*29^(1/2)*R_13^(9)(r)
  = 5/27*R_11^(11)(r) +2/783*29^(1/2)*R_13^(11)(r)
  = 1/29*29^(1/2)*R_13^(13)(r).
```

This expands r^j in a sum over $R_n^{(l)}$ at constant l. As an alternative, it might be regarded as solving (38) as a linear system of equations with a vector of unknowns from r^l to r^n,

$$\begin{pmatrix} R_l^{(l)} \\ R_{l+2}^{(l)} \\ R_{l+4}^{(l)} \\ \vdots \\ R_n^{(l)} \end{pmatrix} = \begin{pmatrix} \sqrt{2l+3} & 0 & 0 & 0 & 0 \\ \cdots & \ddots & 0 & 0 & 0 \\ & & \ddots & 0 & 0 \\ \cdots & \cdots & \cdots & \ddots & 0 \\ \cdots & \cdots & \cdots & \cdots & \ddots \end{pmatrix} \cdot \begin{pmatrix} r^l \\ r^{l+2} \\ r^{l+4} \\ \vdots \\ r^n \end{pmatrix}. \tag{51}$$

The matrix is a lower triangular matrix displaying the coefficients of (38); the equation is easily solved via forward elimination, for example. A complementary expansion in a series of $R_n^{(l)}$ with constant n

$$r^j \equiv \sum_{\substack{l=j \\ \text{mod } 2}}^{n} \hat{f}_{j,n,l} R_n^{(l)}(r), \quad j-n=0 \mod 2, \tag{52}$$

lacks the equivalent orthogonality similar to (39), but again it can be formulated as a linear system of equations,

$$\begin{pmatrix} R_n^{(l)} \\ R_n^{(l+2)} \\ R_n^{(l+4)} \\ \vdots \\ R_n^{(n)} \end{pmatrix} = \begin{pmatrix} \ddots & \cdots & \cdots & \cdots & \cdots \\ 0 & \ddots & \cdots & \cdots & \cdots \\ 0 & 0 & \ddots & & \\ 0 & 0 & 0 & \ddots & \cdots \\ 0 & 0 & 0 & 0 & \sqrt{2n+3} \end{pmatrix} \cdot \begin{pmatrix} r^l \\ r^{l+2} \\ r^{l+4} \\ \vdots \\ r^n \end{pmatrix}, \tag{53}$$

this time with an upper triangular matrix populated by the coefficients of (38), solvable with backward elimination. The sum rule according to (40) is

$$1 = \sqrt{2n+3} \sum_l \hat{f}_{j,n,l}. \tag{54}$$

Unlike (44) which turns out to be helpful in Section III E, (52) is not used further down, so we keep the table short:

```
r^0 / 3^(1/2) = 1/3*R_0^(0).
r^0 / 7^(1/2) = 5/21*R_2^(2) -2/21*R_2^(0).
r^0 / 11^(1/2) = 9/55*R_4^(4) -4/33*R_4^(2) +8/165*R_4^(0).
r^0 / 15^(1/2) = 13/105*R_6^(6) -18/175*R_6^(4) +8/105*R_6^(2) -16/525*R_6^(0).
r^0 / 19^(1/2) = 17/171*R_8^(8) -104/1197*R_8^(6) +48/665*R_8^(4) -64/1197*R_8^(2) +128/5985*R_8^(0).
r^0 / 23^(1/2) = 21/253*R_10^(10) -170/2277*R_10^(8) +1040/15939*R_10^(6) -96/1771*R_10^(4)
    +640/15939*R_10^(2) -256/15939*R_10^(0).
r^0 / 3*3^(1/2) = 25/351*R_12^(12) -28/429*R_12^(10) +680/11583*R_12^(8) -320/6237*R_12^(6)
    +128/3003*R_12^(4) -2560/81081*R_12^(2) +1024/81081*R_12^(0).
r^1 / 5^(1/2) = 1/5*R_1^(1).
r^1 / 3 = 7/45*R_3^(3) -2/45*R_3^(1).
r^1 / 13^(1/2) = 11/91*R_5^(5) -4/65*R_5^(3) +8/455*R_5^(1).
r^1 / 17^(1/2) = 5/51*R_7^(7) -22/357*R_7^(5) +8/255*R_7^(3) -16/1785*R_7^(1).
r^1 / 21^(1/2) = 19/231*R_9^(9) -40/693*R_9^(7) +16/441*R_9^(5) -64/3465*R_9^(3) +128/24255*R_9^(1).
r^1 / 5 = 23/325*R_11^(11) -38/715*R_11^(9) +16/429*R_11^(7) -32/1365*R_11^(5) +128/10725*R_11^(3)
    -256/75075*R_11^(1).
r^1 / 29^(1/2) = 9/145*R_13^(13) -92/1885*R_13^(11) +152/4147*R_13^(9) -320/12441*R_13^(7)
    +128/7917*R_13^(5) -512/62205*R_13^(3) +1024/435435*R_13^(1).
r^2 / 7^(1/2) = 1/7*R_2^(2).
r^2 / 11^(1/2) = 9/77*R_4^(4) -2/77*R_4^(2).
r^2 / 15^(1/2) = 13/135*R_6^(6) -4/105*R_6^(4) +8/945*R_6^(2).
r^2 / 19^(1/2) = 17/209*R_8^(8) -26/627*R_8^(6) +24/1463*R_8^(4) -16/4389*R_8^(2).
r^2 / 23^(1/2) = 21/299*R_10^(10) -136/3289*R_10^(8) +16/759*R_10^(6) -192/23023*R_10^(4)
    +128/69069*R_10^(2).
r^2 / 3*3^(1/2) = 5/81*R_12^(12) -14/351*R_12^(10) +272/11583*R_12^(8) -32/2673*R_12^(6)
    +128/27027*R_12^(4) -256/243243*R_12^(2).
r^3 / 3 = 1/9*R_3^(3).
r^3 / 13^(1/2) = 11/117*R_5^(5) -2/117*R_5^(3).
r^3 / 17^(1/2) = 15/187*R_7^(7) -4/153*R_7^(5) +8/1683*R_7^(3).
r^3 / 21^(1/2) = 19/273*R_9^(9) -30/1001*R_9^(7) +8/819*R_9^(5) -16/9009*R_9^(3).
r^3 / 5 = 23/375*R_11^(11) -152/4875*R_11^(9) +48/3575*R_11^(7) -64/14625*R_11^(5)
    +128/160875*R_11^(3).
r^3 / 29^(1/2) = 27/493*R_13^(13) -46/1479*R_13^(11) +304/19227*R_13^(9) -480/70499*R_13^(7)
    +128/57681*R_13^(5) -256/634491*R_13^(3).
r^4 / 11^(1/2) = 1/11*R_4^(4).
r^4 / 15^(1/2) = 13/165*R_6^(6) -2/165*R_6^(4).
r^4 / 19^(1/2) = 17/247*R_8^(8) -4/209*R_8^(6) +8/2717*R_8^(4).
r^4 / 23^(1/2) = 7/115*R_10^(10) -34/1495*R_10^(8) +8/1265*R_10^(6) -16/16445*R_10^(4).
```

```
r^4 / 3*3^(1/2) = 25/459*R_12^(12) -56/2295*R_12^(10) +16/1755*R_12^(8) -64/25245*R_12^(6)
    +128/328185*R_12^(4).
r^5 / 13^(1/2) = 1/13*R_5^(5).
r^5 / 17^(1/2) = 15/221*R_7^(7) -2/221*R_7^(5).
r^5 / 21^(1/2) = 19/315*R_9^(9) -4/273*R_9^(7) +8/4095*R_9^(5).
r^5 / 5 = 23/425*R_11^(11) -38/2125*R_11^(9) +24/5525*R_11^(7) -16/27625*R_11^(5).
r^5 / 29^(1/2) = 27/551*R_13^(13) -184/9367*R_13^(11) +16/2465*R_13^(9) -192/121771*R_13^(7)
    +128/608855*R_13^(5).
r^6 / 15^(1/2) = 1/15*R_6^(6).
r^6 / 19^(1/2) = 17/285*R_8^(8) -2/285*R_8^(6).
r^6 / 23^(1/2) = 21/391*R_10^(10) -4/345*R_10^(8) +8/5865*R_10^(6).
r^6 / 3*3^(1/2) = 25/513*R_12^(12) -14/969*R_12^(10) +8/2565*R_12^(8) -16/43605*R_12^(6).
r^7 / 17^(1/2) = 1/17*R_7^(7).
r^7 / 21^(1/2) = 19/357*R_9^(9) -2/357*R_9^(7).
r^7 / 5 = 23/475*R_11^(11) -4/425*R_11^(9) +8/8075*R_11^(7).
r^7 / 29^(1/2) = 9/203*R_13^(13) -46/3857*R_13^(11) +8/3451*R_13^(9) -16/65569*R_13^(7).
r^8 / 19^(1/2) = 1/19*R_8^(8).
r^8 / 23^(1/2) = 21/437*R_10^(10) -2/437*R_10^(8).
r^8 / 3*3^(1/2) = 25/567*R_12^(12) -4/513*R_12^(10) +8/10773*R_12^(8).
r^9 / 21^(1/2) = 1/21*R_9^(9).
r^9 / 5 = 23/525*R_11^(11) -2/525*R_11^(9).
r^9 / 29^(1/2) = 27/667*R_13^(13) -4/609*R_13^(11) +8/14007*R_13^(9).
r^10 / 23^(1/2) = 1/23*R_10^(10).
r^10 / 3*3^(1/2) = 25/621*R_12^(12) -2/621*R_12^(10).
r^11 / 5 = 1/25*R_11^(11).
r^11 / 29^(1/2) = 27/725*R_13^(13) -2/725*R_13^(11).
r^12 / 3*3^(1/2) = 1/27*R_12^(12).
r^13 / 29^(1/2) = 1/29*R_13^(13).
```

B. Basis in the Unit Sphere

Let the 3D Zernike functions

$$Z_{n,l}^{(m)} \equiv R_n^{(l)}(r) Y_l^{(m)}(\varphi,\theta); \quad 0 \le \varphi \le 2\pi; \quad 0 \le \theta \le \pi; \quad 0 \le r \le 1, \tag{55}$$

be defined with Edmonds' sign choice of the Spherical Harmonics [6, 15]

$$Y_l^{(m)} = (-1)^m \sqrt{\frac{2l+1}{4\pi}\frac{(l-m)!}{(l+m)!}} P_l^m(\cos\theta) e^{im\varphi}, \quad -l \le m \le l. \tag{56}$$

Complex conjugation, denoted by the star, yields [6, (2.5.6)]

$$Y_l^{(m)*} = (-1)^m Y_l^{(-m)}. \tag{57}$$

The latitudes are spanned via Associated Legendre Functions [6, (2.5.10)]

$$P_l^m(x) = (1-x^2)^{m/2} \frac{d^m}{dx^m} P_l(x), \quad m \ge 0, \tag{58}$$

which differs by a factor $(-1)^m$ from other sign conventions [1, 9]. Extension to negative upper indices is finally defined via

$$P_l^{-m}(x) = (-1)^m \frac{(l-m)!}{(l+m)!} P_l^m(x), \quad m > 0. \tag{59}$$

The 3D Zernike functions are products of Vector Harmonics $r^l Y_l^{(m)}$ by even polynomials in r of order $n-l$. They are ortho-normal over the unit sphere,

$$\int_{r<1} Z_{n,l}^{(m)}(r,\varphi,\theta) Z_{n',l'}^{(m')*}(r,\varphi,\theta) d^3r = \delta_{n,n'}\delta_{m,m'}\delta_{l,l'}, \quad d^3r = r^2 \sin\theta dr\, d\theta\, d\varphi. \tag{60}$$

This foundation in spherical coordinates spawns interest in transformation into (Section III C) or from (Section III D) Cartesian coordinates.

C. Zernike to Cartesian

The Spherical Harmonics are [12, (3.2),(3.3)]

$$Y_l^{(m)}(\theta,\varphi) \;=\; (-1)^m\sqrt{\frac{2l+1}{4\pi}\,\frac{(l-m)!}{(l+m)!}}2^l\sin^m\theta\sum_{\nu=0}^{l-m}\left(\frac{m+\nu+1-l}{2}\right)_l\frac{1}{\nu!(l-m-\nu)!}\cos^\nu\theta$$
$$\times\left(\sum_{j=0,2,4,\ldots}^{m}+i\sum_{j=1,3,5\ldots}^{m}\right)(-1)^{\lfloor j/2\rfloor}\binom{m}{j}\cos^{m-j}\varphi\sin^j\varphi. \tag{61}$$

Rendered as Cartesian Coordinates

$$x=r\sin\theta\cos\varphi,\quad y=r\sin\theta\cos\varphi,\quad z=r\cos\theta, \tag{62}$$

the Vector Harmonics are [12, (3.7)]

$$r^lY_l^{(m)}(\theta,\varphi) \;=\; \left(-\frac{1}{2}\right)^m\sqrt{\frac{2l+1}{4\pi}(l-m)!(l+m)!}\sum_{\sigma_1,\sigma_2\geq0}^{\sigma_1+\sigma_2\leq\frac{l-m}{2}}\frac{1}{\sigma_1!\sigma_2!}\left(-\frac{1}{4}\right)^{\sigma_1+\sigma_2}\frac{1}{(m+\sigma_1+\sigma_2)!(l-m-2(\sigma_1+\sigma_2))!}$$
$$\times\left(\sum_{j=0,2,\ldots}^{m}+i\sum_{j=1,3,5\ldots}^{m}\right)(-1)^{\lfloor j/2\rfloor}\binom{m}{j}x^{m-j+2\sigma_1}y^{j+2\sigma_2}z^{l-m-2(\sigma_1+\sigma_2)}. \tag{63}$$

This is the 3D version of Eqs. (24) and (26).

Sample outputs are tabulated with real and imaginary part separated by a comma on each right hand side, and a factor $\sqrt{\pi}$ moved to the left hand sides:

```
Pi^(1/2) r^0 Y_0^(0) = 1/2 , 0.
Pi^(1/2) r^1 Y_1^(0) = 1/2*z*3^(1/2) , 0.
Pi^(1/2) r^1 Y_1^(1) = -1/4*6^(1/2)*x ,  -1/4*6^(1/2)*y.
Pi^(1/2) r^2 Y_2^(0) = -1/4*( -2*z^2 +y^2 +x^2)*5^(1/2) , 0.
Pi^(1/2) r^2 Y_2^(1) = -1/4*30^(1/2)*x*z ,  -1/4*30^(1/2)*z*y.
Pi^(1/2) r^2 Y_2^(2) = 1/8*30^(1/2)*(x -y)*(x +y) , 1/4*30^(1/2)*x*y.
Pi^(1/2) r^3 Y_3^(0) = -1/4*7^(1/2)*( -2*z^2 +3*y^2 +3*x^2)*z , 0.
Pi^(1/2) r^3 Y_3^(1) = 1/8*x*( -4*z^2 +y^2 +x^2)*21^(1/2) , 1/8*21^(1/2)*( -4*z^2 +y^2 +x^2)*y.
Pi^(1/2) r^3 Y_3^(2) = 1/8*210^(1/2)*(x -y)*(x +y)*z , 1/4*210^(1/2)*x*y*z.
Pi^(1/2) r^3 Y_3^(3) = -1/8*x*(x^2 -3*y^2)*35^(1/2) ,  -1/8*35^(1/2)*( -y^2 +3*x^2)*y.
Pi^(1/2) r^4 Y_4^(0) = 3/2*z^4 -9/2*z^2*y^2 +9/16*y^4 -9/2*x^2*z^2 +9/8*x^2*y^2 +9/16*x^4 , 0.
Pi^(1/2) r^4 Y_4^(1) = 3/8*5^(1/2)*( -4*z^2 +3*y^2 +3*x^2)*x*z , 3/8*5^(1/2)*( -4*z^2 +3*y^2
    +3*x^2)*y*z.
Pi^(1/2) r^4 Y_4^(2) = -3/16*10^(1/2)*(x^2 -6*z^2 +y^2)*(x +y)*(x -y) ,  -3/8*10^(1/2)*x*(x^2 -6*z^2
    +y^2)*y.
Pi^(1/2) r^4 Y_4^(3) = -3/8*35^(1/2)*x*(x^2 -3*y^2)*z ,  -3/8*35^(1/2)*( -y^2 +3*x^2)*y*z.
Pi^(1/2) r^4 Y_4^(4) = 3/32*70^(1/2)*( -y^2 +2*x*y +x^2)*( -y^2 -2*x*y +x^2) , 3/8*70^(1/2)*(x -y)*(x
    +y)*x*y.
Pi^(1/2) r^5 Y_5^(0) = 1/16*11^(1/2)*(8*z^4 -40*x^2*z^2 -40*z^2*y^2 +30*x^2*y^2 +15*x^4 +15*y^4)*z , 0.
Pi^(1/2) r^5 Y_5^(1) = -1/32*x*(8*z^4 -12*z^2*y^2 +y^4 -12*x^2*z^2 +2*x^2*y^2 +x^4)*330^(1/2) ,
    -1/32*330^(1/2)*(8*z^4 -12*z^2*y^2 +y^4 -12*x^2*z^2 +2*x^2*y^2 +x^4)*y.
Pi^(1/2) r^5 Y_5^(2) = -1/16*2310^(1/2)*( -2*z^2 +y^2 +x^2)*(x -y)*(x +y)*z ,  -1/8*2310^(1/2)*x*(
    -2*z^2 +y^2 +x^2)*y*z.
Pi^(1/2) r^5 Y_5^(3) = 1/32*385^(1/2)*(x^2 -8*z^2 +y^2)*(x^2 -3*y^2)*x , 1/32*385^(1/2)*(x^2 -8*z^2
    +y^2)*( -y^2 +3*x^2)*y.
Pi^(1/2) r^5 Y_5^(4) = 3/32*770^(1/2)*( -y^2 -2*x*y +x^2)*( -y^2 +2*x*y +x^2)*z , 3/8*770^(1/2)*(x
    -y)*(x +y)*x*y*z.
Pi^(1/2) r^5 Y_5^(5) = -3/32*x*(x^4 -10*x^2*y^2 +5*y^4)*77^(1/2) ,  -3/32*77^(1/2)*(y^4 -10*x^2*y^2
    +5*x^4)*y.
Pi^(1/2) r^6 Y_6^(0) = -1/32*( -16*z^6 +120*z^4*y^2 -90*z^2*y^4 +5*y^6 +120*z^4*x^2 -180*x^2*y^2*z^2
    +15*x^2*y^4 -90*x^4*z^2 +15*x^4*y^2 +5*x^6)*13^(1/2) , 0.
Pi^(1/2) r^6 Y_6^(1) = -1/32*546^(1/2)*(8*z^4 -20*x^2*z^2 -20*z^2*y^2 +10*x^2*y^2 +5*x^4 +5*y^4)*x*z ,
     -1/32*546^(1/2)*(8*z^4 -20*x^2*z^2 -20*z^2*y^2 +10*x^2*y^2 +5*x^4 +5*y^4)*y*z.
Pi^(1/2) r^6 Y_6^(2) = 1/64*1365^(1/2)*(x^4 -16*x^2*z^2 +2*x^2*y^2 +y^4 +16*z^4 -16*z^2*y^2)*( -y
```

```
    +x)*(x +y) , 1/32*1365^(1/2)*x*(x^4 -16*x^2*z^2 +2*x^2*y^2 +y^4 +16*z^4 -16*z^2*y^2)*y.
Pi^(1/2) r^6 Y_6^(3) = 1/32*1365^(1/2)*(3*x^2 -8*z^2 +3*y^2)*(x^2 -3*y^2)*x*z , 1/32*1365^(1/2)*(3*x^2
    -8*z^2 +3*y^2)*( -y^2 +3*x^2)*y*z.
Pi^(1/2) r^6 Y_6^(4) = -3/64*182^(1/2)*(x^2 +y^2 -10*z^2)*( -y^2 -2*x*y +x^2)*( -y^2 +2*x*y +x^2) ,
    -3/16*182^(1/2)*(x^2 +y^2 -10*z^2)*(y +x)*( -y +x)*x*y.
Pi^(1/2) r^6 Y_6^(5) = -3/32*1001^(1/2)*x*(x^4 -10*x^2*y^2 +5*y^4)*z ,  -3/32*1001^(1/2)*(y^4
    -10*x^2*y^2 +5*x^4)*y*z.
Pi^(1/2) r^6 Y_6^(6) = 1/64*3003^(1/2)*( -y +x)*(y +x)*(x^2 +4*x*y +y^2)*(y^2 -4*x*y +x^2) ,
    1/32*3003^(1/2)*(x^2 -3*y^2)*( -y^2 +3*x^2)*x*y.
```

More general Cartesian representations of $r^n Y_l^{(m)}$, for even $n-l>0$, follow from there by multiplication with the trinomials

$$r^{n-l} = (x^2+y^2+z^2)^{(n-l)/2} = \sum_{\sigma_1,\sigma_2\geq 0}^{\sigma_1+\sigma_2\leq (n-l)/2} \frac{[(n-l)/2]!}{\sigma_1!\sigma_2!(\frac{n-l}{2}-\sigma_1-\sigma_2)!} x^{2\sigma_1} y^{2\sigma_2} z^{n-l-2(\sigma_1+\sigma_2)}. \tag{64}$$

Gathering terms with the aid of the tables in Section III A 1 generates Cartesian expansions for $Z_{n,l}^{(m)}$:

```
Z_0,0^(0) = 1/2*3^(1/2)/Pi^(1/2) , 0.
Z_1,1^(0) = 1/2*z/Pi^(1/2)*15^(1/2) , 0.
Z_1,1^(1) = -1/4*30^(1/2)/Pi^(1/2)*x ,  -1/4*30^(1/2)/Pi^(1/2)*y.
Z_2,0^(0) = 1/4*7^(1/2)*( -3 +5*x^2 +5*y^2 +5*z^2)/Pi^(1/2) , 0.
Z_2,2^(0) = -1/4*( -2*z^2 +y^2 +x^2)*35^(1/2)/Pi^(1/2) , 0.
Z_2,2^(1) = -1/4*210^(1/2)/Pi^(1/2)*x*z ,  -1/4*210^(1/2)/Pi^(1/2)*y*z.
Z_2,2^(2) = 1/8*210^(1/2)*( -y +x)*(y +x)/Pi^(1/2) , 1/4*210^(1/2)/Pi^(1/2)*x*y.
Z_3,1^(0) = 3/4*z*3^(1/2)*( -5 +7*x^2 +7*y^2 +7*z^2)/Pi^(1/2) , 0.
Z_3,1^(1) = -3/8*6^(1/2)*x*( -5 +7*x^2 +7*y^2 +7*z^2)/Pi^(1/2) ,  -3/8*6^(1/2)*y*( -5 +7*x^2 +7*y^2
    +7*z^2)/Pi^(1/2).
Z_3,3^(0) = -3/4*z*( -2*z^2 +3*y^2 +3*x^2)*7^(1/2)/Pi^(1/2) , 0.
Z_3,3^(1) = 3/8*21^(1/2)*x*( -4*z^2 +y^2 +x^2)/Pi^(1/2) , 3/8*21^(1/2)*y*( -4*z^2 +y^2 +x^2)/Pi^(1/2).
Z_3,3^(2) = 3/8*210^(1/2)*z*( -y +x)*(y +x)/Pi^(1/2) , 3/4*210^(1/2)/Pi^(1/2)*x*y*z.
Z_3,3^(3) = -3/8*35^(1/2)*x*(x^2 -3*y^2)/Pi^(1/2) ,  -3/8*35^(1/2)*y*(3*x^2 -y^2)/Pi^(1/2).
Z_4,0^(0) = 1/16*11^(1/2)*(15 -70*x^2 -70*y^2 -70*z^2 +63*x^4 +126*x^2*y^2 +126*x^2*z^2 +63*y^4
    +126*z^2*y^2 +63*z^4)/Pi^(1/2) , 0.
Z_4,2^(0) = -1/8*( -2*z^2 +y^2 +x^2)*55^(1/2)*( -7 +9*x^2 +9*y^2 +9*z^2)/Pi^(1/2) , 0.
Z_4,2^(1) = -1/8*330^(1/2)*x*z*( -7 +9*x^2 +9*y^2 +9*z^2)/Pi^(1/2) ,  -1/8*330^(1/2)*y*z*( -7 +9*x^2
    +9*y^2 +9*z^2)/Pi^(1/2).
Z_4,2^(2) = 1/16*330^(1/2)*(x -y)*(x +y)*( -7 +9*x^2 +9*y^2 +9*z^2)/Pi^(1/2) , 1/8*330^(1/2)*x*y*( -7
    +9*x^2 +9*y^2 +9*z^2)/Pi^(1/2).
Z_4,4^(0) = 3/16*11^(1/2)*(8*z^4 -24*z^2*y^2 +3*y^4 -24*x^2*z^2 +6*x^2*y^2 +3*x^4)/Pi^(1/2) , 0.
Z_4,4^(1) = 3/8*55^(1/2)*x*z*( -4*z^2 +3*y^2 +3*x^2)/Pi^(1/2) , 3/8*55^(1/2)*y*z*( -4*z^2 +3*y^2
    +3*x^2)/Pi^(1/2).
Z_4,4^(2) = -3/16*110^(1/2)*(x -y)*(x +y)*(x^2 -6*z^2 +y^2)/Pi^(1/2) ,  -3/8*110^(1/2)*x*y*(x^2 -6*z^2
    +y^2)/Pi^(1/2).
Z_4,4^(3) = -3/8*385^(1/2)*x*z*(x^2 -3*y^2)/Pi^(1/2) ,  -3/8*385^(1/2)*y*z*(3*x^2 -y^2)/Pi^(1/2).
Z_4,4^(4) = 3/32*770^(1/2)*( -y^2 +2*x*y +x^2)*( -y^2 -2*x*y +x^2)/Pi^(1/2) , 3/8*770^(1/2)*x*y*(x
    -y)*(x +y)/Pi^(1/2).
Z_5,1^(0) = 1/16*z*39^(1/2)*(35 -126*x^2 -126*y^2 -126*z^2 +99*x^4 +198*x^2*y^2 +198*x^2*z^2 +99*y^4
    +198*z^2*y^2 +99*z^4)/Pi^(1/2) , 0.
Z_5,1^(1) = -1/32*78^(1/2)*x*(35 -126*x^2 -126*y^2 -126*z^2 +99*x^4 +198*x^2*y^2 +198*x^2*z^2 +99*y^4
    +198*z^2*y^2 +99*z^4)/Pi^(1/2) ,  -1/32*78^(1/2)*y*(35 -126*x^2 -126*y^2 -126*z^2 +99*x^4 +198*x^2*y^2
    +198*x^2*z^2 +99*y^4 +198*z^2*y^2 +99*z^4)/Pi^(1/2).
Z_5,3^(0) = -1/8*z*( -2*z^2 +3*y^2 +3*x^2)*91^(1/2)*( -9 +11*x^2 +11*y^2 +11*z^2)/Pi^(1/2) , 0.
Z_5,3^(1) = 1/16*273^(1/2)*x*( -4*z^2 +y^2 +x^2)*( -9 +11*x^2 +11*y^2 +11*z^2)/Pi^(1/2) ,
    1/16*273^(1/2)*y*( -4*z^2 +y^2 +x^2)*( -9 +11*x^2 +11*y^2 +11*z^2)/Pi^(1/2).
Z_5,3^(2) = 1/16*2730^(1/2)*z*(x -y)*(x +y)*( -9 +11*x^2 +11*y^2 +11*z^2)/Pi^(1/2) ,
    1/8*2730^(1/2)*x*y*z*( -9 +11*x^2 +11*y^2 +11*z^2)/Pi^(1/2).
Z_5,3^(3) = -1/16*455^(1/2)*x*(x^2 -3*y^2)*( -9 +11*x^2 +11*y^2 +11*z^2)/Pi^(1/2) ,
    -1/16*455^(1/2)*y*(3*x^2 -y^2)*( -9 +11*x^2 +11*y^2 +11*z^2)/Pi^(1/2).
Z_5,5^(0) = 1/16*z*(8*z^4 -40*z^2*y^2 +15*y^4 -40*x^2*z^2 +30*x^2*y^2 +15*x^4)*143^(1/2)/Pi^(1/2) , 0.
Z_5,5^(1) = -1/32*4290^(1/2)*x*(8*z^4 -12*z^2*y^2 +y^4 -12*x^2*z^2 +2*x^2*y^2 +x^4)/Pi^(1/2) ,
    -1/32*4290^(1/2)*y*(8*z^4 -12*z^2*y^2 +y^4 -12*x^2*z^2 +2*x^2*y^2 +x^4)/Pi^(1/2).
Z_5,5^(2) = -1/16*30030^(1/2)*z*(x -y)*(x +y)*( -2*z^2 +y^2 +x^2)/Pi^(1/2) ,  -1/8*30030^(1/2)*x*y*z*(
```

```
    -2*z^2 +y^2 +x^2)/Pi^(1/2).
Z_5,5^(3) = 1/32*5005^(1/2)*x*(x^2 -3*y^2)*(x^2 -8*z^2 +y^2)/Pi^(1/2) , 1/32*5005^(1/2)*y*(3*x^2
    -y^2)*(x^2 -8*z^2 +y^2)/Pi^(1/2).
Z_5,5^(4) = 3/32*10010^(1/2)*z*( -y^2 +2*x*y +x^2)*( -y^2 -2*x*y +x^2)/Pi^(1/2) ,
    3/8*10010^(1/2)*x*y*z*(x -y)*(x +y)/Pi^(1/2).
Z_5,5^(5) = -3/32*1001^(1/2)*x*(x^4 -10*x^2*y^2 +5*y^4)/Pi^(1/2) ,  -3/32*1001^(1/2)*y*(5*x^4
    -10*x^2*y^2 +y^4)/Pi^(1/2).
Z_6,0^(0) = 1/32*15^(1/2)*( -35 +315*x^2 +315*y^2 +315*z^2 -693*x^4 -1386*x^2*y^2 -1386*x^2*z^2
    -693*y^4 -1386*z^2*y^2 -693*z^4 +429*x^6 +1287*x^4*y^2 +1287*x^4*z^2 +1287*x^2*y^4 +2574*x^2*y^2*z^2
    +1287*z^4*x^2 +429*y^6 +1287*z^2*y^4 +1287*z^4*y^2 +429*z^6)/Pi^(1/2) , 0.
Z_6,2^(0) = -5/32*3^(1/2)*( -2*z^2 +y^2 +x^2)*(63 -198*x^2 -198*y^2 -198*z^2 +143*x^4 +286*x^2*y^2
    +286*x^2*z^2 +143*y^4 +286*z^2*y^2 +143*z^4)/Pi^(1/2) , 0.
Z_6,2^(1) = -15/32*2^(1/2)*x*z*(63 -198*x^2 -198*y^2 -198*z^2 +143*x^4 +286*x^2*y^2 +286*x^2*z^2
    +143*y^4 +286*z^2*y^2 +143*z^4)/Pi^(1/2) ,  -15/32*2^(1/2)*y*z*(63 -198*x^2 -198*y^2 -198*z^2 +143*x^4
    +286*x^2*y^2 +286*x^2*z^2 +143*y^4 +286*z^2*y^2 +143*z^4)/Pi^(1/2).
Z_6,2^(2) = 15/64*2^(1/2)*(x -y)*(x +y)*(63 -198*x^2 -198*y^2 -198*z^2 +143*x^4 +286*x^2*y^2
    +286*x^2*z^2 +143*y^4 +286*z^2*y^2 +143*z^4)/Pi^(1/2) , 15/32*2^(1/2)*x*y*(63 -198*x^2 -198*y^2
    -198*z^2 +143*x^4 +286*x^2*y^2 +286*x^2*z^2 +143*y^4 +286*z^2*y^2 +143*z^4)/Pi^(1/2).
Z_6,4^(0) = 3/32*15^(1/2)*(8*z^4 -24*z^2*y^2 +3*y^4 -24*x^2*z^2 +6*x^2*y^2 +3*x^4)*( -11 +13*x^2
    +13*y^2 +13*z^2)/Pi^(1/2) , 0.
Z_6,4^(1) = 15/16*3^(1/2)*x*z*( -4*z^2 +3*y^2 +3*x^2)*( -11 +13*x^2 +13*y^2 +13*z^2)/Pi^(1/2) ,
    15/16*3^(1/2)*y*z*( -4*z^2 +3*y^2 +3*x^2)*( -11 +13*x^2 +13*y^2 +13*z^2)/Pi^(1/2).
Z_6,4^(2) = -15/32*6^(1/2)*(x -y)*(x +y)*(x^2 -6*z^2 +y^2)*( -11 +13*x^2 +13*y^2 +13*z^2)/Pi^(1/2) ,
    -15/16*6^(1/2)*x*y*(x^2 -6*z^2 +y^2)*( -11 +13*x^2 +13*y^2 +13*z^2)/Pi^(1/2).
Z_6,4^(3) = -15/16*21^(1/2)*x*z*(x^2 -3*y^2)*( -11 +13*x^2 +13*y^2 +13*z^2)/Pi^(1/2) ,
    -15/16*21^(1/2)*y*z*(3*x^2 -y^2)*( -11 +13*x^2 +13*y^2 +13*z^2)/Pi^(1/2).
Z_6,4^(4) = 15/64*42^(1/2)*( -y^2 -2*x*y +x^2)*( -y^2 +2*x*y +x^2)*( -11 +13*x^2 +13*y^2
    +13*z^2)/Pi^(1/2) , 15/16*42^(1/2)*x*y*(x -y)*(x +y)*( -11 +13*x^2 +13*y^2 +13*z^2)/Pi^(1/2).
Z_6,6^(0) = -1/32*( -16*z^6 +120*z^4*y^2 -90*z^2*y^4 +5*y^6 +120*z^4*x^2 -180*x^2*y^2*z^2 +15*x^2*y^4
    -90*x^4*z^2 +15*x^4*y^2 +5*x^6)*195^(1/2)/Pi^(1/2) , 0.
Z_6,6^(1) = -3/32*910^(1/2)*x*z*(8*z^4 -20*z^2*y^2 +5*y^4 -20*x^2*z^2 +10*x^2*y^2 +5*x^4)/Pi^(1/2) ,
    -3/32*910^(1/2)*y*z*(8*z^4 -20*z^2*y^2 +5*y^4 -20*x^2*z^2 +10*x^2*y^2 +5*x^4)/Pi^(1/2).
Z_6,6^(2) = 15/64*91^(1/2)*(x -y)*(x +y)*(x^4 -16*x^2*z^2 +2*x^2*y^2 +y^4 +16*z^4
    -16*z^2*y^2)/Pi^(1/2) , 15/32*91^(1/2)*x*y*(x^4 -16*x^2*z^2 +2*x^2*y^2 +y^4 +16*z^4
    -16*z^2*y^2)/Pi^(1/2).
Z_6,6^(3) = 15/32*91^(1/2)*x*z*(x^2 -3*y^2)*(3*x^2 -8*z^2 +3*y^2)/Pi^(1/2) , 15/32*91^(1/2)*y*z*(3*x^2
    -y^2)*(3*x^2 -8*z^2 +3*y^2)/Pi^(1/2).
Z_6,6^(4) = -3/64*2730^(1/2)*( -y^2 +2*x*y +x^2)*( -y^2 -2*x*y +x^2)*(x^2 +y^2 -10*z^2)/Pi^(1/2) ,
    -3/16*2730^(1/2)*x*y*(x -y)*(x +y)*(x^2 +y^2 -10*z^2)/Pi^(1/2).
Z_6,6^(5) = -3/32*15015^(1/2)*x*z*(x^4 -10*x^2*y^2 +5*y^4)/Pi^(1/2) ,  -3/32*15015^(1/2)*y*z*(5*x^4
    -10*x^2*y^2 +y^4)/Pi^(1/2).
Z_6,6^(6) = 3/64*5005^(1/2)*(x -y)*(x +y)*(x^2 +4*x*y +y^2)*(y^2 -4*x*y +x^2)/Pi^(1/2) ,
    3/32*5005^(1/2)*x*y*(x^2 -3*y^2)*(3*x^2 -y^2)/Pi^(1/2).
Z_7,1^(0) = 1/32*z*51^(1/2)*( -105 +693*x^2 +693*y^2 +693*z^2 -1287*x^4 -2574*x^2*y^2 -2574*x^2*z^2
    -1287*y^4 -2574*z^2*y^2 -1287*z^4 +715*x^6 +2145*x^4*y^2 +2145*x^4*z^2 +2145*x^2*y^4 +4290*x^2*y^2*z^2
    +2145*z^4*x^2 +715*y^6 +2145*z^2*y^4 +2145*z^4*y^2 +715*z^6)/Pi^(1/2) , 0.
Z_7,1^(1) = -1/64*102^(1/2)*x*( -105 +693*x^2 +693*y^2 +693*z^2 -1287*x^4 -2574*x^2*y^2 -2574*x^2*z^2
    -1287*y^4 -2574*z^2*y^2 -1287*z^4 +715*x^6 +2145*x^4*y^2 +2145*x^4*z^2 +2145*x^2*y^4 +4290*x^2*y^2*z^2
    +2145*z^4*x^2 +715*y^6 +2145*z^2*y^4 +2145*z^4*y^2 +715*z^6)/Pi^(1/2) ,  -1/64*102^(1/2)*y*( -105
    +693*x^2 +693*y^2 +693*z^2 -1287*x^4 -2574*x^2*y^2 -2574*x^2*z^2 -1287*y^4 -2574*z^2*y^2 -1287*z^4
    +715*x^6 +2145*x^4*y^2 +2145*x^4*z^2 +2145*x^2*y^4 +4290*x^2*y^2*z^2 +2145*z^4*x^2 +715*y^6
    +2145*z^2*y^4 +2145*z^4*y^2 +715*z^6)/Pi^(1/2).
Z_7,3^(0) = -1/32*z*( -2*z^2 +3*y^2 +3*x^2)*119^(1/2)*(99 -286*x^2 -286*y^2 -286*z^2 +195*x^4
    +390*x^2*y^2 +390*x^2*z^2 +195*y^4 +390*z^2*y^2 +195*z^4)/Pi^(1/2) , 0.
Z_7,3^(1) = 1/64*357^(1/2)*x*( -4*z^2 +y^2 +x^2)*(99 -286*x^2 -286*y^2 -286*z^2 +195*x^4 +390*x^2*y^2
    +390*x^2*z^2 +195*y^4 +390*z^2*y^2 +195*z^4)/Pi^(1/2) , 1/64*357^(1/2)*y*( -4*z^2 +y^2 +x^2)*(99
    -286*x^2 -286*y^2 -286*z^2 +195*x^4 +390*x^2*y^2 +390*x^2*z^2 +195*y^4 +390*z^2*y^2 +195*z^4)/Pi^(1/2).
Z_7,3^(2) = 1/64*3570^(1/2)*z*(x -y)*(x +y)*(99 -286*x^2 -286*y^2 -286*z^2 +195*x^4 +390*x^2*y^2
    +390*x^2*z^2 +195*y^4 +390*z^2*y^2 +195*z^4)/Pi^(1/2) , 1/32*3570^(1/2)*x*y*z*(99 -286*x^2 -286*y^2
    -286*z^2 +195*x^4 +390*x^2*y^2 +390*x^2*z^2 +195*y^4 +390*z^2*y^2 +195*z^4)/Pi^(1/2).
Z_7,3^(3) = -1/64*595^(1/2)*x*(x^2 -3*y^2)*(99 -286*x^2 -286*y^2 -286*z^2 +195*x^4 +390*x^2*y^2
    +390*x^2*z^2 +195*y^4 +390*z^2*y^2 +195*z^4)/Pi^(1/2) ,  -1/64*595^(1/2)*y*(3*x^2 -y^2)*(99 -286*x^2
    -286*y^2 -286*z^2 +195*x^4 +390*x^2*y^2 +390*x^2*z^2 +195*y^4 +390*z^2*y^2 +195*z^4)/Pi^(1/2).
Z_7,5^(0) = 1/32*z*(8*z^4 -40*z^2*y^2 +15*y^4 -40*x^2*z^2 +30*x^2*y^2 +15*x^4)*187^(1/2)*( -13 +15*x^2
```

```
    +15*y^2 +15*z^2)/Pi^(1/2) , 0.
Z_7,5^(1) = -1/64*5610^(1/2)*x*(8*z^4 -12*z^2*y^2 +y^4 -12*x^2*z^2 +2*x^2*y^2 +x^4)*( -13 +15*x^2
    +15*y^2 +15*z^2)/Pi^(1/2) ,  -1/64*5610^(1/2)*y*(8*z^4 -12*z^2*y^2 +y^4 -12*x^2*z^2 +2*x^2*y^2 +x^4)*(
    -13 +15*x^2 +15*y^2 +15*z^2)/Pi^(1/2).
Z_7,5^(2) = -1/32*39270^(1/2)*z*(x -y)*(x +y)*( -2*z^2 +y^2 +x^2)*( -13 +15*x^2 +15*y^2
    +15*z^2)/Pi^(1/2) ,  -1/16*39270^(1/2)*x*y*z*( -2*z^2 +y^2 +x^2)*( -13 +15*x^2 +15*y^2
    +15*z^2)/Pi^(1/2).
Z_7,5^(3) = 1/64*6545^(1/2)*x*(x^2 -3*y^2)*(x^2 -8*z^2 +y^2)*( -13 +15*x^2 +15*y^2 +15*z^2)/Pi^(1/2) ,
    1/64*6545^(1/2)*y*(3*x^2 -y^2)*(x^2 -8*z^2 +y^2)*( -13 +15*x^2 +15*y^2 +15*z^2)/Pi^(1/2).
Z_7,5^(4) = 3/64*13090^(1/2)*z*( -y^2 -2*x*y +x^2)*( -y^2 +2*x*y +x^2)*( -13 +15*x^2 +15*y^2
    +15*z^2)/Pi^(1/2) , 3/16*13090^(1/2)*x*y*z*(x -y)*(x +y)*( -13 +15*x^2 +15*y^2 +15*z^2)/Pi^(1/2).
Z_7,5^(5) = -3/64*1309^(1/2)*x*(x^4 -10*x^2*y^2 +5*y^4)*( -13 +15*x^2 +15*y^2 +15*z^2)/Pi^(1/2) ,
    -3/64*1309^(1/2)*y*(5*x^4 -10*x^2*y^2 +y^4)*( -13 +15*x^2 +15*y^2 +15*z^2)/Pi^(1/2).
Z_7,7^(0) = -1/32*z*( -16*z^6 +168*z^4*y^2 -210*z^2*y^4 +35*y^6 +168*z^4*x^2 -420*x^2*y^2*z^2
    +105*x^2*y^4 -210*x^4*z^2 +105*x^4*y^2 +35*x^6)*255^(1/2)/Pi^(1/2) , 0.
Z_7,7^(1) = 1/128*3570^(1/2)*x*( -64*z^6 +240*z^4*y^2 -120*z^2*y^4 +5*y^6 +240*z^4*x^2
    -240*x^2*y^2*z^2 +15*x^2*y^4 -120*x^4*z^2 +15*x^4*y^2 +5*x^6)/Pi^(1/2) , 1/128*3570^(1/2)*y*( -64*z^6
    +240*z^4*y^2 -120*z^2*y^4 +5*y^6 +240*z^4*x^2 -240*x^2*y^2*z^2 +15*x^2*y^4 -120*x^4*z^2 +15*x^4*y^2
    +5*x^6)/Pi^(1/2).
Z_7,7^(2) = 3/64*595^(1/2)*z*(x -y)*(x +y)*(15*x^4 -80*x^2*z^2 +30*x^2*y^2 +15*y^4 +48*z^4
    -80*z^2*y^2)/Pi^(1/2) , 3/32*595^(1/2)*x*y*z*(15*x^4 -80*x^2*z^2 +30*x^2*y^2 +15*y^4 +48*z^4
    -80*z^2*y^2)/Pi^(1/2).
Z_7,7^(3) = -3/128*1190^(1/2)*x*(x^2 -3*y^2)*(3*x^4 -60*x^2*z^2 +6*x^2*y^2 +80*z^4 -60*z^2*y^2
    +3*y^4)/Pi^(1/2) ,  -3/128*1190^(1/2)*y*(3*x^2 -y^2)*(3*x^4 -60*x^2*z^2 +6*x^2*y^2 +80*z^4 -60*z^2*y^2
    +3*y^4)/Pi^(1/2).
Z_7,7^(4) = -3/64*13090^(1/2)*z*( -y^2 +2*x*y +x^2)*( -y^2 -2*x*y +x^2)*(3*x^2 +3*y^2
    -10*z^2)/Pi^(1/2) ,  -3/16*13090^(1/2)*x*y*z*(x -y)*(x +y)*(3*x^2 +3*y^2 -10*z^2)/Pi^(1/2).
Z_7,7^(5) = 3/128*13090^(1/2)*x*(x^4 -10*x^2*y^2 +5*y^4)*(x^2 +y^2 -12*z^2)/Pi^(1/2) ,
    3/128*13090^(1/2)*y*(5*x^4 -10*x^2*y^2 +y^4)*(x^2 +y^2 -12*z^2)/Pi^(1/2).
Z_7,7^(6) = 3/64*85085^(1/2)*z*(x -y)*(x +y)*(x^2 +4*x*y +y^2)*(y^2 -4*x*y +x^2)/Pi^(1/2) ,
    3/32*85085^(1/2)*x*y*z*(x^2 -3*y^2)*(3*x^2 -y^2)/Pi^(1/2).
Z_7,7^(7) = -3/128*24310^(1/2)*x*(x^6 -21*x^4*y^2 +35*x^2*y^4 -7*y^6)/Pi^(1/2) ,
    -3/128*24310^(1/2)*y*(7*x^6 -35*x^4*y^2 +21*x^2*y^4 -y^6)/Pi^(1/2).
```

Terms with negative upper index m of Z have not been listed and follow from (57): If m is even, the imaginary part of Z changes sign; if m is odd, the real part changes sign.

D. Cartesian to Zernike

The inverse problem to Section III C is finding the u-coefficients in the ansatz

$$x^p y^q z^t = \sum_{\substack{-p-q \le m \le p+q \\ l \le n \le p+q+t}} u_{p,q,t,n,l,m} R_n^{(l)}(r) Y_l^{(m)}(\theta,\varphi), \tag{65}$$

given p, q and t. In practise we use (60) to construct

$$u_{p,q,t,n,l,m} = \int_{r<1} r^{p+q+t} \sin^{p+q}\theta \cos^t\theta \cos^p\varphi \sin^q\varphi R_n^{(l)}(r) Y_l^{(m)*}(\theta,\varphi) d^3r \tag{66}$$

by projection onto each individual $Z_{n,l}^{(m)}$. After dropping a common exponential factor in the wave function bases, Section 3.3 of my earlier work [12] states,

$$u_{p,q,t,n,l,m} = (-1)^m \sqrt{\frac{2l+1}{4\pi}\frac{(l-m)!}{(l+m)!}} I_r(p+q+t,n,l) I_\theta(p+q,t,l,m) I_\varphi(p,q,m)^*, \tag{67}$$

with two factors defined as

$$I_r(j,n,l) = \int_0^1 r^{j+2} R_n^{(l)}(r) dr = \begin{cases} 0, & j-l \text{ odd or } n-l \text{ odd}; \\ f_{j,n,l}, & j+l \text{ even}. \end{cases} \tag{68}$$

and

$$I_\varphi(p,q,m) = \int_0^{2\pi} e^{im\varphi}\cos^p\varphi\sin^q\varphi d\varphi \tag{69}$$

$$= \begin{cases} 0, & p+q-m\,\text{odd}; \\ \dfrac{\pi}{2^{p+q-1}} i^q \displaystyle\sum_{\sigma=\max(0,(p-q-m)/2)}^{\min(p,(p+q-m)/2)} \binom{p}{\sigma}\binom{q}{\frac{p+q-m}{2}-\sigma}(-1)^{\sigma-(p+q-m)/2}, & p+q-m\,\text{even}. \end{cases} \tag{70}$$

An obvious recurrence is

$$I_\varphi(p,q+2,m) = I_\varphi(p,q,m) - I_\varphi(p+2,q,m). \tag{71}$$

The third factor is only evaluated for even $k-m$—otherwise I_φ equals zero which turns u to zero and I_θ is not of interest—

$$I_\theta(k,t,l,m) = \int_0^{\pi} \sin^{k+1}\theta\cos^t\theta P_l^m(\cos\theta)d\theta \tag{72}$$

$$= \begin{cases} 0, & l-m+t\,\text{odd}; \\ \dfrac{2^{l+1}(-1)^{(m-|m|)/2}}{(l-m)!} \displaystyle\sum_{\nu=0}^{(l-|m|)/2} \dfrac{\left(\frac{1}{2}-\nu\right)_l \binom{l-|m|}{2\nu}}{(1+t+l-|m|-2\nu)\binom{(1+t+l+k)/2-\nu}{(k+|m|)/2}}, & l-m+t\,\text{even}. \end{cases} \tag{73}$$

An actual table of (65) looks as follows:

```
x / Pi^(1/2) = 1/15*30^(1/2)*Z_1,1^(-1) -1/15*30^(1/2)*Z_1,1^(1).
y / Pi^(1/2) = 1/15*i*30^(1/2)*Z_1,1^(-1) +1/15*i*30^(1/2)*Z_1,1^(1).
z / Pi^(1/2) = 2/15*15^(1/2)*Z_1,1^(0).
x^2 / Pi^(1/2) = 2/15*3^(1/2)*Z_0,0^(0) +4/105*7^(1/2)*Z_2,0^(0) +1/105*210^(1/2)*Z_2,2^(-2)
    -2/105*35^(1/2)*Z_2,2^(0) +1/105*210^(1/2)*Z_2,2^(2).
x y / Pi^(1/2) = 1/105*i*210^(1/2)*Z_2,2^(-2) -1/105*i*210^(1/2)*Z_2,2^(2).
x z / Pi^(1/2) = 1/105*210^(1/2)*Z_2,2^(-1) -1/105*210^(1/2)*Z_2,2^(1).
y^2 / Pi^(1/2) = 2/15*3^(1/2)*Z_0,0^(0) +4/105*7^(1/2)*Z_2,0^(0) -1/105*210^(1/2)*Z_2,2^(-2)
    -2/105*35^(1/2)*Z_2,2^(0) -1/105*210^(1/2)*Z_2,2^(2).
y z / Pi^(1/2) = 1/105*i*210^(1/2)*Z_2,2^(-1) +1/105*i*210^(1/2)*Z_2,2^(1).
z^2 / Pi^(1/2) = 2/15*3^(1/2)*Z_0,0^(0) +4/105*7^(1/2)*Z_2,0^(0) +4/105*35^(1/2)*Z_2,2^(0).
x^3 / Pi^(1/2) = 1/35*30^(1/2)*Z_1,1^(-1) -1/35*30^(1/2)*Z_1,1^(1) +2/105*6^(1/2)*Z_3,1^(-1)
    -2/105*6^(1/2)*Z_3,1^(1) +1/105*35^(1/2)*Z_3,3^(-3) -1/105*21^(1/2)*Z_3,3^(-1)
    +1/105*21^(1/2)*Z_3,3^(1) -1/105*35^(1/2)*Z_3,3^(3).
x^2 y / Pi^(1/2) = 1/105*i*30^(1/2)*Z_1,1^(-1) +1/105*i*30^(1/2)*Z_1,1^(1) +2/315*i*6^(1/2)*Z_3,1^(-1)
    +2/315*i*6^(1/2)*Z_3,1^(1) +1/105*i*35^(1/2)*Z_3,3^(-3) -1/315*i*21^(1/2)*Z_3,3^(-1)
    -1/315*i*21^(1/2)*Z_3,3^(1) +1/105*i*35^(1/2)*Z_3,3^(3).
x^2 z / Pi^(1/2) = 2/105*15^(1/2)*Z_1,1^(0) +4/315*3^(1/2)*Z_3,1^(0) +1/315*210^(1/2)*Z_3,3^(-2)
    -2/105*7^(1/2)*Z_3,3^(0) +1/315*210^(1/2)*Z_3,3^(2).
x y^2 / Pi^(1/2) = 1/105*30^(1/2)*Z_1,1^(-1) -1/105*30^(1/2)*Z_1,1^(1) +2/315*6^(1/2)*Z_3,1^(-1)
    -2/315*6^(1/2)*Z_3,1^(1) -1/105*35^(1/2)*Z_3,3^(-3) -1/315*21^(1/2)*Z_3,3^(-1)
    +1/315*21^(1/2)*Z_3,3^(1) +1/105*35^(1/2)*Z_3,3^(3).
x y z / Pi^(1/2) = 1/315*i*210^(1/2)*Z_3,3^(-2) -1/315*i*210^(1/2)*Z_3,3^(2).
x z^2 / Pi^(1/2) = 1/105*30^(1/2)*Z_1,1^(-1) -1/105*30^(1/2)*Z_1,1^(1) +2/315*6^(1/2)*Z_3,1^(-1)
    -2/315*6^(1/2)*Z_3,1^(1) +4/315*21^(1/2)*Z_3,3^(-1) -4/315*21^(1/2)*Z_3,3^(1).
y^3 / Pi^(1/2) = 1/35*i*30^(1/2)*Z_1,1^(-1) +1/35*i*30^(1/2)*Z_1,1^(1) +2/105*i*6^(1/2)*Z_3,1^(-1)
    +2/105*i*6^(1/2)*Z_3,1^(1) -1/105*i*35^(1/2)*Z_3,3^(-3) -1/105*i*21^(1/2)*Z_3,3^(-1)
    -1/105*i*21^(1/2)*Z_3,3^(1) -1/105*i*35^(1/2)*Z_3,3^(3).
y^2 z / Pi^(1/2) = 2/105*15^(1/2)*Z_1,1^(0) +4/315*3^(1/2)*Z_3,1^(0) -1/315*210^(1/2)*Z_3,3^(-2)
    -2/105*7^(1/2)*Z_3,3^(0) -1/315*210^(1/2)*Z_3,3^(2).
y z^2 / Pi^(1/2) = 1/105*i*30^(1/2)*Z_1,1^(-1) +1/105*i*30^(1/2)*Z_1,1^(1) +2/315*i*6^(1/2)*Z_3,1^(-1)
    +2/315*i*6^(1/2)*Z_3,1^(1) +4/315*i*21^(1/2)*Z_3,3^(-1) +4/315*i*21^(1/2)*Z_3,3^(1).
z^3 / Pi^(1/2) = 2/35*15^(1/2)*Z_1,1^(0) +4/105*3^(1/2)*Z_3,1^(0) +4/105*7^(1/2)*Z_3,3^(0).
x^4 / Pi^(1/2) = 2/35*3^(1/2)*Z_0,0^(0) +8/315*7^(1/2)*Z_2,0^(0) +2/315*210^(1/2)*Z_2,2^(-2)
    -4/315*35^(1/2)*Z_2,2^(0) +2/315*210^(1/2)*Z_2,2^(2) +16/3465*11^(1/2)*Z_4,0^(0)
    +4/3465*330^(1/2)*Z_4,2^(-2) -8/3465*55^(1/2)*Z_4,2^(0) +4/3465*330^(1/2)*Z_4,2^(2)
```

```
    +1/1155*770^(1/2)*Z_4,4^(-4) -2/1155*110^(1/2)*Z_4,4^(-2) +2/385*11^(1/2)*Z_4,4^(0)
    -2/1155*110^(1/2)*Z_4,4^(2) +1/1155*770^(1/2)*Z_4,4^(4).
x^3 y / Pi^(1/2) = 1/315*i*210^(1/2)*Z_2,2^(-2) -1/315*i*210^(1/2)*Z_2,2^(2)
    +2/3465*i*330^(1/2)*Z_4,2^(-2) -2/3465*i*330^(1/2)*Z_4,2^(2) +1/1155*i*770^(1/2)*Z_4,4^(-4)
    -1/1155*i*110^(1/2)*Z_4,4^(-2) +1/1155*i*110^(1/2)*Z_4,4^(2) -1/1155*i*770^(1/2)*Z_4,4^(4).
x^3 z / Pi^(1/2) = 1/315*210^(1/2)*Z_2,2^(-1) -1/315*210^(1/2)*Z_2,2^(1) +2/3465*330^(1/2)*Z_4,2^(-1)
    -2/3465*330^(1/2)*Z_4,2^(1) +1/1155*385^(1/2)*Z_4,4^(-3) -1/385*55^(1/2)*Z_4,4^(-1)
    +1/385*55^(1/2)*Z_4,4^(1) -1/1155*385^(1/2)*Z_4,4^(3).
x^2 y^2 / Pi^(1/2) = 2/105*3^(1/2)*Z_0,0^(0) +8/945*7^(1/2)*Z_2,0^(0) -4/945*35^(1/2)*Z_2,2^(0)
    +16/10395*11^(1/2)*Z_4,0^(0) -8/10395*55^(1/2)*Z_4,2^(0) -1/1155*770^(1/2)*Z_4,4^(-4)
    +2/1155*11^(1/2)*Z_4,4^(0) -1/1155*770^(1/2)*Z_4,4^(4).
x^2 y z / Pi^(1/2) = 1/945*i*210^(1/2)*Z_2,2^(-1) +1/945*i*210^(1/2)*Z_2,2^(1)
    +2/10395*i*330^(1/2)*Z_4,2^(-1) +2/10395*i*330^(1/2)*Z_4,2^(1) +1/1155*i*385^(1/2)*Z_4,4^(-3)
    -1/1155*i*55^(1/2)*Z_4,4^(-1) -1/1155*i*55^(1/2)*Z_4,4^(1) +1/1155*i*385^(1/2)*Z_4,4^(3).
x^2 z^2 / Pi^(1/2) = 2/105*3^(1/2)*Z_0,0^(0) +8/945*7^(1/2)*Z_2,0^(0) +1/945*210^(1/2)*Z_2,2^(-2)
    +2/945*35^(1/2)*Z_2,2^(0) +1/945*210^(1/2)*Z_2,2^(2) +16/10395*11^(1/2)*Z_4,0^(0)
    +2/10395*330^(1/2)*Z_4,2^(-2) +4/10395*55^(1/2)*Z_4,2^(0) +2/10395*330^(1/2)*Z_4,2^(2)
    +2/1155*110^(1/2)*Z_4,4^(-2) -8/1155*11^(1/2)*Z_4,4^(0) +2/1155*110^(1/2)*Z_4,4^(2).
x y^3 / Pi^(1/2) = 1/315*i*210^(1/2)*Z_2,2^(-2) -1/315*i*210^(1/2)*Z_2,2^(2)
    +2/3465*i*330^(1/2)*Z_4,2^(-2) -2/3465*i*330^(1/2)*Z_4,2^(2) -1/1155*i*770^(1/2)*Z_4,4^(-4)
    -1/1155*i*110^(1/2)*Z_4,4^(-2) +1/1155*i*110^(1/2)*Z_4,4^(2) +1/1155*i*770^(1/2)*Z_4,4^(4).
x y^2 z / Pi^(1/2) = 1/945*210^(1/2)*Z_2,2^(-1) -1/945*210^(1/2)*Z_2,2^(1)
    +2/10395*330^(1/2)*Z_4,2^(-1) -2/10395*330^(1/2)*Z_4,2^(1) -1/1155*385^(1/2)*Z_4,4^(-3)
    -1/1155*55^(1/2)*Z_4,4^(-1) +1/1155*55^(1/2)*Z_4,4^(1) +1/1155*385^(1/2)*Z_4,4^(3).
x y z^2 / Pi^(1/2) = 1/945*i*210^(1/2)*Z_2,2^(-2) -1/945*i*210^(1/2)*Z_2,2^(2)
    +2/10395*i*330^(1/2)*Z_4,2^(-2) -2/10395*i*330^(1/2)*Z_4,2^(2) +2/1155*i*110^(1/2)*Z_4,4^(-2)
    -2/1155*i*110^(1/2)*Z_4,4^(2).
x z^3 / Pi^(1/2) = 1/315*210^(1/2)*Z_2,2^(-1) -1/315*210^(1/2)*Z_2,2^(1) +2/3465*330^(1/2)*Z_4,2^(-1)
    -2/3465*330^(1/2)*Z_4,2^(1) +4/1155*55^(1/2)*Z_4,4^(-1) -4/1155*55^(1/2)*Z_4,4^(1).
y^4 / Pi^(1/2) = 2/35*3^(1/2)*Z_0,0^(0) +8/315*7^(1/2)*Z_2,0^(0) -2/315*210^(1/2)*Z_2,2^(-2)
    -4/315*35^(1/2)*Z_2,2^(0) -2/315*210^(1/2)*Z_2,2^(2) +16/3465*11^(1/2)*Z_4,0^(0)
    -4/3465*330^(1/2)*Z_4,2^(-2) -8/3465*55^(1/2)*Z_4,2^(0) -4/3465*330^(1/2)*Z_4,2^(2)
    +1/1155*770^(1/2)*Z_4,4^(-4) +2/1155*110^(1/2)*Z_4,4^(-2) +2/385*11^(1/2)*Z_4,4^(0)
    +2/1155*110^(1/2)*Z_4,4^(2) +1/1155*770^(1/2)*Z_4,4^(4).
y^3 z / Pi^(1/2) = 1/315*i*210^(1/2)*Z_2,2^(-1) +1/315*i*210^(1/2)*Z_2,2^(1)
    +2/3465*i*330^(1/2)*Z_4,2^(-1) +2/3465*i*330^(1/2)*Z_4,2^(1) -1/1155*i*385^(1/2)*Z_4,4^(-3)
    -1/385*i*55^(1/2)*Z_4,4^(-1) -1/385*i*55^(1/2)*Z_4,4^(1) -1/1155*i*385^(1/2)*Z_4,4^(3).
y^2 z^2 / Pi^(1/2) = 2/105*3^(1/2)*Z_0,0^(0) +8/945*7^(1/2)*Z_2,0^(0) -1/945*210^(1/2)*Z_2,2^(-2)
    +2/945*35^(1/2)*Z_2,2^(0) -1/945*210^(1/2)*Z_2,2^(2) +16/10395*11^(1/2)*Z_4,0^(0)
    -2/10395*330^(1/2)*Z_4,2^(-2) +4/10395*55^(1/2)*Z_4,2^(0) -2/10395*330^(1/2)*Z_4,2^(2)
    -2/1155*110^(1/2)*Z_4,4^(-2) -8/1155*11^(1/2)*Z_4,4^(0) -2/1155*110^(1/2)*Z_4,4^(2).
y z^3 / Pi^(1/2) = 1/315*i*210^(1/2)*Z_2,2^(-1) +1/315*i*210^(1/2)*Z_2,2^(1)
    +2/3465*i*330^(1/2)*Z_4,2^(-1) +2/3465*i*330^(1/2)*Z_4,2^(1) +4/1155*i*55^(1/2)*Z_4,4^(-1)
    +4/1155*i*55^(1/2)*Z_4,4^(1).
z^4 / Pi^(1/2) = 2/35*3^(1/2)*Z_0,0^(0) +8/315*7^(1/2)*Z_2,0^(0) +8/315*35^(1/2)*Z_2,2^(0)
    +16/3465*11^(1/2)*Z_4,0^(0) +16/3465*55^(1/2)*Z_4,2^(0) +16/1155*11^(1/2)*Z_4,4^(0).
x^5 / Pi^(1/2) = 1/63*30^(1/2)*Z_1,1^(-1) -1/63*30^(1/2)*Z_1,1^(1) +4/231*6^(1/2)*Z_3,1^(-1)
    -4/231*6^(1/2)*Z_3,1^(1) +2/231*35^(1/2)*Z_3,3^(-3) -2/231*21^(1/2)*Z_3,3^(-1)
    +2/231*21^(1/2)*Z_3,3^(1) -2/231*35^(1/2)*Z_3,3^(3) +8/9009*78^(1/2)*Z_5,1^(-1)
    -8/9009*78^(1/2)*Z_5,1^(1) +4/9009*455^(1/2)*Z_5,3^(-3) -4/9009*273^(1/2)*Z_5,3^(-1)
    +4/9009*273^(1/2)*Z_5,3^(1) -4/9009*455^(1/2)*Z_5,3^(3) +1/3003*1001^(1/2)*Z_5,5^(-5)
    -1/9009*5005^(1/2)*Z_5,5^(-3) +1/9009*4290^(1/2)*Z_5,5^(-1) -1/9009*4290^(1/2)*Z_5,5^(1)
    +1/9009*5005^(1/2)*Z_5,5^(3) -1/3003*1001^(1/2)*Z_5,5^(5).
x^4 y / Pi^(1/2) = 1/315*i*30^(1/2)*Z_1,1^(-1) +1/315*i*30^(1/2)*Z_1,1^(1)
    +4/1155*i*6^(1/2)*Z_3,1^(-1) +4/1155*i*6^(1/2)*Z_3,1^(1) +2/385*i*35^(1/2)*Z_3,3^(-3)
    -2/1155*i*21^(1/2)*Z_3,3^(-1) -2/1155*i*21^(1/2)*Z_3,3^(1) +2/385*i*35^(1/2)*Z_3,3^(3)
    +8/45045*i*78^(1/2)*Z_5,1^(-1) +8/45045*i*78^(1/2)*Z_5,1^(1) +4/15015*i*455^(1/2)*Z_5,3^(-3)
    -4/45045*i*273^(1/2)*Z_5,3^(-1) -4/45045*i*273^(1/2)*Z_5,3^(1) +4/15015*i*455^(1/2)*Z_5,3^(3)
    +1/3003*i*1001^(1/2)*Z_5,5^(-5) -1/15015*i*5005^(1/2)*Z_5,5^(-3) +1/45045*i*4290^(1/2)*Z_5,5^(-1)
    +1/45045*i*4290^(1/2)*Z_5,5^(1) -1/15015*i*5005^(1/2)*Z_5,5^(3) +1/3003*i*1001^(1/2)*Z_5,5^(5).
x^4 z / Pi^(1/2) = 2/315*15^(1/2)*Z_1,1^(0) +8/1155*3^(1/2)*Z_3,1^(0) +2/1155*210^(1/2)*Z_3,3^(-2)
    -4/385*7^(1/2)*Z_3,3^(0) +2/1155*210^(1/2)*Z_3,3^(2) +16/45045*39^(1/2)*Z_5,1^(0)
    +4/45045*2730^(1/2)*Z_5,3^(-2) -8/15015*91^(1/2)*Z_5,3^(0) +4/45045*2730^(1/2)*Z_5,3^(2)
    +1/15015*10010^(1/2)*Z_5,5^(-4) -2/45045*30030^(1/2)*Z_5,5^(-2) +2/3003*143^(1/2)*Z_5,5^(0)
```

```
    -2/45045*30030^(1/2)*Z_5,5^(2) +1/15015*10010^(1/2)*Z_5,5^(4).
x^3 y^2 / Pi^(1/2) = 1/315*30^(1/2)*Z_1,1^(-1) -1/315*30^(1/2)*Z_1,1^(1) +4/1155*6^(1/2)*Z_3,1^(-1)
    -4/1155*6^(1/2)*Z_3,1^(1) -2/1155*35^(1/2)*Z_3,3^(-3) -2/1155*21^(1/2)*Z_3,3^(-1)
    +2/1155*21^(1/2)*Z_3,3^(1) +2/1155*35^(1/2)*Z_3,3^(3) +8/45045*78^(1/2)*Z_5,1^(-1)
    -8/45045*78^(1/2)*Z_5,1^(1) -4/45045*455^(1/2)*Z_5,3^(-3) -4/45045*273^(1/2)*Z_5,3^(-1)
    +4/45045*273^(1/2)*Z_5,3^(1) +4/45045*455^(1/2)*Z_5,3^(3) -1/3003*1001^(1/2)*Z_5,5^(-5)
    +1/45045*5005^(1/2)*Z_5,5^(-3) +1/45045*4290^(1/2)*Z_5,5^(-1) -1/45045*4290^(1/2)*Z_5,5^(1)
    -1/45045*5005^(1/2)*Z_5,5^(3) +1/3003*1001^(1/2)*Z_5,5^(5).
x^3 y z / Pi^(1/2) = 1/1155*i*210^(1/2)*Z_3,3^(-2) -1/1155*i*210^(1/2)*Z_3,3^(2)
    +2/45045*i*2730^(1/2)*Z_5,3^(-2) -2/45045*i*2730^(1/2)*Z_5,3^(2) +1/15015*i*10010^(1/2)*Z_5,5^(-4)
    -1/45045*i*30030^(1/2)*Z_5,5^(-2) +1/45045*i*30030^(1/2)*Z_5,5^(2) -1/15015*i*10010^(1/2)*Z_5,5^(4).
x^3 z^2 / Pi^(1/2) = 1/315*30^(1/2)*Z_1,1^(-1) -1/315*30^(1/2)*Z_1,1^(1) +4/1155*6^(1/2)*Z_3,1^(-1)
    -4/1155*6^(1/2)*Z_3,1^(1) +1/1155*35^(1/2)*Z_3,3^(-3) +1/385*21^(1/2)*Z_3,3^(-1)
    -1/385*21^(1/2)*Z_3,3^(1) -1/1155*35^(1/2)*Z_3,3^(3) +8/45045*78^(1/2)*Z_5,1^(-1)
    -8/45045*78^(1/2)*Z_5,1^(1) +2/45045*455^(1/2)*Z_5,3^(-3) +2/15015*273^(1/2)*Z_5,3^(-1)
    -2/15015*273^(1/2)*Z_5,3^(1) -2/45045*455^(1/2)*Z_5,3^(3) +4/45045*5005^(1/2)*Z_5,5^(-3)
    -2/15015*4290^(1/2)*Z_5,5^(-1) +2/15015*4290^(1/2)*Z_5,5^(1) -4/45045*5005^(1/2)*Z_5,5^(3).
x^2 y^3 / Pi^(1/2) = 1/315*i*30^(1/2)*Z_1,1^(-1) +1/315*i*30^(1/2)*Z_1,1^(1)
    +4/1155*i*6^(1/2)*Z_3,1^(-1) +4/1155*i*6^(1/2)*Z_3,1^(1) +2/1155*i*35^(1/2)*Z_3,3^(-3)
    -2/1155*i*21^(1/2)*Z_3,3^(-1) -2/1155*i*21^(1/2)*Z_3,3^(1) +2/1155*i*35^(1/2)*Z_3,3^(3)
    +8/45045*i*78^(1/2)*Z_5,1^(-1) +8/45045*i*78^(1/2)*Z_5,1^(1) +4/45045*i*455^(1/2)*Z_5,3^(-3)
    -4/45045*i*273^(1/2)*Z_5,3^(-1) -4/45045*i*273^(1/2)*Z_5,3^(1) +4/45045*i*455^(1/2)*Z_5,3^(3)
    -1/3003*i*1001^(1/2)*Z_5,5^(-5) -1/45045*i*5005^(1/2)*Z_5,5^(-3) +1/45045*i*4290^(1/2)*Z_5,5^(-1)
    +1/45045*i*4290^(1/2)*Z_5,5^(1) -1/45045*i*5005^(1/2)*Z_5,5^(3) -1/3003*i*1001^(1/2)*Z_5,5^(5).
x^2 y^2 z / Pi^(1/2) = 2/945*15^(1/2)*Z_1,1^(0) +8/3465*3^(1/2)*Z_3,1^(0) -4/1155*7^(1/2)*Z_3,3^(0)
    +16/135135*39^(1/2)*Z_5,1^(0) -8/45045*91^(1/2)*Z_5,3^(0) -1/15015*10010^(1/2)*Z_5,5^(-4)
    +2/9009*143^(1/2)*Z_5,5^(0) -1/15015*10010^(1/2)*Z_5,5^(4).
x^2 y z^2 / Pi^(1/2) = 1/945*i*30^(1/2)*Z_1,1^(-1) +1/945*i*30^(1/2)*Z_1,1^(1)
    +4/3465*i*6^(1/2)*Z_3,1^(-1) +4/3465*i*6^(1/2)*Z_3,1^(1) +1/1155*i*35^(1/2)*Z_3,3^(-3)
    +1/1155*i*21^(1/2)*Z_3,3^(-1) +1/1155*i*21^(1/2)*Z_3,3^(1) +1/1155*i*35^(1/2)*Z_3,3^(3)
    +8/135135*i*78^(1/2)*Z_5,1^(-1) +8/135135*i*78^(1/2)*Z_5,1^(1) +2/45045*i*455^(1/2)*Z_5,3^(-3)
    +2/45045*i*273^(1/2)*Z_5,3^(-1) +2/45045*i*273^(1/2)*Z_5,3^(1) +2/45045*i*455^(1/2)*Z_5,3^(3)
    +4/45045*i*5005^(1/2)*Z_5,5^(-3) -2/45045*i*4290^(1/2)*Z_5,5^(-1) -2/45045*i*4290^(1/2)*Z_5,5^(1)
    +4/45045*i*5005^(1/2)*Z_5,5^(3).
x^2 z^3 / Pi^(1/2) = 2/315*15^(1/2)*Z_1,1^(0) +8/1155*3^(1/2)*Z_3,1^(0) +1/1155*210^(1/2)*Z_3,3^(-2)
    -2/1155*7^(1/2)*Z_3,3^(0) +1/1155*210^(1/2)*Z_3,3^(2) +16/45045*39^(1/2)*Z_5,1^(0)
    +2/45045*2730^(1/2)*Z_5,3^(-2) -4/45045*91^(1/2)*Z_5,3^(0) +2/45045*2730^(1/2)*Z_5,3^(2)
    +2/45045*30030^(1/2)*Z_5,5^(-2) -8/9009*143^(1/2)*Z_5,5^(0) +2/45045*30030^(1/2)*Z_5,5^(2).
x y^4 / Pi^(1/2) = 1/315*30^(1/2)*Z_1,1^(-1) -1/315*30^(1/2)*Z_1,1^(1) +4/1155*6^(1/2)*Z_3,1^(-1)
    -4/1155*6^(1/2)*Z_3,1^(1) -2/385*35^(1/2)*Z_3,3^(-3) -2/1155*21^(1/2)*Z_3,3^(-1)
    +2/1155*21^(1/2)*Z_3,3^(1) +2/385*35^(1/2)*Z_3,3^(3) +8/45045*78^(1/2)*Z_5,1^(-1)
    -8/45045*78^(1/2)*Z_5,1^(1) -4/15015*455^(1/2)*Z_5,3^(-3) -4/45045*273^(1/2)*Z_5,3^(-1)
    +4/45045*273^(1/2)*Z_5,3^(1) +4/15015*455^(1/2)*Z_5,3^(3) +1/3003*1001^(1/2)*Z_5,5^(-5)
    +1/15015*5005^(1/2)*Z_5,5^(-3) +1/45045*4290^(1/2)*Z_5,5^(-1) -1/45045*4290^(1/2)*Z_5,5^(1)
    -1/15015*5005^(1/2)*Z_5,5^(3) -1/3003*1001^(1/2)*Z_5,5^(5).
x y^3 z / Pi^(1/2) = 1/1155*i*210^(1/2)*Z_3,3^(-2) -1/1155*i*210^(1/2)*Z_3,3^(2)
    +2/45045*i*2730^(1/2)*Z_5,3^(-2) -2/45045*i*2730^(1/2)*Z_5,3^(2) -1/15015*i*10010^(1/2)*Z_5,5^(-4)
    -1/45045*i*30030^(1/2)*Z_5,5^(-2) +1/45045*i*30030^(1/2)*Z_5,5^(2) +1/15015*i*10010^(1/2)*Z_5,5^(4).
x y^2 z^2 / Pi^(1/2) = 1/945*30^(1/2)*Z_1,1^(-1) -1/945*30^(1/2)*Z_1,1^(1) +4/3465*6^(1/2)*Z_3,1^(-1)
    -4/3465*6^(1/2)*Z_3,1^(1) -1/1155*35^(1/2)*Z_3,3^(-3) +1/1155*21^(1/2)*Z_3,3^(-1)
    -1/1155*21^(1/2)*Z_3,3^(1) +1/1155*35^(1/2)*Z_3,3^(3) +8/135135*78^(1/2)*Z_5,1^(-1)
    -8/135135*78^(1/2)*Z_5,1^(1) -2/45045*455^(1/2)*Z_5,3^(-3) +2/45045*273^(1/2)*Z_5,3^(-1)
    -2/45045*273^(1/2)*Z_5,3^(1) +2/45045*455^(1/2)*Z_5,3^(3) -4/45045*5005^(1/2)*Z_5,5^(-3)
    -2/45045*4290^(1/2)*Z_5,5^(-1) +2/45045*4290^(1/2)*Z_5,5^(1) +4/45045*5005^(1/2)*Z_5,5^(3).
x y z^3 / Pi^(1/2) = 1/1155*i*210^(1/2)*Z_3,3^(-2) -1/1155*i*210^(1/2)*Z_3,3^(2)
    +2/45045*i*2730^(1/2)*Z_5,3^(-2) -2/45045*i*2730^(1/2)*Z_5,3^(2) +2/45045*i*30030^(1/2)*Z_5,5^(-2)
    -2/45045*i*30030^(1/2)*Z_5,5^(2).
x z^4 / Pi^(1/2) = 1/315*30^(1/2)*Z_1,1^(-1) -1/315*30^(1/2)*Z_1,1^(1) +4/1155*6^(1/2)*Z_3,1^(-1)
    -4/1155*6^(1/2)*Z_3,1^(1) +8/1155*21^(1/2)*Z_3,3^(-1) -8/1155*21^(1/2)*Z_3,3^(1)
    +8/45045*78^(1/2)*Z_5,1^(-1) -8/45045*78^(1/2)*Z_5,1^(1) +16/45045*273^(1/2)*Z_5,3^(-1)
    -16/45045*273^(1/2)*Z_5,3^(1) +8/45045*4290^(1/2)*Z_5,5^(-1) -8/45045*4290^(1/2)*Z_5,5^(1).
y^5 / Pi^(1/2) = 1/63*i*30^(1/2)*Z_1,1^(-1) +1/63*i*30^(1/2)*Z_1,1^(1) +4/231*i*6^(1/2)*Z_3,1^(-1)
    +4/231*i*6^(1/2)*Z_3,1^(1) -2/231*i*35^(1/2)*Z_3,3^(-3) -2/231*i*21^(1/2)*Z_3,3^(-1)
    -2/231*i*21^(1/2)*Z_3,3^(1) -2/231*i*35^(1/2)*Z_3,3^(3) +8/9009*i*78^(1/2)*Z_5,1^(-1)
```

```
    +8/9009*i*78^(1/2)*Z_5,1^(1) -4/9009*i*455^(1/2)*Z_5,3^(-3) -4/9009*i*273^(1/2)*Z_5,3^(-1)
    -4/9009*i*273^(1/2)*Z_5,3^(1) -4/9009*i*455^(1/2)*Z_5,3^(3) +1/3003*i*1001^(1/2)*Z_5,5^(-5)
    +1/9009*i*5005^(1/2)*Z_5,5^(-3) +1/9009*i*4290^(1/2)*Z_5,5^(-1) +1/9009*i*4290^(1/2)*Z_5,5^(1)
    +1/9009*i*5005^(1/2)*Z_5,5^(3) +1/3003*i*1001^(1/2)*Z_5,5^(5).
y^4 z / Pi^(1/2) = 2/315*15^(1/2)*Z_1,1^(0) +8/1155*3^(1/2)*Z_3,1^(0) -2/1155*210^(1/2)*Z_3,3^(-2)
    -4/385*7^(1/2)*Z_3,3^(0) -2/1155*210^(1/2)*Z_3,3^(2) +16/45045*39^(1/2)*Z_5,1^(0)
    -4/45045*2730^(1/2)*Z_5,3^(-2) -8/15015*91^(1/2)*Z_5,3^(0) -4/45045*2730^(1/2)*Z_5,3^(2)
    +1/15015*10010^(1/2)*Z_5,5^(-4) +2/45045*30030^(1/2)*Z_5,5^(-2) +2/3003*143^(1/2)*Z_5,5^(0)
    +2/45045*30030^(1/2)*Z_5,5^(2) +1/15015*10010^(1/2)*Z_5,5^(4).
y^3 z^2 / Pi^(1/2) = 1/315*i*30^(1/2)*Z_1,1^(-1) +1/315*i*30^(1/2)*Z_1,1^(1)
    +4/1155*i*6^(1/2)*Z_3,1^(-1) +4/1155*i*6^(1/2)*Z_3,1^(1) -1/1155*i*35^(1/2)*Z_3,3^(-3)
    +1/385*i*21^(1/2)*Z_3,3^(-1) +1/385*i*21^(1/2)*Z_3,3^(1) -1/1155*i*35^(1/2)*Z_3,3^(3)
    +8/45045*i*78^(1/2)*Z_5,1^(-1) +8/45045*i*78^(1/2)*Z_5,1^(1) -2/45045*i*455^(1/2)*Z_5,3^(-3)
    +2/15015*i*273^(1/2)*Z_5,3^(-1) +2/15015*i*273^(1/2)*Z_5,3^(1) -2/45045*i*455^(1/2)*Z_5,3^(3)
    -4/45045*i*5005^(1/2)*Z_5,5^(-3) -2/15015*i*4290^(1/2)*Z_5,5^(-1) -2/15015*i*4290^(1/2)*Z_5,5^(1)
    -4/45045*i*5005^(1/2)*Z_5,5^(3).
y^2 z^3 / Pi^(1/2) = 2/315*15^(1/2)*Z_1,1^(0) +8/1155*3^(1/2)*Z_3,1^(0) -1/1155*210^(1/2)*Z_3,3^(-2)
    -2/1155*7^(1/2)*Z_3,3^(0) -1/1155*210^(1/2)*Z_3,3^(2) +16/45045*39^(1/2)*Z_5,1^(0)
    -2/45045*2730^(1/2)*Z_5,3^(-2) -4/45045*91^(1/2)*Z_5,3^(0) -2/45045*2730^(1/2)*Z_5,3^(2)
    -2/45045*30030^(1/2)*Z_5,5^(-2) -8/9009*143^(1/2)*Z_5,5^(0) -2/45045*30030^(1/2)*Z_5,5^(2).
y z^4 / Pi^(1/2) = 1/315*i*30^(1/2)*Z_1,1^(-1) +1/315*i*30^(1/2)*Z_1,1^(1)
    +4/1155*i*6^(1/2)*Z_3,1^(-1) +4/1155*i*6^(1/2)*Z_3,1^(1) +8/1155*i*21^(1/2)*Z_3,3^(-1)
    +8/1155*i*21^(1/2)*Z_3,3^(1) +8/45045*i*78^(1/2)*Z_5,1^(-1) +8/45045*i*78^(1/2)*Z_5,1^(1)
    +16/45045*i*273^(1/2)*Z_5,3^(-1) +16/45045*i*273^(1/2)*Z_5,3^(1) +8/45045*i*4290^(1/2)*Z_5,5^(-1)
    +8/45045*i*4290^(1/2)*Z_5,5^(1).
z^5 / Pi^(1/2) = 2/63*15^(1/2)*Z_1,1^(0) +8/231*3^(1/2)*Z_3,1^(0) +8/231*7^(1/2)*Z_3,3^(0)
    +16/9009*39^(1/2)*Z_5,1^(0) +16/9009*91^(1/2)*Z_5,3^(0) +16/9009*143^(1/2)*Z_5,5^(0).
```

Above, `i` is the imaginary unit which appears on the right hand sides if q is odd.

E. Product Expansion (Linearization Coefficients)

The product of the angular variables are the established expansions with Wigner $3j$ coefficients [6, (4.6.5)]

$$Y_{l_1}^{(m_1)} Y_{l_2}^{(m_2)} = \sum_{l=|l_1-l_2|}^{l_1+l_2} \sum_{m=-l}^{l} \sqrt{\frac{(2l_1+1)(2l_2+1)(2l+1)}{4\pi}} \begin{pmatrix} l_1 & l_2 & l \\ m_1 & m_2 & m \end{pmatrix} \begin{pmatrix} l_1 & l_2 & l \\ 0 & 0 & 0 \end{pmatrix} Y_l^{(m)*}, \tag{74}$$

where the sum over m is nonzero only at $m_1 + m_2 + m = 0$. The relation to Clebsch-Gordan coefficients

$$\begin{pmatrix} j_1 & j_2 & j_3 \\ m_1 & m_2 & m_3 \end{pmatrix} = (-1)^{j_1 - j_2 - m_3} \frac{1}{\sqrt{2j_3+1}} (j_1 m_1 j_2 m_2 \mid j_1 j_2 j_3 - m_3) \tag{75}$$

opens a route to computation via [6, (3.6.11)][7, (7.5)][1, 27.9.1]

$$\begin{aligned} (j_1 m_1 j_2 m_2 \mid j_1 j_2 j m) \;=\; & \delta(m_1+m_2, m) \sqrt{\frac{(2j+1)(j_1+j_2-j)!(j_1-j_2+j)!(-j_1+j_2+j)!}{(j_1+j_2+j+1)!}} \\ & \times \sqrt{(j_1+m_1)!(j_1-m_1)!(j_2+m_2)!(j_2-m_2)!(j+m)!(j-m)!} \\ & \times \sum_z \frac{(-1)^z}{z!(j_1+j_2-j-z)!(j_1-m_1-z)!(j_2+m_2-z)!(j-j_2+m_1+z)!(j-j_1-m_2+z)!}, \end{aligned} \tag{76}$$

where the sum is over all z that keep the arguments of the factorials in the denominator non-negative. The familiar table of (74) starts in conjunction with (57) as:

```
Pi^(1/2) Y_0^(0) Y_0^(0) = 2^(1/2)*Y_0^(0).
Pi^(1/2) Y_1^(-1) Y_0^(0) = 1/3*2^(1/2)*Y_1^(-1).
Pi^(1/2) Y_1^(-1) Y_1^(-1) = 1/30*6^(1/2)*Y_2^(-2).
Pi^(1/2) Y_1^(0) Y_0^(0) = 2/3*2^(1/2)*Y_1^(0).
Pi^(1/2) Y_1^(0) Y_1^(-1) = 1/15*6^(1/2)*Y_2^(-1).
Pi^(1/2) Y_1^(0) Y_1^(0) = 2/3*2^(1/2)*Y_0^(0) +4/15*6^(1/2)*Y_2^(0).
```

```
Pi^(1/2) Y_1^(1) Y_0^(0) = 1/3*2^(1/2)*Y_1^(1).
Pi^(1/2) Y_1^(1) Y_1^(-1) = -1/3*2^(1/2)*Y_0^(0) +1/30*6^(1/2)*Y_2^(0).
Pi^(1/2) Y_1^(1) Y_1^(0) = 1/15*6^(1/2)*Y_2^(1).
Pi^(1/2) Y_1^(1) Y_1^(1) = 1/30*6^(1/2)*Y_2^(2).
Pi^(1/2) Y_2^(-2) Y_0^(0) = 1/40*2^(1/2)*Y_2^(-2).
Pi^(1/2) Y_2^(-2) Y_1^(-1) = 1/420*3^(1/2)*Y_3^(-3).
Pi^(1/2) Y_2^(-2) Y_1^(0) = 1/210*3^(1/2)*Y_3^(-2).
Pi^(1/2) Y_2^(-2) Y_1^(1) = -1/30*6^(1/2)*Y_1^(-1) +1/420*3^(1/2)*Y_3^(-1).
Pi^(1/2) Y_2^(-2) Y_2^(-2) = 1/20160*10^(1/2)*Y_4^(-4).
Pi^(1/2) Y_2^(-1) Y_0^(0) = 1/10*2^(1/2)*Y_2^(-1).
Pi^(1/2) Y_2^(-1) Y_1^(-1) = 1/105*3^(1/2)*Y_3^(-2).
Pi^(1/2) Y_2^(-1) Y_1^(0) = 1/15*6^(1/2)*Y_1^(-1) +2/105*3^(1/2)*Y_3^(-1).
Pi^(1/2) Y_2^(-1) Y_1^(1) = -1/15*6^(1/2)*Y_1^(0) +1/105*3^(1/2)*Y_3^(0).
Pi^(1/2) Y_2^(-1) Y_2^(-2) = 1/5040*10^(1/2)*Y_4^(-3).
Pi^(1/2) Y_2^(-1) Y_2^(-1) = 1/140*6^(1/2)*Y_2^(-2) +1/1260*10^(1/2)*Y_4^(-2).
Pi^(1/2) Y_2^(0) Y_0^(0) = 3/5*2^(1/2)*Y_2^(0).
Pi^(1/2) Y_2^(0) Y_1^(-1) = -1/30*6^(1/2)*Y_1^(-1) +1/70*3^(1/2)*Y_3^(-1).
Pi^(1/2) Y_2^(0) Y_1^(0) = 4/15*6^(1/2)*Y_1^(0) +12/35*3^(1/2)*Y_3^(0).
Pi^(1/2) Y_2^(0) Y_1^(1) = -1/30*6^(1/2)*Y_1^(1) +1/70*3^(1/2)*Y_3^(1).
Pi^(1/2) Y_2^(0) Y_2^(-2) = -1/280*6^(1/2)*Y_2^(-2) +1/3360*10^(1/2)*Y_4^(-2).
Pi^(1/2) Y_2^(0) Y_2^(-1) = 1/140*6^(1/2)*Y_2^(-1) +1/840*10^(1/2)*Y_4^(-1).
Pi^(1/2) Y_2^(0) Y_2^(0) = 3/5*2^(1/2)*Y_0^(0) +6/35*6^(1/2)*Y_2^(0) +6/35*10^(1/2)*Y_4^(0).
Pi^(1/2) Y_2^(1) Y_0^(0) = 1/10*2^(1/2)*Y_2^(1).
Pi^(1/2) Y_2^(1) Y_1^(-1) = -1/15*6^(1/2)*Y_1^(0) +1/105*3^(1/2)*Y_3^(0).
Pi^(1/2) Y_2^(1) Y_1^(0) = 1/15*6^(1/2)*Y_1^(1) +2/105*3^(1/2)*Y_3^(1).
Pi^(1/2) Y_2^(1) Y_1^(1) = 1/105*3^(1/2)*Y_3^(2).
Pi^(1/2) Y_2^(1) Y_2^(-2) = -1/140*6^(1/2)*Y_2^(-1) +1/5040*10^(1/2)*Y_4^(-1).
Pi^(1/2) Y_2^(1) Y_2^(-1) = -1/10*2^(1/2)*Y_0^(0) -1/140*6^(1/2)*Y_2^(0) +1/1260*10^(1/2)*Y_4^(0).
Pi^(1/2) Y_2^(1) Y_2^(0) = 1/140*6^(1/2)*Y_2^(1) +1/840*10^(1/2)*Y_4^(1).
Pi^(1/2) Y_2^(1) Y_2^(1) = 1/140*6^(1/2)*Y_2^(2) +1/1260*10^(1/2)*Y_4^(2).
Pi^(1/2) Y_2^(2) Y_0^(0) = 1/40*2^(1/2)*Y_2^(2).
Pi^(1/2) Y_2^(2) Y_1^(-1) = -1/30*6^(1/2)*Y_1^(1) +1/420*3^(1/2)*Y_3^(1).
Pi^(1/2) Y_2^(2) Y_1^(0) = 1/210*3^(1/2)*Y_3^(2).
Pi^(1/2) Y_2^(2) Y_1^(1) = 1/420*3^(1/2)*Y_3^(3).
Pi^(1/2) Y_2^(2) Y_2^(-2) = 1/40*2^(1/2)*Y_0^(0) -1/280*6^(1/2)*Y_2^(0) +1/20160*10^(1/2)*Y_4^(0).
Pi^(1/2) Y_2^(2) Y_2^(-1) = -1/140*6^(1/2)*Y_2^(1) +1/5040*10^(1/2)*Y_4^(1).
Pi^(1/2) Y_2^(2) Y_2^(0) = -1/280*6^(1/2)*Y_2^(2) +1/3360*10^(1/2)*Y_4^(2).
Pi^(1/2) Y_2^(2) Y_2^(1) = 1/5040*10^(1/2)*Y_4^(3).
Pi^(1/2) Y_2^(2) Y_2^(2) = 1/20160*10^(1/2)*Y_4^(4).
```

The products of the radial polynomials are essentially products of Jacobi polynomials and are expanded according to Srivastava's equation [21, (21)]. Since we are concerned about products of two Zernike functions, $R_{n_1}^{(l_1)}Y_{l_1}^{(m_1)}R_{n_2}^{(l_2)}Y_{l_2}^{(m_2)}$, with coupling of the angular variables to products in the range $|l_1-l_2| \leq l \leq l_1+l_2$ via (74), the request is to expand $R_{n_1}^{(l_1)}R_{n_2}^{(l_2)}$ as $R_n^{(l)}$ with l fixed within that interval. The 3D equivalent to (30) and (32) is

$$R_{n_1}^{(l_1)}(r)R_{n_2}^{(l_2)}(r) \equiv \sum_{n_3=l_3}^{n_1+n_2} k_{n_1,l_1,n_2,l_2,n_3,l_3}R_{n_3}^{(l_3)}(r); \tag{77}$$

$$k_{n_1,l_1,n_2,l_2,n_3,l_3} = \int_0^1 r^2 R_{n_1}^{(l_1)}(r)R_{n_2}^{(l_2)}(r)R_{n_3}^{(l_3)}(r)dr, \tag{78}$$

with a k-sum rule immediate from taking $r=1$ with (40). In practise, given the product of the radial polynomials as a polynomial in r, double insertion of (44) leads to products of the following format:

```
R_1^(1)(r)*R_1^(1)(r) = 3^(1/2)*R_0^(0)(r) +2/7*7^(1/2)*R_2^(0)(r)
   = 5/7*7^(1/2)*R_2^(2)(r).
R_1^(1)(r)*R_2^(0)(r) = 2/7*7^(1/2)*R_1^(1)(r) +5/21*35^(1/2)*R_3^(1)(r).
R_1^(1)(r)*R_2^(2)(r) = 5/7*7^(1/2)*R_1^(1)(r) +2/21*35^(1/2)*R_3^(1)(r)
   = 1/3*35^(1/2)*R_3^(3)(r).
R_1^(1)(r)*R_3^(1)(r) = 5/21*35^(1/2)*R_2^(0)(r) +4/33*55^(1/2)*R_4^(0)(r)
   = 2/21*35^(1/2)*R_2^(2)(r) +7/33*55^(1/2)*R_4^(2)(r).
R_1^(1)(r)*R_3^(3)(r) = 1/3*35^(1/2)*R_2^(2)(r) +2/33*55^(1/2)*R_4^(2)(r)
   = 3/11*55^(1/2)*R_4^(4)(r).
```

```
R_2^(0)(r)*R_2^(0)(r) = 3^(1/2)*R_0^(0)(r) -2/9*7^(1/2)*R_2^(0)(r) +50/99*11^(1/2)*R_4^(0)(r).
R_2^(0)(r)*R_2^(2)(r) = 4/9*7^(1/2)*R_2^(2)(r) +35/99*11^(1/2)*R_4^(2)(r).
R_2^(2)(r)*R_2^(2)(r) = 3^(1/2)*R_0^(0)(r) +4/9*7^(1/2)*R_2^(0)(r) +8/99*11^(1/2)*R_4^(0)(r)
   = 7/9*7^(1/2)*R_2^(2)(r) +14/99*11^(1/2)*R_4^(2)(r)
   = 7/11*11^(1/2)*R_4^(4)(r).
R_1^(1)(r)*R_4^(0)(r) = 4/33*55^(1/2)*R_3^(1)(r) +7/143*715^(1/2)*R_5^(1)(r).
R_1^(1)(r)*R_4^(2)(r) = 7/33*55^(1/2)*R_3^(1)(r) +4/143*715^(1/2)*R_5^(1)(r)
   = 2/33*55^(1/2)*R_3^(3)(r) +9/143*715^(1/2)*R_5^(3)(r).
R_1^(1)(r)*R_4^(4)(r) = 3/11*55^(1/2)*R_3^(3)(r) +2/143*715^(1/2)*R_5^(3)(r)
   = 1/13*715^(1/2)*R_5^(5)(r).
R_2^(0)(r)*R_3^(1)(r) = 5/21*35^(1/2)*R_1^(1)(r) -8/77*7^(1/2)*R_3^(1)(r) +70/429*91^(1/2)*R_5^(1)(r).
R_2^(0)(r)*R_3^(3)(r) = 6/11*7^(1/2)*R_3^(3)(r) +15/143*91^(1/2)*R_5^(3)(r).
R_2^(2)(r)*R_3^(1)(r) = 2/21*35^(1/2)*R_1^(1)(r) +43/77*7^(1/2)*R_3^(1)(r) +28/429*91^(1/2)*R_5^(1)(r)
   = 4/11*7^(1/2)*R_3^(3)(r) +21/143*91^(1/2)*R_5^(3)(r).
R_2^(2)(r)*R_3^(3)(r) = 1/3*35^(1/2)*R_1^(1)(r) +4/11*7^(1/2)*R_3^(1)(r) +8/429*91^(1/2)*R_5^(1)(r)
   = 9/11*7^(1/2)*R_3^(3)(r) +6/143*91^(1/2)*R_5^(3)(r)
   = 3/13*91^(1/2)*R_5^(5)(r).
R_1^(1)(r)*R_5^(1)(r) = 7/143*715^(1/2)*R_4^(0)(r) +2/65*975^(1/2)*R_6^(0)(r)
   = 4/143*715^(1/2)*R_4^(2)(r) +3/65*975^(1/2)*R_6^(2)(r).
R_1^(1)(r)*R_5^(3)(r) = 9/143*715^(1/2)*R_4^(2)(r) +4/195*975^(1/2)*R_6^(2)(r)
   = 2/143*715^(1/2)*R_4^(4)(r) +11/195*975^(1/2)*R_6^(4)(r).
R_1^(1)(r)*R_5^(5)(r) = 1/13*715^(1/2)*R_4^(4)(r) +2/195*975^(1/2)*R_6^(4)(r)
   = 1/15*975^(1/2)*R_6^(6)(r).
R_2^(0)(r)*R_4^(0)(r) = 50/99*11^(1/2)*R_2^(0)(r) -28/117*7^(1/2)*R_4^(0)(r)
    +7/143*1155^(1/2)*R_6^(0)(r).
R_2^(0)(r)*R_4^(2)(r) = 35/99*11^(1/2)*R_2^(2)(r) +2/117*7^(1/2)*R_4^(2)(r)
    +6/143*1155^(1/2)*R_6^(2)(r).
R_2^(0)(r)*R_4^(4)(r) = 8/13*7^(1/2)*R_4^(4)(r) +1/39*1155^(1/2)*R_6^(4)(r).
R_2^(2)(r)*R_4^(0)(r) = 8/99*11^(1/2)*R_2^(2)(r) +56/117*7^(1/2)*R_4^(2)(r)
    +21/715*1155^(1/2)*R_6^(2)(r).
R_2^(2)(r)*R_4^(2)(r) = 35/99*11^(1/2)*R_2^(0)(r) +56/117*7^(1/2)*R_4^(0)(r)
    +8/715*1155^(1/2)*R_6^(0)(r)
   = 14/99*11^(1/2)*R_2^(2)(r) +71/117*7^(1/2)*R_4^(2)(r) +12/715*1155^(1/2)*R_6^(2)(r)
   = 4/13*7^(1/2)*R_4^(4)(r) +3/65*1155^(1/2)*R_6^(4)(r).
R_2^(2)(r)*R_4^(4)(r) = 7/11*11^(1/2)*R_2^(2)(r) +4/13*7^(1/2)*R_4^(2)(r) +8/2145*1155^(1/2)*R_6^(2)(r)
   = 11/13*7^(1/2)*R_4^(4)(r) +2/195*1155^(1/2)*R_6^(4)(r)
   = 1/15*1155^(1/2)*R_6^(6)(r).
R_3^(1)(r)*R_3^(1)(r) = 3^(1/2)*R_0^(0)(r) -8/77*7^(1/2)*R_2^(0)(r) +34/143*11^(1/2)*R_4^(0)(r)
    +196/715*15^(1/2)*R_6^(0)(r)
   = 43/77*7^(1/2)*R_2^(2)(r) -14/143*11^(1/2)*R_4^(2)(r) +294/715*15^(1/2)*R_6^(2)(r).
R_3^(1)(r)*R_3^(3)(r) = 4/11*7^(1/2)*R_2^(2)(r) +61/143*11^(1/2)*R_4^(2)(r) +84/715*15^(1/2)*R_6^(2)(r)
   = 54/143*11^(1/2)*R_4^(4)(r) +21/65*15^(1/2)*R_6^(4)(r).
R_3^(3)(r)*R_3^(3)(r) = 3^(1/2)*R_0^(0)(r) +6/11*7^(1/2)*R_2^(0)(r) +24/143*11^(1/2)*R_4^(0)(r)
    +16/715*15^(1/2)*R_6^(0)(r)
   = 9/11*7^(1/2)*R_2^(2)(r) +36/143*11^(1/2)*R_4^(2)(r) +24/715*15^(1/2)*R_6^(2)(r)
   = 9/13*11^(1/2)*R_4^(4)(r) +6/65*15^(1/2)*R_6^(4)(r)
   = 3/5*15^(1/2)*R_6^(6)(r).
R_1^(1)(r)*R_6^(0)(r) = 2/65*975^(1/2)*R_5^(1)(r) +3/85*1275^(1/2)*R_7^(1)(r).
R_1^(1)(r)*R_6^(2)(r) = 3/65*975^(1/2)*R_5^(1)(r) +2/85*1275^(1/2)*R_7^(1)(r)
   = 4/195*975^(1/2)*R_5^(3)(r) +11/255*1275^(1/2)*R_7^(3)(r).
R_1^(1)(r)*R_6^(4)(r) = 11/195*975^(1/2)*R_5^(3)(r) +4/255*1275^(1/2)*R_7^(3)(r)
   = 2/195*975^(1/2)*R_5^(5)(r) +13/255*1275^(1/2)*R_7^(5)(r).
R_1^(1)(r)*R_6^(6)(r) = 1/15*975^(1/2)*R_5^(5)(r) +2/255*1275^(1/2)*R_7^(5)(r)
   = 1/17*1275^(1/2)*R_7^(7)(r).
R_2^(0)(r)*R_5^(1)(r) = 70/429*91^(1/2)*R_3^(1)(r) -2/11*7^(1/2)*R_5^(1)(r)
    +9/221*1547^(1/2)*R_7^(1)(r).
R_2^(0)(r)*R_5^(3)(r) = 15/143*91^(1/2)*R_3^(3)(r) +4/33*7^(1/2)*R_5^(3)(r)
    +22/663*1547^(1/2)*R_7^(3)(r).
R_2^(0)(r)*R_5^(5)(r) = 2/3*7^(1/2)*R_5^(5)(r) +1/51*1547^(1/2)*R_7^(5)(r).
R_2^(2)(r)*R_5^(1)(r) = 28/429*91^(1/2)*R_3^(1)(r) +29/55*7^(1/2)*R_5^(1)(r)
    +18/1105*1547^(1/2)*R_7^(1)(r)
   = 8/429*91^(1/2)*R_3^(3)(r) +24/55*7^(1/2)*R_5^(3)(r) +33/1105*1547^(1/2)*R_7^(3)(r).
R_2^(2)(r)*R_5^(3)(r) = 21/143*91^(1/2)*R_3^(1)(r) +24/55*7^(1/2)*R_5^(1)(r)
    +8/1105*1547^(1/2)*R_7^(1)(r)
```

```
   = 6/143*91^(1/2)*R_3^(3)(r) +107/165*7^(1/2)*R_5^(3)(r) +44/3315*1547^(1/2)*R_7^(3)(r)
   = 4/15*7^(1/2)*R_5^(5)(r) +11/255*1547^(1/2)*R_7^(5)(r).
R_2^(2)(r)*R_5^(5)(r) = 3/13*91^(1/2)*R_3^(3)(r) +4/15*7^(1/2)*R_5^(3)(r) +8/3315*1547^(1/2)*R_7^(3)(r)
   = 13/15*7^(1/2)*R_5^(5)(r) +2/255*1547^(1/2)*R_7^(5)(r)
   = 1/17*1547^(1/2)*R_7^(7)(r).
R_3^(1)(r)*R_4^(0)(r) = 4/33*55^(1/2)*R_1^(1)(r) +34/143*11^(1/2)*R_3^(1)(r)
    -28/2145*143^(1/2)*R_5^(1)(r) +1323/12155*187^(1/2)*R_7^(1)(r).
R_3^(1)(r)*R_4^(2)(r) = 7/33*55^(1/2)*R_1^(1)(r) -14/143*11^(1/2)*R_3^(1)(r)
    +194/2145*143^(1/2)*R_5^(1)(r) +756/12155*187^(1/2)*R_7^(1)(r)
   = 61/143*11^(1/2)*R_3^(3)(r) -12/715*143^(1/2)*R_5^(3)(r) +126/1105*187^(1/2)*R_7^(3)(r).
R_3^(1)(r)*R_4^(4)(r) = 54/143*11^(1/2)*R_3^(3)(r) +79/715*143^(1/2)*R_5^(3)(r)
    +28/1105*187^(1/2)*R_7^(3)(r)
   = 8/65*143^(1/2)*R_5^(5)(r) +7/85*187^(1/2)*R_7^(5)(r).
R_3^(3)(r)*R_4^(0)(r) = 24/143*11^(1/2)*R_3^(3)(r) +84/715*143^(1/2)*R_5^(3)(r)
    +63/1105*187^(1/2)*R_7^(3)(r).
R_3^(3)(r)*R_4^(2)(r) = 2/33*55^(1/2)*R_1^(1)(r) +61/143*11^(1/2)*R_3^(1)(r)
    +184/2145*143^(1/2)*R_5^(1)(r) +216/12155*187^(1/2)*R_7^(1)(r)
   = 36/143*11^(1/2)*R_3^(3)(r) +93/715*143^(1/2)*R_5^(3)(r) +36/1105*187^(1/2)*R_7^(3)(r)
   = 6/65*143^(1/2)*R_5^(5)(r) +9/85*187^(1/2)*R_7^(5)(r).
R_3^(3)(r)*R_4^(4)(r) = 3/11*55^(1/2)*R_1^(1)(r) +54/143*11^(1/2)*R_3^(1)(r)
    +24/715*143^(1/2)*R_5^(1)(r) +48/12155*187^(1/2)*R_7^(1)(r)
   = 9/13*11^(1/2)*R_3^(3)(r) +4/65*143^(1/2)*R_5^(3)(r) +8/1105*187^(1/2)*R_7^(3)(r)
   = 1/5*143^(1/2)*R_5^(5)(r) +2/85*187^(1/2)*R_7^(5)(r)
   = 3/17*187^(1/2)*R_7^(7)(r).
```

Products of two entries of the previous two tables expand products $Z_{n_1,l_1}^{(m_1)} Z_{n_2,l_2}^{(m_2)}$ of two 3D Zernike functions into a sum over 3D Zernike functions by picking lines with l-parameters which match.

IV. SUMMARY

The 2D and 3D Zernike functions are orthogonal basis sets defined in the unit circle and unit sphere, where the specific notation introduced by Noll is the most common standard in 2D, and a more rational (but square-root loaded) standard seems to emerge in 3D. We have demonstrated the transformation of the basis functions between the radial-angular and the centered Cartesian systems for both dimensions.

The applications are numerical field simulations, where the foundation is backed by an isotropy in 2D or 3D space, but followup calculations employ vector field operators which have simpler representations in global Cartesian than in circular or spherical local coordinates.

Acknowledgments

This work is supported by the NWO VICI grant 639.043.201 to A. Quirrenbach, "Optical Interferometry: A new Method for Studies of Extrasolar Planets."

APPENDIX A: NOTATIONS

$(z)_n$	Pochhammer's Symbol, $(z)_0 \equiv 1$, $(z)_n = z(z+1)(z+2)\cdots(z+n-1) = \Gamma(z+n)/\Gamma(z)$ [1, 6.1.22]
${}_2F_1(.,.;.;.)$	Gaussian Hypergeometric Function [1, §15]
${}_.F_.(.,.;.;.)$	generalized Hypergeometric Function [20]
(....|....)	Clebsch-Gordan coefficient [1, 27.9]
$\begin{pmatrix} \cdot & \cdot & \cdot \\ \cdot & \cdot & \cdot \end{pmatrix}$	Wigner's $3j$ coefficient, Section III
$\binom{\cdot}{\cdot}$	binomial coefficient [1, 3.1.2]
$\ldots^*$	complex conjugate
$\lfloor \ldots \rfloor$	floor function, the largest integer not larger than the embraced argument
$j!$	factorial $j \cdot (j-1) \cdot (j-2) \cdots 1$
$j!!$	double factorial $j \cdot (j-2) \cdot (j-4) \cdots = \prod_{s=0}^{\lfloor (j-1)/2 \rfloor} (j-2s)$
`f^(1/2)`	square root of f
a	index excess (4)
α	index excess (43)
b	index mean (4)
φ, `phi`	azimuth angle
f, $\hat{f}$	linearization coefficients (44), (52)
g	linearization coefficient (30)
h	expansion coefficient (5)
i, `i`	imaginary unit
k	expansion coefficient (77)
$P_.^.(.)$	Associated Legendre Polynomial (58) [1, §8]
$P_.^{(.,.)}(.)$	Jacobi Polynomial [1, §22]
`Pi`	π
q	3D radial polynomial group parameter (43)
$R_n^m(.)$, `R_.^.`	Zernike radial polynomial, circular, Section II
$R_n^{(l)}(.)$, `R_.^(.)`	Zernike radial polynomial, spherical, Section III
θ	polar angle, Section III
u	expansion coefficient (65)
x, y, z	Cartesian coordinates (13), (62)
$Y_.^{(.)}$, `Y_.^(.)`	Spherical Harmonics, Section III
$Z_.^.$, `Z_.`	Zernike function, circular, Section II
$Z_{.,.}^{(.)}$, `Z_.,.^(.)`	Zernike function, spherical, Section III

[1] Abramowitz, M., and I. A. Stegun (eds.), 1972, *Handbook of Mathematical Functions* (Dover Publications, New York), 9th edition, ISBN 0-486-61272-4.
[2] Conforti, G., 1983, Opt. Lett. **8**(7), 407.
[3] Dai, G.-m., 1995, J. Opt. Soc. Am. A **12**(10), 2182.
[4] Dai, G.-m., 2006, J. Opt. Soc. Am. A **23**(7), 1657, E: [5].
[5] Dai, G.-m., 2006, J. Opt. Soc. Am. A **23**(11), 2970.
[6] Edmonds, A. R., 1957, *Angular momentum in quantum mechanics* (Princeton University Press), E: the factor $\sqrt{2j_2+1}$ in the denominator of (3.7.3) ought read $\sqrt{2j_3+1}$.
[7] Fano, U., and G. Racah, 1959, *Irreducible tensor sets*, volume 4 of *Pure and Applied Physics* (Academic Press, New York).
[8] Fields, J. L., and J. Wimp, 1961, Math. Comp. **15**(76), 390, in the second line of (2.10), the fraction bar in the argument of ${}_1F_1$ should be removed.
[9] Gradstein, I., and I. Ryshik, 1981, *Summen-, Produkt- und Integraltafeln* (Harri Deutsch, Thun), 1st edition, ISBN 3-87144-350-6.
[10] Kintner, E. C., 1976, Optica Acta **23**(8), 679.
[11] Mak, L., S. Grandison, and R. J. Morris, 2008, J. Mol. Graph. Model. **26**(7), 1035.
[12] Mathar, R. J., 2002, Int. J. Quant. Chem. **90**(1), 227, E: The big slash in the square root of (2.3) is to be removed. In (3.5), $x^{\sigma_1} y^{\sigma_2} z^{\sigma_3}$ should read $x^{2\sigma_1} y^{2\sigma_2} z^{2\sigma_3}$. In (3.7), the lower limits should be $\sigma_1, \sigma_2 \geq 0$, and a factor $2^{1/2-m}$ is to be added to the right hand side.
[13] Mathar, R. J., 2007, arXiv:0705.1329 [math.NA] .
[14] Mathar, R. J., 2008, arXiv:0805.3979 [astro-ph] .
[15] Messiah, A., 1976, *Quantenmechanik*, volume 1 (Walter de Gruyter, Berlin, New York), ISBN 3-11-003686-X.
[16] Noll, R. J., 1976, J. Opt. Soc. Am. **66**(3), 207.

[17] Novotni, M., and R. Klein, 2004, Computer-Aided Design **36**(11), 1047.
[18] Prata, A., Jr., and W. V. T. Rusch, 1989, Appl. Opt. **28**(4), 749.
[19] Sánchez-Ruiz, J., and J. S. Dehesa, 1997, J. Comp. Appl. Math. **89**(1), 155.
[20] Slater, L. J., 1966, *Generalized Hypergeometric Functions* (Cambridge University Press).
[21] Srivastava, H. M., 1988, J. Phys. A: Math. Gen. **21**(23), 4463.
[22] Tango, W. J., 1977, Appl. Phys. A **13**(4), 327.
[23] Tyson, R. K., 1982, Opt. Lett. **7**(6), 262.
[24] Whipple, F. J. W., 1926, Proc. Lond. Math. Soc. **25**(2), 525.